


NJM3415

The NJM3415 integrated circuit is a high gain, high output current, high output voltage swing dual operational amplifier capable of driving 70mA.

Absolute Maximum Ratings (Ta=25°C)

Supply Voltage	V^+ (V^+ / V^-)	15V (or $\pm 7.5V$)
Differential Input Voltage	V_{ID}	15V
Input Voltage	V_I	$-0.3 \sim +15V$
Power Dissipation	P_D (D-Type)	500mW
	(M-Type)	300mW
	(L-Type)	800mW
Operating Temperature Range	T_{opr}	$-20 \sim +75^\circ C$
Storage Temperature Range	T_{stg}	$-40 \sim +125^\circ C$


Package Outline



NJM3415D



NJM3415M




NJM3415L


Electrical Characteristics (Ta=25°C, $V^+ = 8.6V$)

Parameter	Symbol	Test Condition	Min.	Typ.	Max.	Unit
Input Offset Voltage	V_{IO}	$R_S = 0\Omega$	—	2	5	mV
Input Offset Current	I_{IO}		—	± 30	± 100	nA
Input Bias Current	I_B		—	100	500	nA
Large Signal Voltage Gain	A_v	$R_L = 2k\Omega$	88	100	—	dB
Input Common Mode Voltage Range	V_{ICM}		$V^+ - 2$	—	—	V
Maximum Output Voltage Swing 1	V_{OM1}	$R_L \geq 2k\Omega, V^+ = 5V$	3.5	—	—	V
Maximum Output Voltage Swing 2	V_{OM2}	$I_O = 70mA, V^+ = 5V$	3.2	—	—	V
Common Mode Rejection Ratio	CMR		80	90	—	dB
Supply Voltage Rejection Ratio	SVR		80	90	—	dB
Supply Current	I_{CC}	$R_L = \infty$	4.5	5.5	7.0	mA
Slew Rate	SR		—	1.0	—	V/ μS
Unity Gain Bandwidth	GB		—	1.3	—	MHz
Operating Voltage Range	V^+		—	—	10	V

Equivalent Circuit (1/2 Shown)




Connection Diagrams



PIN FUNCTION

1. OUTPUT
2. A-INPUT
3. A+INPUT
4. GND
5. B+INPUT
6. B-INPUT
7. B OUTPUT
8. V^+



■ Typical Characteristics

2

