



44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

## NTE2090

### Integrated Circuit

### 7-Channel Transistor Array

#### **Description:**

The NTE2090 is an integrated circuit in a 16-Lead DIP type package comprised of six NPN low saturation drivers. All units feature integral clamp diodes for switching inductive loads and protective diodes for protection against a negative input voltage.

#### **Features:**

- Low Saturation Outputs:  
 $V_{CE(sat)} = 0.6V$  Max @  $I_{OUT} = 120mA$
- Output Rating:  
20V/150mA
- Output Clamp Diodes
- CMOS and PMOS Compatable Inputs
- Input Protection Diodes

#### **Absolute Maximum Ratings:** ( $T_A = +25^\circ C$ unless otherwise specified)

Supply Voltage, $V_{CC}$ .....	-0.5V to +20V
Output Sustaining Voltage, $V_{CE(sus)}$ .....	-0.5V to $V_{CC} + 0.5V$
Output Current, $I_{OUT}$ .....	150mA
Input Voltage, $V_{IN}$ .....	-37V to +20V
Input Current, $I_{IN}$ .....	1.5mA
Clamp Diode Reverse Voltage, $V_R$ .....	20V
Clamp Diode Forward Current, $I_F$ .....	120mA
GND Pin Current, $I_{GND}$ .....	800mA
Power Dissipation, $P_D$ .....	1W
Operating Temperature Range, $T_{opr}$ .....	-40° to +85°C
Storage Temperature Range, $T_{stg}$ .....	-55° to +150°C

#### **Recommended Operating Conditions:** ( $T_A = -40^\circ$ to +85°C unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Voltage	$V_{CC}$		4.75	—	18	V
Output Current	$I_{OUT}$		0	—	120	mA
		$T_{PW} = 25ms, D_F = 10\% \text{ 7 Circuits}$	0	—	100	mA
Input Voltage	$V_{IN}$		-35	—	$V_{CC}$	V
Clamp Diode Reverse Voltage	$V_R$		—	—	18	V
Clamp Diode Forward Voltage	$I_F$		—	—	120	mA
Power Dissipation	$P_D$		—	—	0.36	W

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Output Leakage Current	$I_{CEX}$	$V_{CC} = 18\text{V}$ , $V_{OUT} = 18\text{V}$ , $T_A = +75^\circ\text{C}$	—	—	100	$\mu\text{A}$
Output Saturation Voltage	$V_{CE(\text{sat})}$	$V_{CC} = 5\text{V}$ , $I_{IN} = 0.2\text{mA}$ , $I_{OUT} = 120\text{mA}$	—	0.45	0.6	$\text{V}$
DC Forward Current Transfer Ratio	$h_{FE}$	$V_{CC} = 5\text{V}$ , $V_{OUT} = 2\text{V}$ , $I_{OUT} = 120\text{mA}$	1000	—	—	
Input Current Output ON	$I_{IN(\text{ON})}$	$V_{IN} = 5\text{V}$ , $I_{OUT} = 120\text{mA}$	—	0.16	0.23	$\text{mA}$
		$V_{IN} = 15\text{V}$ , $I_{OUT} = 120\text{mA}$	—	0.66	0.94	$\text{mA}$
Output OFF	$I_{IN(\text{OFF})}$	$V_{IN} = -35\text{V}$	—	—	-10	$\mu\text{A}$
Clamp Diode Forward Voltage	$V_F$	$I_F = 120\text{mA}$	—	1.25	1.6	$\text{V}$
Supply Current Output ON	$I_{CC(\text{ON})}$	$V_{CC} = V_{IN} = 5\text{V}$	—	4	6	$\text{mA}/\text{Gate}$
		$V_{CC} = V_{IN} = 15\text{V}$	—	14	22	
Output OFF	$I_{CC(\text{OFF})}$	$V_{CC} = 18\text{V}$ , $V_{IN} = 0\text{V}$	—	—	10	$\mu\text{A}$
Turn-On Delay	$t_{ON}$	$V_{CC} = 18\text{V}$ , $R_L = 150\Omega$ , $C_L = 15\text{pF}$	—	0.1	—	$\mu\text{s}$
Turn-Off Delay	$t_{OFF}$		—	0.8	—	$\mu\text{s}$

Pin Connection Diagram

