

The RF MOSFET Line

RF Power Field-Effect Transistor


N-Channel Enhancement-Mode Lateral MOSFET

Designed for broadband commercial and industrial applications with frequencies from 470 to 860 MHz. The high gain and broadband performance of this device make it ideal for large-signal, common source amplifier applications in 32 volt digital television transmitter equipment.

- Typical Broadband DVBT OFDM Performance @ 470–860 MHz, 32 Volts, $I_{DQ} = 2.0$ A, 8K Mode, 64 QAM
 - Output Power — 45 Watts Avg.
 - Power Gain ≥ 16.7 dB
 - Efficiency $\geq 21\%$
 - ACPR ≤ -58 dBc
- Typical Broadband ATSC 8VSB Performance @ 470–860 MHz, 32 Volts, $I_{DQ} = 2.0$ A
 - Output Power — 80 Watts Avg.
 - Power Gain ≥ 16.5 dB
 - Efficiency $\geq 27.5\%$
 - IMD ≤ -31.3 dBc
- Internally Input and Output Matched for Ease of Use
- Integrated ESD Protection
- Capable of Handling 10:1 VSWR, @ 32 Vdc, 860 MHz, 45 Watts DVBT OFDM Output Power
- Excellent Thermal Stability
- Characterized with Series Equivalent Large-Signal Impedance Parameters
- Available in Tape and Reel. R3 Suffix = 250 Units per 56 mm, 13 inch Reel. R5 Suffix = 50 Units per 56 mm, 13 inch Reel.

MRF377
MRF377R3
MRF377R5

470 – 860 MHz, 240 W, 32 V
LATERAL N-CHANNEL
RF POWER MOSFET



CASE 375G-04, STYLE 1
NI-860C3

MAXIMUM RATINGS ⁽¹⁾

Rating	Symbol	Value	Unit
Drain-Source Voltage	V_{DSS}	65	Vdc
Gate-Source Voltage	V_{GS}	– 0.5, +15	Vdc
Drain Current – Continuous	I_D	17	Adc
Total Device Dissipation @ $T_C = 25^\circ\text{C}$ Derate above 25°C	P_D	486 2.78	W W/ $^\circ\text{C}$
Storage Temperature Range	T_{stg}	– 65 to +150	$^\circ\text{C}$
Operating Junction Temperature	T_J	200	$^\circ\text{C}$

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	0.36	$^\circ\text{C/W}$

ESD PROTECTION CHARACTERISTICS

Test Conditions	Class
Human Body Model	1 (Minimum)
Machine Model	M3 (Minimum)
Charge Device Model	7 (Minimum)

(1) Each side of device measured separately.

NOTE – CAUTION – MOS devices are susceptible to damage from electrostatic charge. Reasonable precautions in handling and packaging MOS devices should be observed.

REV 0

Freescale Semiconductor, Inc.

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS ⁽¹⁾					
Drain–Source Breakdown Voltage (V _{GS} = 0 Vdc, I _D = 10 μA)	V _{(BR)DSS}	65	—	—	Vdc
Zero Gate Voltage Drain Current (V _{DS} = 32 Vdc, V _{GS} = 0 Vdc)	I _{DSS}	—	—	1	μAdc
Gate–Source Leakage Current (V _{GS} = 5 Vdc, V _{DS} = 0 Vdc)	I _{GSS}	—	—	1	μAdc
ON CHARACTERISTICS ⁽¹⁾					
Gate Threshold Voltage (V _{DS} = 10 Vdc, I _D = 200 μA)	V _{GS(th)}	—	2.8	—	Vdc
Gate Quiescent Voltage (V _{DS} = 32 Vdc, I _D = 225 mA)	V _{GS(Q)}	—	3.5	—	Vdc
Drain–Source On–Voltage (V _{GS} = 10 Vdc, I _D = 3 A)	V _{DS(on)}	—	0.27	—	Vdc
DYNAMIC CHARACTERISTICS ⁽¹⁾					
Reverse Transfer Capacitance (V _{DS} = 28 Vdc, V _{GS} = 0, f = 1 MHz)	C _{rss}	—	3.2	—	pF
FUNCTIONAL CHARACTERISTICS (In DVBT OFDM Single–Channel, Narrowband Fixture, 50 ohm system) ⁽²⁾					
Common Source Power Gain (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA, f = 860 MHz)	G _{ps}	16.5	18.2	—	dB
Drain Efficiency (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA, f = 860 MHz)	η	21	22.9	—	%
Adjacent Channel Power Ratio (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA, f = 860 MHz)	ACPR	—	–59.2	–57	dBc
TYPICAL CHARACTERISTICS (In DVBT OFDM Single–Channel, Broadband Fixture, 50 ohm system) ⁽²⁾					
Common Source Power Gain (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	G _{ps}	— — — — —	17.6 17.6 17.4 17.4 16.8	— — — — —	dB
Drain Efficiency (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	η	— — — — —	23.5 25.8 23.0 22.7 21.3	— — — — —	%
Adjacent Channel Power Ratio (V _{DD} = 32 Vdc, P _{out} = 45 W Avg., I _{DQ} = 2 x 1000 mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	ACPR	— — — — —	–59.3 –59.3 –58.7 –58.7 –58.1	— — — — —	dBc

(1) Each side of device measured separately.

(2) Measured in push–pull configuration.

Freescale Semiconductor, Inc.

TYPICAL CHARACTERISTICS (In ATSC 8VSB Single-Channel, Broadband Fixture, 50 ohm system)⁽²⁾

Characteristic	Symbol	Min	Typ	Max	Unit
Common Source Power Gain ($V_{DD} = 32$ Vdc, $P_{out} = 80$ W Avg., $I_{DQ} = 2 \times 1000$ mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	G_{ps}	— — — — —	17.5 17.5 17.2 17.2 16.6	— — — — —	dB
Drain Efficiency ($V_{DD} = 32$ Vdc, $P_{out} = 80$ W Avg., $I_{DQ} = 2 \times 1000$ mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	η	— — — — —	31.0 34.3 30.1 29.6 27.8	— — — — —	%
Intermodulation Distortion ($V_{DD} = 32$ Vdc, $P_{out} = 80$ W Avg., $I_{DQ} = 2 \times 1000$ mA) f = 470 MHz f = 560 MHz f = 660 MHz f = 760 MHz f = 860 MHz	IMD	— — — — —	31.7 32.7 32.9 34.2 35.4	— — — — —	dBc

(2) Measured in push-pull configuration.

Freescale Semiconductor, Inc.

Table 1. 845–875 MHz Narrowband Test Circuit Component Designations and Values

Part	Description	Value, P/N or DWG	Manufacturer
B1, B2	Ferrite Beads, Surface Mount, 11 Ω (0805)	2508051107Y0	Fair-Rite
Balun 1, Balun 2	0.8–1GHz Xinger Balun	3A412	Anaran
C1	33 pF Chip Capacitor (0805)	08055J330JBT	AVX / Kyocera
C2	2.7 pF Chip Capacitor (0603)	06035J2R7BBT	AVX / Kyocera
C3	12 pF Chip Capacitor (0805)	08051J120GBT	AVX / Kyocera
C4, C5	6.8 pF Chip Capacitors (0805)	08051J6R8BBT	AVX / Kyocera
C6	2.7 pF Chip Capacitor (0805)	0805J2R7BBT	AVX / Kyocera
C7, C8, C9, C10	3.3 pF Chip Capacitors (0805)	08051J3R3BBT	AVX / Kyocera
C11, C12	2.2 μ F, 50 V Chip Capacitors	C1825C225J5RAC3810	Kemet
C13, C14, C15, C16	0.01 μ F, 100 V Chip Capacitors	C1825C103J1GAC	Kemet
C17, C18	0.56 μ F, 50 V Chip Capacitors	C1825C564J5RAC	Kemet
C19, C20	10 μ F, 50 V Tantalum Chip Capacitors	522Z050/100MTRE	Tecate
C21, C22, C23, C24	47 μ F, 16 V Tantalum Chip Capacitors	TPSD476K016R0150	AVX / Kyocera
C25, C26	470 μ F, 63 V Electrolytic Capacitors	NACZF471M63V (18x22)	Nippon
L1	12 nH Inductor (0603)	0603HC-12NXJB	CoilCraft
L2	7.15 nH Inductor	1606-7	CoilCraft
L3, L4	10 nH Inductor (0603)	0603HC-10NXJB	CoilCraft
R1, R2	24 Ω , 1/8 W, 5% Chip Resistors (1206)		
WB1, WB2, WB3, WB4	Brass Wear Shims		
PCB	Arlon 30 mil, $\epsilon_r = 2.56$	DS1152	DS Electronics




Figure 1. 845–875 MHz Narrowband Test Circuit Component Layout

Freescale Semiconductor, Inc.

TYPICAL NARROWBAND CHARACTERISTICS




Figure 2. Two-Tone Power Gain versus Output Power




Figure 3. Third Order Intermodulation Distortion versus Output Power




Figure 4. Intermodulation Distortion Products versus Output Power




Figure 5. Two-Tone Drain Efficiency versus Output Power





Figure 6. Power Gain, Efficiency and IMD versus Output Power



$V_{DD} = 32 \text{ V}$, $I_{DQ} = 2 \times 1000 \text{ mA}$, $P_{out} = 45 \text{ W Avg.}$, DVB-T OFDM

f MHz	Z_{source} Ω	Z_{load} Ω
845	$4.66 - j5.90$	$8.59 - j4.22$
860	$4.38 - j5.64$	$9.36 - j4.95$
875	$3.93 - j5.33$	$9.39 - j6.06$

Z_{source} = Test circuit impedance as measured from gate to gate, balanced configuration.

Z_{load} = Test circuit impedance as measured from drain to drain, balanced configuration.





Figure 7. 845–875 MHz Narrowband Series Equivalent Input and Output Impedance

Freescale Semiconductor, Inc.

Table 2. 470—860 MHz Broadband Test Circuit Component Designations and Values

Part	Description	Value, P/N or DWG	Manufacturer
B1, B2	Ferrite Beads, Surface Mount, 30 Ω (0603)	2506033007Y0	Fair-Rite
Balun 1, Balun 2	Rogers 3.006, $\epsilon_r = 6.06$, 1 oz Cu	DS1046	DS Electronics
C1	12 pF Chip Capacitor (0603)	06035J120GBT	AVX / Kyocera
C2, C5	12 pF Chip Capacitors (0805)	08051J120GBT	AVX / Kyocera
C3	3.9 pF Chip Capacitor (0805)	08051J3R9BBT	AVX / Kyocera
C4, C7, C12, C15, C17	8.2 pF Chip Capacitors (0805)	08051J8R2BBT	AVX / Kyocera
C6	3.3 pF Chip Capacitor (0805)	08051J3R3BBT	AVX / Kyocera
C8	0.4–2.5 pF Variable Capacitor	27283PC	Gigatronics
C9, C10	3.3 pF Chip Capacitors (0603)	06035J3R3BBT	AVX / Kyocera
C11, C14	10 pF Chip Capacitor (0805)	08051J100GBT	AVX / Kyocera
C13	4.7 pF Chip Capacitor (0805)	08051J4R7BBT	AVX / Kyocera
C16	2.2 pF Chip Capacitor (0603)	06035J2R2BBT	AVX / Kyocera
C18	2.2 pF Chip Capacitor (0805)	08051J2R2BBT	AVX / Kyocera
C19, C20, C21, C22	47 μ F, 16 V Tantalum Chip Capacitors	TPSD476K016R0150	AVX
C23, C26	2.2 μ F, 50 V Ceramic Chip Capacitors	C1825C225J5RAC3810	Kemet
C24, C25, C27, C29	0.01 μ F, 100 V Ceramic Chip Capacitors	C1825C103J1GAC	Kemet
C28, C30	0.56 μ F, 50 V Ceramic Chip Capacitors	C1825C564J5GAC	Kemet
C31, C32	10 μ F, 50 V Chip Capacitors	522Z–050/100MTRE	Tecate
C33, C34	470 μ F, 63 V Electrolytic Capacitors	SME63VB471M12X25LL	United Chemi-Con
L1, L2	15 nH Inductors (0603)	L0603150GGW003	AVX
L3, L4	12 nH Inductors (0603)	0603HC–12NHJBU	CoilCraft
L5, L6	8 nH Coil Inductors	A03T–5	CoilCraft
L7	22 nH Coil Inductor	B07T–5	CoilCraft
L8	18.5 nH Coil Inductor	A05T–5	CoilCraft
R1, R2	12.1 Ω , 1/16 W, 1% Chip Resistors (0603)		
PCB Gate, PCB Drain	PCB Motherboard w/Integrated Daughterboard, Rogers 3003, $\epsilon_r = 3.03$, 0.5 oz Cu	DS1047	DS Electronics



Multilayer Balun Mounting Detail




Figure 8. 470–860 MHz Broadband Test Circuit Component Layout

Freescale Semiconductor, Inc.

TYPICAL DVBT OFDM BROADBAND CHARACTERISTICS




Figure 9. Single-Channel DVBT OFDM Broadband Performance




Figure 10. Single-Channel DVBT OFDM Broadband Performance Power Gain versus Output Power




Figure 11. Single-Channel DVBT OFDM Broadband Performance Drain Efficiency versus Output Power




Figure 12. Single-Channel DVBT OFDM Broadband Performance Adjacent Channel Power Ratio versus Output Power




Figure 13. 8K Mode DVBT OFDM Spectrum

Freescale Semiconductor, Inc.

TYPICAL ATSC 8VSB BROADBAND CHARACTERISTICS




Figure 14. Single-Channel ATSC 8VSB Broadband Performance




Figure 15. Single-Channel ATSC 8VSB Broadband Performance Power Gain versus Output Power




Figure 16. Single-Channel ATSC 8VSB Broadband Performance Drain Efficiency versus Output Power




Figure 17. Single-Channel ATSC 8VSB Broadband Performance Adjacent Channel Power Ratio versus Output Power





Figure 18. ATSC 8VSB Spectrum

Freescale Semiconductor, Inc.



Optimized for $V_{DD} = 32$ V, $I_{DQ} = 2 \times 1000$ mA, $P_{out} = 45$ W Avg., DVBT OFDM

f MHz	Z_{source} Ω	Z_{load} Ω
470	$5.79 - j2.40$	$6.21 - j1.69$
560	$6.63 - j2.63$	$5.66 - j1.12$
660	$6.57 - j4.03$	$6.76 - j1.00$
760	$6.67 - j4.55$	$6.57 - j1.91$
860	$5.34 - j6.28$	$7.37 - j5.45$

Z_{source} = Test circuit impedance as measured from gate to gate, balanced configuration.

Z_{load} = Test circuit impedance as measured from drain to drain, balanced configuration.





Figure 19. 470—860 MHz Broadband Series Equivalent Input and Output Impedance

Freescal Semiconductor, Inc.


PACKAGE DIMENSIONS



- NOTES:
1. CONTROLLING DIMENSION: INCH.
 2. INTERPRET DIMENSIONS AND TOLERANCES PER ASME Y14.5M-1994.
 3. DIMENSION H TO BE MEASURED 0.030 (0.762) AWAY FROM PACKAGE BODY.
 4. RECOMMENDED BOLT CENTER DIMENSION OF 1.140 (28.96) BASED ON 3M SCREW.

	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	1.335	1.345	33.91	34.16
B	0.380	0.390	9.65	9.91
C	0.180	0.224	4.57	5.69
D	0.325	0.335	8.26	8.51
E	0.060	0.070	1.52	1.78
F	0.004	0.006	0.10	0.15
G	1.100 BSC		27.94 BSC	
H	0.097	0.107	2.46	2.72
J	0.2125 BSC		5.397 BSC	
K	0.135	0.165	3.43	4.19
L	0.425 BSC		10.8 BSC	
M	0.852	0.868	21.64	22.05
N	0.851	0.869	21.62	22.07
Q	0.118	0.138	3.00	3.30
R	0.395	0.405	10.03	10.29
S	0.394	0.406	10.01	10.31
bbb	0.010 REF		0.25 REF	
ccc	0.015 REF		0.38 REF	

STYLE 1:
 PIN 1. DRAIN
 2. DRAIN
 3. GATE
 4. GATE
 5. SOURCE



**CASE 375G-04
 ISSUE E
 NI-860C3**

Information in this document is provided solely to enable system and software implementers to use Motorola products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part.

MOTOROLA and the Stylized M Logo are registered in the US Patent and Trademark Office. All other product or service names are the property of their respective owners. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

© Motorola Inc. 2003

HOW TO REACH US:

USA/EUROPE/LOCATIONS NOT LISTED:
 Motorola Literature Distribution
 P.O. Box 5405, Denver, Colorado 80217
 1-800-521-6274 or 480-768-2130

JAPAN: Motorola Japan Ltd.; SPS, Technical Information Center,
 3-20-1, Minami-Azabu, Minato-ku, Tokyo 106-8573, Japan
 81-3-3440-3569

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Centre,
 2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong
 852-2668334

HOME PAGE: <http://motorola.com/semiconductors>



MOTOROLA

**For More Information On This Product,
 Go to: www.freescale.com**

MRF377/D