

PBMPLS-RM Series

500-5000 WATTS DC/AC INVERTER

Features

- True sinewave waveform.
- Massive inrush and overload capability.
- Galvanically isolated.
- High efficiency toroidal transformer.
- DC circuit breaker/ BATT isolator switch
- Rack mounted design.
- LED status indicators.



Specifications

INPUT

Voltage	12, 24, 48, 96, 120 (Standard). 36, 72, and others (Also available).
---------	--

Voltage range	-20% to +45% of nominal.
---------------	--------------------------

OUTPUT

Voltage	230Vac ±4% (Standard). 110Vac ±4% (Option).
---------	---

Frequency	50/60Hz ±0.1
-----------	--------------

Output waveform	True sinewave < 4% THD.
-----------------	-------------------------

Power factor correction	All conditions.
-------------------------	-----------------

Crest factor	>4
--------------	----

Load start sensitivity	0-20W
------------------------	-------

DC to AC isolation	3500V
--------------------	-------

Over-load protection	Yes.
----------------------	------

Over-temperature protection	Yes.
-----------------------------	------

Short circuit protection	Yes.
--------------------------	------

BATT under and over voltage protection	Yes.
--	------

OPERATING

AC Outlet	Screw terminal junction box.
-----------	------------------------------

Battery Leads	Heavy duty low loss battery leads.
---------------	------------------------------------

Dimensions	19", 3RU x 350mm (D) – all models.
------------	------------------------------------

Cooling	Thermostatically controlled 2-speed fan.
---------	--

STANDARDS AND APPROVALS

Safety standards	AS3100, AS3000
------------------	----------------

C-tick	AS/NZS CISPR14, AS/NZS 1044
--------	-----------------------------

EMC standards	AS2279, AS3000, AS3100 and EN55014
---------------	------------------------------------

ENVIRONMENTAL

Temperature Range	-10°C to 50°C, derate above 40°C by 10%
-------------------	---

Options

CODE ADD OPTION TO THE END OF INVERTER PART NUMBER

L	Alarm output – Voltage free contacts.
---	---------------------------------------

O	Transfer alarm.
---	-----------------

KX	Automatic AC transfer switch with voltage sensing.
----	--

V	110Vac output.
---	----------------

J	Psophometric noise to ETS 3000132-2 (Available only on 48Vdc, 1800W to 3500W models)
---	--

B	High voltage isolation 2kV AC RMS 1 minute
---	--

D	RCD/Earth leakage
---	-------------------

G	Mil spec conformal coating
---	----------------------------

R	Ruggedisation for high vibration environment.
---	---

H	Frequency 60Hz
---	----------------

L	"AC OK" alarm relay contact
---	-----------------------------

C	Twin switched GPO
---	-------------------

D	Twin switched RCD GPO
---	-----------------------

Anderson 175 Amp connectors battery leads

Anderson 120 Amp connectors battery leads

Anderson 75 Amp connectors battery leads

PBMPLS-RM Series

500-5000 WATTS DC/AC INVERTER

Selection Table

MODEL NUMBER	DC INPUT	INPUT RANGE	CONT. RATING	½ HOUR RATING	SURGE 5 SEC PEAK	EFF%	WEIGHT
PBMPLS-12U-RM	12V	10-17V	500W	550W	1500W	90%	7KG
PBMPLS-24X-RM	24V	21-34V	600W	750W	2000W	92%	7KG
PBMPLS-48X-RM	48V	42-68V	600W	750W	2000W	93%	7KG
PBMPLS-96X-RM	96V	80-140V	600W	750W	2000W	93%	7KG
PBMPLS-120X-RM	120V	96-160V	600W	750W	2000W	93%	7KG
PBMPLS-12W-RM	12V	10-17V	1000W	1150W	3000W	91%	12KG
PBMPLS-24V-RM	24V	21-34V	1200W	1600W	3600W	92%	12KG
PBMPLS-48V-RM	48V	42-68V	1200W	1600W	3600W	94%	12KG
PBMPLS-96V-RM	96V	80-140V	1200W	1600W	3600W	94%	12KG
PBMPLS-120V-RM	120V	96-160V	1200W	1600W	3600W	94%	12KG
PBMPLS-12V-RM	12V	10-17V	1500W	1600W	4500W	91%	16KG
PBMPLS-24I-RM	24V	21-34V	1800W	2200W	5400W	94%	16KG
PBMPLS-48I-RM	48V	42-68V	1800W	2200W	5400W	94%	16KG
PBMPLS-96I-RM	96V	80-140V	1800W	2200W	5400W	94%	16KG
PBMPLS-120I-RM	120V	96-160V	1800W	2200W	5400W	94%	16KG
PBMPLS-12I-RM	12V	10-17V	2000W	2200W	6000W	90%	22KG
PBMPLS-24IA-RM	24V	21-34V	2300W	2800W	7000W	94%	22KG
PBMPLS-48IA-RM	48V	42-68V	2500W	3000W	7500W	94%	22KG
PBMPLS-96IA-RM	96V	80-140V	2500W	3000W	7500W	94%	22KG
PBMPLS-120IA-RM	120V	96-160V	2500W	3000W	7500W	94%	22KG
PBMPLS-24Z-RM	24V	21-34V	3000W	3700W	9000W	93%	24KG
PBMPLS-48Z-RM	48V	42-68V	3500W	4100W	10500W	94%	24KG
PBMPLS-96Z-RM	96V	80-140V	3500W	4100W	10500W	94%	24KG
PBMPLS-120Z-RM	120V	96-160V	3500W	4100W	10500W	95%	24KG
PBMPLS-48ZC-RM	48V	42-68V	5000W	6000W	15000W	95%	30KG