

## FEATURES

- **Audio Input/Output**
  - Three Synchronous Serial Audio Inputs (Six Channels)
  - Two Synchronous Serial Audio Outputs (Four Channels)
  - Input and Output Data Formats: 16-, 20-, or 24-Bit Data Left, Right, and I<sup>2</sup>S
  - SPDIF Transmitter
  - $64 \times F_s$  Bit Clock Rate
  - $512 \times F_s$  XTAL Input for Master-Mode Clock Rates
  - $256 \times F_s$  MCLKIN for Slave-Mode Clock Rates
  - Ten Multiplexed Stereo Analog Inputs Selectable Into One Stereo ADC and Three Stereo Line Outputs
    - High-Quality 93 dB DNR (Typical) ADC Channel Performance (Two Channels)
    - A Single Ended Analog Stereo Line Driver Output With 1 of 11 Selectable Inputs, 10-k $\Omega$ , 100-pF Drive Capability (Typical Output Level: 1-V RMS)
  - Three Stereo Audio DACs
    - High-Quality 96-dB DNR (Typical) DAC Channel Performance (Six Channels)
    - Stereo Headphone Amplifier – 24 mW Power Output Into 16  $\Omega$ , 100 pF
- **Audio Digital Signal Processor**
  - Programmable Functionality
  - 135-MHz Operation
  - 48-Bit Data Path With 76-Bit Accumulator
  - Hardware Single Cycle Multiplier ( $28 \times 48$ )
  - Two Memory Loads and One Memory Store Per Cycle
  - Usable 768 Data RAM Words (48 Bit), Usable 1K Coefficient RAM (28 Bit)
  - Usable 2.5K Program RAM
  - 360 mS @ 48KHz, 17280 Words 24-Bit Delay Memory for Video Sync
- **System Control Processor**
  - Embedded 8051 WARP Microprocessor
  - Programmable Using Standard 8051 C Compilers
  - 16K Words of Program RAM (8 Bit)
  - Programmable Using Standard 8051 C Compilers
  - 2048 Words of Data RAM (8 Bit)
  - 256 Words of Internal RAM (8 Bit)
  - Programmable Functionality
- **General Features**
  - Easy to Use Control Interface
  - I<sup>2</sup>C Serial Control Master and Slave Interface
  - Control Interface Operational Without External MCLK Input
  - Single 3.3-V Power Supply
  - Integrated Regulators
  - 100-Pin TQFP Package




Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

# TAS3208

## DIGITAL AUDIO PROCESSOR WITH ANALOG INTERFACE

SLES201A–JANUARY 2007–REVISED FEBRUARY 2007



## DESCRIPTION/ORDERING INFORMATION

The TAS3208 is an audio SOC designed for digital TV Audio Systems and Mini/Micro Component applications. TAS3208 has a programmable audio DSP that preserves high-quality audio by using a 48-bit data path, 28-bit filter coefficients, and a single-cycle 28 times 48-bit multiplier. The programmability feature allows users to customize features in the DSP RAM.

The TAS3208 is composed of seven functional blocks.


- Clock and Serial Data Interface
- Analog Input and Output
- 8051 WARP Controller, Serial Control Interface and Device Control
- Audio DSP – Digital Audio Processing
- Power Supply
- Internal References

## ORDERING INFORMATION

T <sub>A</sub>	PACKAGE <sup>(1)</sup>		ORDERABLE PART NUMBER	TOP-SIDE MARKING
–40°C to 85°C	TQFP – YZP	TBD	TAS3208YZPR	TBD

(1) Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at [www.ti.com/sc/package](http://www.ti.com/sc/package).

# BLOCK DIAGRAM



### TYPICAL APPLICATIONS

The TAS3208 may be used with an external Asynchronous Sample Rate Converter (ASRC) to accommodate asynchronous serial inputs at different sampling rates. An example of this is shown in the block diagram of Figure 2.2.




Figure 1. TAS3208 and interface to external ASRC

## ABSOLUTE MAXIMUM RATINGS<sup>(1)</sup>

over operating free-air temperature range (unless otherwise noted)

		MIN	MAX	UNIT
$D_{VDD}$	Supply voltage range	–0.5	3.8	V
$A_{VDD}$	Supply voltage range	–0.5	3.8	V
$V_I$	Input voltage range	3.3-V TTL	–0.5 $V_{DDS} + 0.5$	V
		3.3-V analog	–0.5 $A_{VDDS} + 0.5$	
		1.8-V LVCMOS	–0.5 $A_{VDD} + 0.5^{(2)}$	
$V_O$	Voltage range applied to any output in the high-impedance or power-off state	3.3-V TTL	–0.5 $V_{DDS} + 0.5$	V
		3.3-V analog	–0.5 $A_{VDDS} + 0.5$	
		1.8-V LVCMOS	–0.5 $D_{VDD} + 0.5^{(3)}$	
		1.8-V LVCMOS	–0.5 $A_{VDD} + 0.5^{(4)}$	
$I_{IK}$	Input clamp current	$V_I < 0$ or $V_I > D_{VDD}$	±20	mA
$I_{OK}$	Output clamp current	$V_O < 0$ or $V_O > D_{VDD}$	±20	mA
$T_{stg}$	Storage temperature range	–65	150	°C
	Lead temperature 1,6 mm (1/16 in) from case for 10 s		260	°C

- (1) Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- (2)  $A_{VDD}$  is an internal 1.8-V supply derived from a regulator in the CXD9890Q chip. Pin XTALI is the only CXD9890Q input that is referenced to this 1.8-V logic supply. The absolute maximum rating listed is for reference; only a crystal should be connected to XTALI.
- (3)  $D_{VDD}$  is an internal 1.8-V supply derived from regulators in the CXD9890Q chip.  $D_{VDD}$  is routed to – DVDD\_BYPASS\_CAP – to provide access to external filter capacitors, but should not be used to source power to external devices.
- (4) Pin XTALO is the only CXD9890Q output that is derived from the internal 1.8-V logic supply  $A_{VDD}$ . The absolute maximum rating listed is for reference; only a crystal should be connected to XTALO.  $A_{VDD}$  is also routed to – AVDD\_BYPASS\_CAP – to provide access to external filter capacitors, but should not be used to source power to external devices.

## RECOMMENDED OPERATING CONDITIONS

			MIN	NOM	MAX	UNIT
D <sub>VDD</sub>	Digital supply voltage		3.0	3.3	3.6	V
A <sub>VDD</sub>	Analog supply voltage	3.3-V analog	3.0	3.3	3.6	V
V <sub>IH</sub>	High-level input voltage	3.3-V TTL	2.0			V
		1.8-V LVCMOS (XTL_IN)	1.26		1.95	
V <sub>IL</sub>	Low-level input voltage	3.3-V TTL			0.8	V
		1.8-V LVCMOS (XTL_IN)			0.54	
T <sub>A</sub>	Operating ambient air temperature (ensuring Parametric)		−20	25	70	°C
T <sub>J</sub>	Operating junction temperature		−20		105	°C

## ELECTRICAL CHARACTERISTICS

over recommended operating conditions (unless otherwise noted)

PARAMETER			TEST CONDITIONS	MIN	MAX	UNIT
$V_{OH}$	High-level output voltage	3.3-V TTL	$I_{OH} = -4 \text{ mA}$	2.4		V
		1.8-V LVCMOS (XTL_OUT)	$I_{OH} = -0.55 \text{ mA}$	1.44		
$V_{OL}$	Low-level output voltage	3.3-V TTL	$I_{OL} = 4 \text{ mA}$		0.5	V
		1.8-V LVCMOS (XTL_OUT)	$I_{OL} = 0.75 \text{ mA}$		0.396	
$I_{OZ}$	High-impedance output current	3.3-V TTL			$\pm 20$	$\mu\text{A}$
$I_{IL}^{(1)}$	Low-level input current	1.8-V LVCMOS (XTL_IN)	$V_I = V_{IL}$		$\pm 1$	$\mu\text{A}$
		3.3-V TTL	$V_I = V_{IL}$		$\pm 1$	
$I_{IH}^{(2)}$	High-level input current	1.8-V LVCMOS (XTL_IN)	$V_I = V_{IH}$		$\pm 1$	$\mu\text{A}$
		3.3-V TTL	$V_I = V_{IH}$		$\pm 1$	
$I_{DVDD}$	Digital supply current		DSP clock = 135-MHz LRCLKIN/LRCLKOUT = 48 KHz, XTALI = 24.288 MHz		200	mA
$I_{AVDD}$	Analog supply current		DSP clock = 135-MHz LRCLKIN/LRCLKOUT = 48 KHz, XTALI = 24.288 MHz		28	mA
$I_{DVDD}$	Digital supply current		RESET = Low		0.1	mA
$I_{AVDD}$	Analog supply current		RESET = Low		5	mA

(1) Value given is for those input pins that connect to an internal pull-up resistor as well as an input buffer. For inputs that have a pull-down resistor or no resistor,  $I_{IL}$  is  $\pm 1 \mu\text{A}$ .

(2) Value given is for those input pins that connect to an internal pull-down resistor as well as an input buffer. For inputs that have a pull-up resistor or no resistor,  $I_{IH}$  is  $\pm 1 \mu\text{A}$ .

## PACKAGING INFORMATION

Orderable Device	Status <sup>(1)</sup>	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/Ball Finish	MSL Peak Temp <sup>(3)</sup>
TAS3208PZP	ACTIVE	HTQFP	PZP	100	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-3-260C-168 HR
TAS3208PZPR	ACTIVE	HTQFP	PZP	100	1000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-3-260C-168 HR

<sup>(1)</sup> The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBsolete:** TI has discontinued the production of the device.

<sup>(2)</sup> Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)


<sup>(3)</sup> MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

PZP (S-PQFP-G100)

PowerPAD™ PLASTIC QUAD FLATPACK



- NOTES:
- All linear dimensions are in millimeters.
  - This drawing is subject to change without notice.
  - Body dimensions do not include mold flash or protrusion.
  - This package is designed to be soldered to a thermal pad on the board. Refer to Technical Brief, PowerPad Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 for information regarding recommended board layout. This document is available at [www.ti.com](http://www.ti.com) <<http://www.ti.com>>.
  - Falls within JEDEC MS-026

PowerPAD is a trademark of Texas Instruments.



## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

### Products

Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
Low Power Wireless	<a href="http://www.ti.com/lpw">www.ti.com/lpw</a>

### Applications

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments  
Post Office Box 655303 Dallas, Texas 75265