



35A5
35L6GT

Replacement Type

TYPE 35A5
(LOCTAL BASE)
OUTPUT BEAM
TETRODE





RATINGS

Heater Voltage	...	...	...	...	...	...	35 volts
Heater Current	...	...	...	...	...	...	0.15 amp.
Anode Voltage	...	...	...	...	...	...	200 volts max.
Anode Dissipation	...	...	...	...	...	...	8.5 watts max.
Screen (g_2) Voltage	...	...	...	...	...	...	110 volts max.
Screen Dissipation	...	...	...	...	...	...	1.0 watts max.

For further information and characteristic curves refer to type 35L6GT.

Replacement Type

TYPE 35L6GT
(OCTAL BASE)
OUTPUT BEAM
TETRODE



RATINGS

Heater Voltage	...	...	...	...	...	...	35 volts
Heater Current	...	...	...	...	...	...	0.15 amp.
Anode Voltage	...	...	...	...	...	...	200 volts max.
Anode Dissipation	...	...	...	...	...	...	8.5 watts max.
Screen (g_2) Voltage	...	...	...	...	...	...	110 volts max.
Screen Dissipation	...	...	...	...	...	...	1.0 watt max.

OPERATING CHARACTERISTICS

Anode Voltage	...	...	...	...	...	110	200	volts
Anode Current	...	...	...	...	...	40	41	mA
Screen Voltage	...	...	...	...	...	110	110	volts
Screen Current (Zero Signal)	...	...	...	...	...	3.0	2.0	mA
Screen Current (Max. Signal)	...	...	...	...	...	7	7	mA
Control Grid (g_1) Voltage	...	...	...	...	...	-7.5	-8	volts
Cathode Bias Resistor	...	...	...	...	...	170	185	ohms
Anode Impedance	...	...	...	...	...	14,000	40,000	ohms
Mutual Conductance	...	...	...	...	...	5.8	5.9	mA/V
Optimum Load	...	...	...	...	...	2,500	4,500	ohms
Power Output	...	...	...	...	...	1.5	3.3	watts
Harmonic Distortion	...	...	...	...	...	10	10	per cent

INTER-ELECTRODE CAPACITANCES

Input	...	...	...	...	...	...	13.2 pF
Output	...	...	...	...	...	...	8.25 pF
Control Grid to Anode	...	...	...	...	...	...	0.95 pF

