

TOSHIBA TRANSISTOR SILICON NPN EPITAXIAL TYPE (PCT PROCESS)


RN1110, RN1111

Unit in mm

SWITCHING, INVERTER CIRCUIT, INTERFACE CIRCUIT
AND DRIVER CIRCUIT APPLICATIONS.

- With Built-in Bias Resistors
- Simplify Circuit Design
- Reduce a Quantity of Parts and Manufacturing Process
- Complementary to RN2110~RN2111

EQUIVALENT CIRCUIT




MAXIMUM RATINGS (Ta = 25°C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Collector-Base Voltage	V _{CB0}	50	V
Collector-Emitter Voltage	V _{CEO}	50	V
Emitter-Base Voltage	V _{EBO}	5	V
Collector Current	I _C	100	mA
Collector Power Dissipation	P _C	100	mW
Junction Temperature	T _j	150	°C
Storage Temperature Range	T _{stg}	-55~150	°C





ELECTRICAL CHARACTERISTICS (Ta = 25°C)

CHARACTERISTIC		SYMBOL	TEST CONSITION	MIN.	TYP.	MAX.	UNIT
Collector Cut-off Current		I _{CBO}	V _{CB} =50V, I _E =0	—	—	0.1	μA
Emitter Cut-off Current		I _{EBO}	V _{EB} =5V, I _C =0	—	—	0.1	μA
DC Current Gain		h _{FE}	V _{CE} =5V, I _C =1mA	120	—	700	
Collector-Emitter Saturation Voltage		V _{CE (sat)}	I _C =5mA, I _B =0.25mA	—	0.1	0.3	V
Transition Frequency		f _T	V _{CE} =10V, I _C =5mA	—	250	—	MHz
Collector Output Capacitance		C _{ob}	V _{CB} =10V, I _E =0, f=1MHz	—	3	6	pF
Input Resistor	RN1110	R1		3.29	4.7	6.11	kΩ
	RN1111			7	10	13	







961001EAA2



● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.



961001EAA2'

- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.



TYPE NAME	MARKING
RN1110	 The diagram shows a rectangular component with two pins at the bottom. A line points from the text 'Type Name' to the top of the component, which is marked with 'X K'.
RN1111	 The diagram shows a rectangular component with two pins at the bottom. A line points from the text 'Type Name' to the top of the component, which is marked with 'X M'.