### Dual 2-to-4 Decoder/ Demultiplexer


The MC74VHC139 is an advanced high speed CMOS 2–to–4 decoder/demultiplexer fabricated with silicon gate CMOS technology. It achieves high speed operation similar to equivalent Bipolar Schottky TTL while maintaining CMOS low power dissipation. \_

When the device is enabled (E = low), it can be used for gating or as a data input for demultiplexing operations. When the enable input is held high, all four outputs are fixed high, independent of other inputs.

The internal circuit is composed of three stages, including a buffer output which provides high noise immunity and stable output. The inputs tolerate voltages up to 7V, allowing the interface of 5V systems to 3V systems.

- High Speed: tpp = 5.0ns (Typ) at Vcc = 5V
- Low Power Dissipation:  $I_{CC} = 4\mu A$  (Max) at  $T_A = 25^{\circ}C$
- High Noise Immunity: VNIH = VNIL = 28% VCC
- Power Down Protection Provided on Inputs
- Balanced Propagation Delays
- Designed for 2V to 5.5V Operating Range
- Low Noise: VOLP = 0.8 V (Max)
- · Pin and Function Compatible with Other Standard Logic Families
- · Latchup Performance Exceeds 300mA
- ESD Performance: HBM > 2000V; Machine Model > 200V
- Chip Complexity: 100 FETs or 25 Equivalent Gates

#### **LOGIC DIAGRAM**



### **MC74VHC139**



#### **D SUFFIX** 16-LEAD SOIC PACKAGE CASE 751B-05



#### **DT SUFFIX** 16-LEAD TSSOP PACKAGE CASE 948F-01



#### **M SUFFIX** 16-LEAD SOIC EIAJ PACKAGE CASE 966-01

#### **ORDERING INFORMATION**

MC74VHCXXXD SOIC
MC74VHCXXXDT TSSOP
MC74VHCXXXM SOIC EIAJ

### PIN ASSIGNMENT — \_ \_ \_


Ea L	1 ●	16	µ ∨сс
A0a [	2	15	Eb
A1a [	3	14	A0b
Y0a [	4	13	A1b
Y1a [	5	12	Y0b
Y2a [	6	11	Y1b
Y3a [	7	10	Y2b
GND [	8	9	Y3b

#### **FUNCTION TABLE**

Inputs			Outputs			
Е	A1	Α0	Y0	Y1	Y2	Y3
Н	Х	Χ	Н	Н	Н	Н
L	L	L	L	Н	Н	Н
L	L	Н	Н	L	Н	Н
L	Н	L	Н	Н	L	Н
L	Н	Н	Н	Н	Н	L



# EXPANDED LOGIC DIAGRAM (1/2 OF DEVICE)






Figure 1. Input Equivalent Circuit

MOTOROLA 2

#### **MAXIMUM RATINGS\***

Symbol	Parameter		Value	Unit
VCC	DC Supply Voltage		- 0.5 to + 7.0	٧
V <sub>in</sub>	DC Input Voltage	- 0.5 to + 7.0	٧	
V <sub>out</sub>	DC Output Voltage	-0.5 to V <sub>CC</sub> + 0.5	V	
lικ	Input Diode Current	<b>- 20</b>	mA	
lok	Output Diode Current		± 20	mA
l <sub>out</sub>	DC Output Current, per Pin		± 25	mA
ICC	DC Supply Current, V <sub>CC</sub> and GN	ID Pins	± 75	mA
PD	Power Dissipation in Still Air,	SOIC Packages† TSSOP Package†	500 450	mW
T <sub>stg</sub>	Storage Temperature		- 65 to + 150	°C

<sup>\*</sup> Absolute maximum continuous ratings are those values beyond which damage to the device may occur. Exposure to these conditions or conditions beyond those indicated may adversely affect device reliability. Functional operation under absolute—maximum—rated conditions is not implied.

†Derating — SOIC Packages: – 7 mW/°C from 65° to 125°C TSSOP Package: – 6.1 mW/°C from 65° to 125°C

This device contains protection circuitry to guard against damage due to high static voltages or electric fields. However, precautions must be taken to avoid applications of any voltage higher than maximum rated voltages to this high–impedance circuit. For proper operation,  $V_{in}$  and  $V_{out}$  should be constrained to the range GND  $\leq$  ( $V_{in}$  or  $V_{out}$ )  $\leq$  VCC. Unused inputs must always be tied to an appropriate logic voltage

level (e.g., either GND or V<sub>CC</sub>). Unused outputs must be left open.

#### **RECOMMENDED OPERATING CONDITIONS**

Symbol	Parameter			Max	Unit
VCC	DC Supply Voltage			5.5	V
V <sub>in</sub>	DC Input Voltage			5.5	V
V <sub>out</sub>	DC Output Voltage			Vcc	V
TA	Operating Temperature		- 40	+ 85	°C
t <sub>r</sub> , t <sub>f</sub>	Input Rise and Fall Time VCC (Figure 1)	$c = 3.3V \pm 0.3V$ $c = 5.0V \pm 0.5V$	0 0	100 20	ns/V

#### DC ELECTRICAL CHARACTERISTICS

			VCC		T <sub>A</sub> = 25°C	;	$T_A = -40$	0 to 85°C	
Symbol	Parameter	Test Conditions	v	Min	Тур	Max	Min	Max	Unit
VIH	Minimum High–Level Input Voltage		2.0 3.0 to 5.5	1.50 V <sub>CC</sub> x 0.7			1.50 V <sub>CC</sub> x 0.7		V
VIL	Maximum Low–Level Input Voltage		2.0 3.0 to 5.5			0.50 V <sub>CC</sub> x 0.3		0.50 V <sub>CC</sub> x 0.3	V
VOH	Minimum High–Level Output Voltage	V <sub>in</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>OH</sub> = – 50μΑ	2.0 3.0 4.5	1.9 2.9 4.4	2.0 3.0 4.5		1.9 2.9 4.4		V
		$V_{\text{in}} = V_{\text{IH}} \text{ or } V_{\text{IL}}$ $I_{\text{OH}} = -4\text{mA}$ $I_{\text{OH}} = -8\text{mA}$	3.0 4.5	2.58 3.94			2.48 3.80		
V <sub>OL</sub>	Maximum Low–Level Output Voltage	V <sub>in</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>OL</sub> = 50μA	2.0 3.0 4.5		0.0 0.0 0.0	0.1 0.1 0.1		0.1 0.1 0.1	V
		$V_{\text{in}} = V_{\text{IH}} \text{ or } V_{\text{IL}}$ $I_{\text{OL}} = 4\text{mA}$ $I_{\text{OL}} = 8\text{mA}$	3.0 4.5			0.36 0.36		0.44 0.44	

3

MOTOROLA

#### DC ELECTRICAL CHARACTERISTICS

			Vcc TA		v <sub>cc</sub>		T <sub>A</sub> = 25°C		$T_A = -40$	) to 85°C	
Symbol	Parameter	Test Conditions	V	Min	Тур	Max	Min	Max	Unit		
lin	Maximum Input Leakage Current	V <sub>in</sub> = 5.5 V or GND	0 to 5.5			± 0.1		± 1.0	μА		
lcc	Maximum Quiescent Supply Current	$V_{in} = V_{CC}$ or GND	5.5			4.0		40.0	μА		

#### AC ELECTRICAL CHARACTERISTICS (Input $t_f = t_f = 3.0 \text{ns}$ )

					T <sub>A</sub> = 25°C		$T_A = -40$	) to 85°C	
Symbol	Parameter	Test Condi	tions	Min	Тур	Max	Min	Max	Unit
tPLH, tPHL	Maximum Propagation Delay, A to Y	$V_{CC} = 3.3 \pm 0.3 V$	$C_L = 15pF$ $C_L = 50pF$		7.2 9.7	11.0 14.5	1.0 1.0	13.0 16.5	ns
		$V_{CC} = 5.0 \pm 0.5 V$	$C_L = 15pF$ $C_L = 50pF$		5.0 6.5	7.2 9.2	1.0 1.0	8.5 10.5	
tPLH, tPHL	Maximum Propagation Delay, E to Y	$V_{CC} = 3.3 \pm 0.3 V$	$C_L = 15pF$ $C_L = 50pF$		6.4 8.9	9.2 12.7	1.0 1.0	11.0 14.5	ns
		$V_{CC} = 5.0 \pm 0.5 V$	$C_L = 15pF$ $C_L = 50pF$		4.4 5.9	6.3 8.3	1.0 1.0	7.5 9.5	
C <sub>in</sub>	Maximum Input Capacitance				4	10		10	pF

		Typical @ 25°C, V <sub>CC</sub> = 5.0V	
$C_{PD}$	Power Dissipation Capacitance (Note NO TAG)	26	pF

C<sub>PD</sub> is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.
 Average operating current can be obtained by the equation: I<sub>CC(OPR)</sub> = C<sub>PD</sub> • V<sub>CC</sub> • f<sub>in</sub> + I<sub>CC</sub>/2 (per decoder). C<sub>PD</sub> is used to determine the no–load dynamic power consumption; P<sub>D</sub> = C<sub>PD</sub> • V<sub>CC</sub><sup>2</sup> • f<sub>in</sub> + I<sub>CC</sub> • V<sub>CC</sub>.

#### **SWITCHING WAVEFORMS**




Figure 2.





Figure 3.



\* Includes all probe and jig capacitance

Figure 4. Test Circuit

MOTOROLA 4

INCHES

MIN MAX 0.386 0.393

0 150 0 157

0.054 0.068


0.014 0.019


0.016 0.049 0.050 BSC

0.008 0.009

0.004 0.009

#### **OUTLINE DIMENSIONS**





5

#### **OUTLINE DIMENSIONS**

## **M SUFFIX** PLASTIC SOIC EIAJ PACKAGE CASE 966-01 **ISSUE O** ффф $Q_1$ ΗE Ε **DETAIL P** VIEW P 0.10 (0.004) 0.13 (0.005) M

- 1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
- 2. CONTROLLING DIMENSION: MILLIMETER.
  3. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS AND ARE MEASURED AT THE PARTING LINE. MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.15 (0.006)
  PER SIDE.
- TERMINAL NUMBERS ARE SHOWN FOR REFERENCE ONLY.
- THE LEAD WIDTH DIMENSION (b) DOES NOT INCLUDE DAMBAR PROTRUSION, ALLOWABLE DAMBAR PROTRUSION SHALL BE 0.08 (0.003) TOTAL IN EXCESS OF THE LEAD WIDTH DIMENSION AT MAXIMUM MATERIAL CONDITION. DAMBAR CANNOT BE LOCATED ON THE LOWER RADIUS OR THE FOOT. MINIMUM SPACE BETWEEN PROTRUSIONS AND ADJACENT LEAD TO BE 0.46 (0.018).

	MILLIN	IETERS	INC	HES
DIM	MIN	MAX	MIN	MAX
Α	_	2.05		0.081
Α <sub>1</sub>	0.05	0.20	0.002	0.008
b	0.35	0.50	0.014	0.020
С	0.18	0.27	0.007	0.011
D	9.90	10.50	0.390	0.413
E	5.10	5.45	0.201	0.215
е	1.27	BSC	0.050	BSC
HE	7.40	8.20	0.291	0.323
L	0.50	0.85	0.020	0.033
LF	1.10	1.50	0.043	0.059
M	0 °	10 °	0 °	10 °
Q <sub>1</sub>	0.70	0.90	0.028	0.035
Z		0.78		0.031

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Mfax is a trademark of Motorola, Inc.

#### How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution; P.O. Box 5405, Denver, Colorado 80217. 303-675-2140 or 1-800-441-2447 JAPAN: Nippon Motorola Ltd.: SPD, Strategic Planning Office, 4-32-1, Nishi-Gotanda, Shinagawa-ku, Tokyo 141, Japan. 81-3-5487-8488

Mfax™: RMFAX0@email.sps.mot.com - TOUCHTONE 602-244-6609 - US & Canada ONLY 1-800-774-1848

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

INTERNET: http://motorola.com/sps



MC74VHC139/D