

Dual preamplifier with ALC detector circuit

BA3313L

The BA3313L is dual preamplifier ICs with built-in ALC detector circuit, designed for use in stereo radio cassette recorders. It comes in a compact 12-pin ZIP package, and has two record/playback preamplifiers, and an ALC detector circuit. The preamplifiers can be directly coupled to the tape head without coupling capacitors to prevent tape head magnetization and "pop" noise generation.

With the built-in ALC detector circuit, an ALC circuit with large dynamic range can be constructed with addition of just an external time constant circuit.


● Applications

Stereo radio cassette recorders

● Features

- 1) Input bias circuit does not require coupling capacitors.
- 2) Built-in ALC circuit with external time constant circuit.
- 3) Wide operating supply voltage range.
- 4) High gain.
- 5) Low noise.

● Block diagram



7828999 0019103 034

● Absolute maximum ratings (Ta = 25°C)

Parameter	Symbol	Limits	Unit
Supply voltage	Vcc	14	V
Power dissipation	Pd	400*	mW
Operating temperature	Topr	−25~75	°C
Storage temperature	Tstg	−55~125	°C

* Reduced by 4.0mW for each increase in Ta of 1°C over 25°C

● Recommended operating conditions (Ta = 25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Supply voltage	Vcc	5.0	8.0	12.0	V

● Electrical characteristics (unless otherwise specified Ta = 25°C, Vcc = 8V and f = 1kHz)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Quiescent circuit current	I _Q	1.5	3.0	6.0	mA	
Open-circuit voltage gain	G _{VO}	70	85	—	dB	V _O =1Vrms
Closed-circuit voltage gain	G _{VC}	49	52	55	dB	V _O =0.3Vrms
Total harmonic distortion	THD 1	—	0.3	1.0	%	V _O =0.3Vrms
Maximum output voltage	V _{OM}	1.5	2.0	—	Vrms	THD=1%
Input conversion-noise voltage	V _{NIN}	—	1.0	1.8	μVrms	R _g =2.2kΩ, DIN AUDIO 45dB at 1kHz NAB
Input resistance	R _{IN}	35	51	71	kΩ	
Channel separation	CS	40	55	—	dB	R _g =2.2kΩ
ALC range *	ALC	40	53	—	dB	
ALC balance	ALB	—	0	3.0	dB	V _{IN} =−45dBV
ALC distortion	THD 2	—	0.3	1.0	%	V _{IN} =−45dBV
ALC output voltage	V _{ALC}	700	850	1000	mVrms	V _{IN} =−45dBV

* The range for which the ALC begins to operate is the output voltage + 3dB with respect to the output voltage.

7828999 0019104 T70

ROHM

● Application example




Fig. 2

SW

1: Recording

2: Playback

Unit

Resistance : Ω ($\pm 5\%$)Film capacitors : F ($\pm 10\%$)Electrolytic capacitors : F ($\pm 20\%$)

● Operation notes (the resistor marked with an asterisk)

Changing the input resistor R_g , and the ALC time constant influences the ALC transient characteristics. In particular, if R_g is less than $3.9k\Omega$ or the time

constant capacitor is less than $47\mu F$, the ALC may operate excessively. Do not use smaller values than those recommended for these components.

Preamplifiers

Low-frequency amplifiers

7828999 0019106 843

ROHM

241

● Electrical characteristics curves




Fig. 3 Input voltage vs. output voltage

● External dimensions (Unit: mm)

