

SANYO

No.934G

2SC3069

NPN Epitaxial Planar Silicon Transistor

High h_{FE} , Low-Frequency
General-Purpose Amp Applications**Applications**

- Low-frequency, general-purpose amp., various drivers, muting circuit

Features

- High DC current gain ($h_{FE}=800$ to 3200)
- Low collector-to-emitter saturation voltage: $V_{CE(sat)}=0.5V$ max.
- High V_{EBO} ($V_{EBO} \geq 15V$)

Absolute Maximum Ratings/ $T_a=25^\circ C$


			unit
Collector to Base Voltage	V_{CBO}	60	V
Collector to Emitter Voltage	V_{CEO}	50	V
Emitter to Base Voltage	V_{EBO}	15	V
Collector Current	I_C	200	mA
Collector Current(Pulse)	I_{CP}	300	mA
Base Current	I_B	40	mA
Collector Dissipation	P_C	600	mW
Junction Temperature	T_j	150	$^\circ C$
Storage Temperature	T_{stg}	-55 to +150	$^\circ C$

Electrical Characteristics/ $T_a=25^\circ C$

			min	typ	max	unit
Collector Cut-off Current	I_{CBO}	$V_{CB}=40V, I_E=0$			0.1	μA
Emitter Cut-off Current	I_{EBO}	$V_{EB}=10V, I_C=0$			0.1	μA
DC Current Gain	$h_{FE}(1)$	$V_{CE}=5V, I_C=10mA$	800	1500	3200	
	$h_{FE}(2)$	$V_{CE}=5V, I_C=100mA$	600			
Gain-bandwidth product	f_T	$V_{CE}=10V, I_C=10mA$		250		MHz
Common Base Output Capacitance	c_{ob}	$V_{CB}=10V, f=1MHz$		4.0		pF
Collector to Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C=100mA, I_B=2mA$		0.12	0.5	V
Base to Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C=100mA, I_B=2mA$		0.85	1.2	V
Collector to Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C=10\mu A, I_E=0$	60			V
Collector to Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C=1mA, I_B=0$	50			V
Emitter to Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E=10\mu A, I_C=0$	15			V









Package Dimensions 2003A



(unit: mm)

**SANYO Electric Co., Ltd. Semiconductor Business Headquarters**

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110 JAPAN

6140M0/4207KI/3085KI/2033KI, TS No.934-1/3





■ No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.

■ Anyone purchasing any products described or contained herein for an above-mentioned use shall:

- ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
- ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.

■ Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.