

**SPECIFICATION SHEET**  
**JFW MODEL 50L-001 BNC**  
**FEEDTHRU TERMINATION**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

|                             |                                                        |
|-----------------------------|--------------------------------------------------------|
| Frequency Range             | DC-1000 MHz                                            |
| Impedance                   | 50 Ohms nominal                                        |
| VSWR                        | 1.1:1 maximum DC-500 MHz<br>1.2:1 maximum 500-1000 MHz |
| RF Input Power              | 1 Watt average                                         |
| Peak Power                  | 1000 Watts                                             |
| RF Connector                | BNC male/female                                        |
| Operating Temperature Range | -20°C to +100°C                                        |
| Physical Size               | See outline drawing 092-004                            |

| ECR/ECN # | DATE       | REV | APPR / DATE   | ECR/ECN # | DATE | REV | APPR / DATE |
|-----------|------------|-----|---------------|-----------|------|-----|-------------|
| 9999      | 04/12/2004 | A   | SL 10/04/2005 |           |      |     |             |