



# MAC7100 Microcontroller Family Hardware Specifications

Covers MAC7101, MAC7106, MAC7111, MAC7116, MAC7121,  
MAC7126, MAC7131, MAC7136, MAC7141<sup>1</sup>

32-bit Embedded Controller Division

1. With preliminary information on MAC7112, MAC7122, MAC7142 devices.

This document provides electrical specifications, pin assignments, and package diagrams for MAC7100 family of microcontroller devices. For functional characteristics, refer to the *MAC7100 Microcontroller Family Reference Manual* (MAC7100RM).

## 1 Overview

The MAC7100 Family of microcontrollers (MCUs) are members of a pin-compatible family of 32-bit Flash-memory-based devices developed specifically for embedded automotive applications. The pin-compatible family concept enables users to select between different memory and peripheral options for scalable designs. All MAC7100 Family members are composed of a 32-bit ARM7TDMI-S™ central processing unit, up to 1 Mbyte of embedded Flash EEPROM for program storage, up to 32 Kbytes of embedded Flash for data and/or program storage, and up to 48 Kbytes of RAM. The family is implemented with an enhanced DMA (eDMA) controller to improve performance for transfers between memory and many of the on-chip peripherals. The peripheral set includes asynchronous serial communications interfaces (eSCI), serial peripheral interfaces (DSPI),

### Table of Contents

|      |                                                  |    |
|------|--------------------------------------------------|----|
| 1    | Overview .....                                   | 1  |
| 2    | Ordering Information .....                       | 2  |
| 3    | Electrical Characteristics .....                 | 4  |
| 3.1  | Parameter Classification .....                   | 4  |
| 3.2  | Absolute Maximum Ratings .....                   | 4  |
| 3.3  | ESD Protection and Latch-up Immunity .....       | 5  |
| 3.4  | Operating Conditions .....                       | 6  |
| 3.5  | Input/Output Characteristics .....               | 7  |
| 3.6  | Power Dissipation and Thermal Characteristics .. | 8  |
| 3.7  | Power Supply .....                               | 11 |
| 3.8  | Clock and Reset Generator .....                  | 15 |
| 3.9  | External Bus Timing .....                        | 20 |
| 3.10 | Analog-to-Digital Converter .....                | 24 |
| 3.11 | Serial Peripheral Interface .....                | 29 |
| 3.12 | FlexCAN Interface .....                          | 32 |
| 3.13 | Common Flash Module .....                        | 32 |
| 4    | Device Pin Assignments .....                     | 36 |
| 4.1  | MAC7141 Pin Diagram .....                        | 41 |
| 4.2  | MAC7142 Pin Diagram .....                        | 42 |
| 4.3  | MAC7121 / MAC7126 Pin Diagram .....              | 43 |
| 4.4  | MAC7122 Pin Diagram .....                        | 44 |
| 4.5  | MAC7101 / MAC7106 Pin Diagram .....              | 45 |
| 4.6  | MAC7111 / MAC7116 Pin Diagram .....              | 46 |
| 4.7  | MAC7112 Pin Diagram .....                        | 47 |
| 4.8  | MAC7131 Pin Diagram .....                        | 48 |
| 4.9  | MAC7136 Pin Diagram .....                        | 49 |
| 5    | Mechanical Information .....                     | 50 |
|      | Revision History .....                           | 51 |




## Ordering Information

inter-integrated circuit (I<sup>2</sup>C™) bus controllers, FlexCAN interfaces, an enhanced modular I/O subsystem (eMIOS), 10-bit analog-to-digital converter (ATD) module(s), general-purpose timers (PIT) and two special-purpose timers (RTI and SWT). The peripherals share a large number of general purpose input-output (GPIO) pins, all of which are bidirectional and available with interrupt capability to trigger wake-up from low-power chip modes. Refer to [Table 2](#) for a comparison of family members and availability of peripheral modules on each device.

The use of a PLL allows power drain and performance to be balanced to best fit requirements. The operating frequency of devices in the family is up to a maximum of 50 MHz. The internal data paths between the CPU core, eDMA, memory and peripherals are all 32 bits wide, further improving performance for 32-bit applications. The MAC7111, MAC7116, MAC7131 and MAC7136 also offer a 16-bit wide external data bus with 22 address lines. The family of devices is capable of operating over a junction temperature range of -40° C to 150° C.

## 2 Ordering Information



**Figure 1. Order Part Number Example**

The mask set of a device is marked with a four-character code consisting of a letter, two numerical digits, and a letter, for example L49P. Slight variations to the mask set identification code may result in an optional numerical digit preceding the standard four-character code, for example 0L49P.

**Table 1. MAC7100 Family Mask Set to Part Number Correspondence**

| Mask Set | Status                                | Part Number(s)                              |
|----------|---------------------------------------|---------------------------------------------|
| 0L49P    | Engineering samples                   | PAC7101, PAC7111, PAC7121, PAC7131, PAC7141 |
| 1L49P    | Limited production, pre-qualification | PAC7101, PAC7111, PAC7121, PAC7131, PAC7141 |
| 0L47W    | Limited production, pre-qualification | PAC7101, PAC7111, PAC7121, PAC7131, PAC7141 |
| 1L47W    | Fully-qualified, production           | MAC7101, MAC7111, MAC7121, MAC7131, MAC7141 |
| 0L61W    | Engineering samples                   | PAC7112, PAC7122, PAC7142                   |
| 0L38Y    | Engineering samples                   | PAC7106, PAC7116, PAC7126, PAC7136          |
| 1L38Y    | Fully-qualified, production           | MAC7106, MAC7116, MAC7126, MAC7136          |

Table 2. MAC7100 Family Device Derivatives

| Module Options                    |              | MAC7101             | MAC7111          | MAC7121          | MAC7131         | MAC7141          | MAC7112         | MAC7122          | MAC7142  | MAC7106   | MAC7116  | MAC7126          | MAC7136          |
|-----------------------------------|--------------|---------------------|------------------|------------------|-----------------|------------------|-----------------|------------------|----------|-----------|----------|------------------|------------------|
| Program Flash                     |              | 512 KBytes          |                  |                  |                 |                  | 256 KBytes      |                  |          | 1 MByte   |          |                  |                  |
| Data Flash                        |              | 32 KBytes           |                  |                  |                 |                  |                 |                  |          |           |          |                  |                  |
| SRAM                              |              | 32 KBytes           |                  |                  |                 |                  | 16 KBytes       |                  |          | 48 KBytes |          |                  |                  |
| External Bus                      |              | —                   | Yes              | —                | Yes             | —                | —               | —                | —        | —         | Yes      | —                | Yes              |
| ATD Modules <sup>1</sup>          | A            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
|                                   | B            | Yes                 | —                | —                | Yes             | —                | —               | —                | —        | Yes       | —        | —                | Yes              |
| CAN Modules                       | A            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
|                                   | B            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
|                                   | C            | Yes                 | Yes              | Yes              | Yes             | —                | —               | —                | —        | Yes       | Yes      | Yes              | Yes              |
|                                   | D            | Yes                 | Yes              | Yes              | Yes             | —                | —               | —                | —        | Yes       | Yes      | Yes              | Yes              |
| eSCI Modules                      | A            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
|                                   | B            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
|                                   | C            | Yes                 | Yes              | Yes              | Yes             | —                | Yes             | Yes              | —        | Yes       | Yes      | Yes              | Yes              |
|                                   | D            | Yes                 | Yes              | Yes              | Yes             | Yes              | —               | —                | —        | Yes       | Yes      | Yes              | Yes              |
| DSPI Modules                      | A            | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes <sup>2</sup> |
|                                   | B            | Yes                 | Yes              | Yes <sup>3</sup> | Yes             | Yes              | Yes             | Yes <sup>3</sup> | Yes      | Yes       | Yes      | Yes <sup>3</sup> | Yes <sup>2</sup> |
| I <sup>2</sup> C Module           |              | Yes                 | Yes              | Yes              | Yes             | Yes              | Yes             | Yes              | Yes      | Yes       | Yes      | Yes              | Yes              |
| eMIOS Module                      |              | 16 channels, 16-bit |                  |                  |                 |                  |                 |                  |          |           |          |                  |                  |
| Timer Module                      |              | 10 channels, 24-bit |                  |                  |                 |                  |                 |                  |          |           |          |                  |                  |
| General-Purpose<br>I/O Ports/Pins | A            | 10                  | 16               | 10               | 16              | 4                | 16              | 10               | 4        | 10        | 16       | 10               | 16               |
|                                   | B            | 16                  | 16               | 15               | 16              | 16               | 16              | 15               | 16       | 16        | 16       | 15               | 16               |
|                                   | C            | 12                  | 16               | 1                | 16              | —                | 16              | 1                | —        | 12        | 16       | 1                | 16               |
|                                   | D            | 10 <sup>4</sup>     | 16 <sup>4</sup>  | 11 <sup>4</sup>  | 16 <sup>4</sup> | 10 <sup>4</sup>  | 16              | 11               | 10       | 10        | 16       | 11               | 16               |
|                                   | E            | 16                  | 16               | 16               | 16              | 16               | 16              | 16               | 16       | 16        | 16       | 16               | 16               |
|                                   | F            | 16                  | 16               | 16               | 16              | 16               | 16              | 16               | 16       | 16        | 16       | 16               | 16               |
|                                   | G            | 16                  | 16               | 16               | 16              | 10               | 16              | 16               | 10       | 16        | 16       | 16               | 16               |
|                                   | H            | 16                  | —                | —                | 16              | —                | —               | —                | —        | 16        | —        | —                | 16               |
|                                   | I            | —                   | —                | —                | —               | —                | —               | —                | —        | —         | —        | —                | 16               |
|                                   | Total (max.) |                     | 112 <sup>4</sup> | 112 <sup>4</sup> | 85 <sup>4</sup> | 128 <sup>4</sup> | 72 <sup>4</sup> | 112              | 85       | 72        | 112      | 112              | 85               |
| Package                           |              | 144 LQFP            | 144 LQFP         | 112 LQFP         | 208 BGA         | 100 LQFP         | 144 LQFP        | 112 LQFP         | 100 LQFP | 144 LQFP  | 144 LQFP | 112 LQFP         | 208 BGA          |

## NOTES:

- 16 channels, 8/10-bit, per module.
- Four additional chip selects available.
- PB11 / PCS2\_B not available on non-L49P-mask devices; PB10 / PCS5\_B / PCSS\_B not available on mask L47W devices.
- Reduce these values by one for mask set L49P devices (PD2 is not available for general-purpose use).

### 3 Electrical Characteristics

This section contains electrical information for MAC7100 Family microcontrollers. The information is preliminary and subject to change without notice.

MAC7100 Family devices are specified and tested over the 5 V and 3.3 V ranges. For operation at any voltage within that range, the 3.3 V specifications generally apply. However, no production testing is done to verify operation at intermediate supply voltage levels.

#### 3.1 Parameter Classification

The electrical parameters shown in this appendix are derived by various methods. To provide a better understanding to the designer, the following classification is used. Parameters are tagged accordingly in the column labeled “C” of the parametric tables, as appropriate.

**Table 3. Parametric Value Classification**

|   |                                                                                                                                                                                                                                            |
|---|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| P | Parameters guaranteed during production testing on each individual device.                                                                                                                                                                 |
| C | Parameters derived by the design characterization and by measuring a statistically relevant sample size across process variations.                                                                                                         |
| T | Parameters derived by design characterization on a small sample size from typical devices under typical conditions (unless otherwise noted). All values shown in the typical column are within this classification, even if not so tagged. |
| D | Parameters derived mainly from simulations.                                                                                                                                                                                                |

#### 3.2 Absolute Maximum Ratings

Absolute maximum ratings are stress ratings only. Functional operation outside these maximums is not guaranteed. Stress beyond these limits may affect reliability or cause permanent damage to the device.

MAC7100 Family devices contain circuitry protecting against damage due to high static voltage or electrical fields; however, it is advised that normal precautions be taken to avoid application of any voltages higher than maximum-rated voltages to this high-impedance circuit. Reliability of operation is enhanced if unused inputs are tied to an appropriate logic voltage level (for example, either  $V_{SS}^{51}$  or  $V_{DD}^{51}$ ).

**Table 4. Absolute Maximum Ratings**

| Num | Rating                                    | Symbol            | Min  | Max  | Unit |
|-----|-------------------------------------------|-------------------|------|------|------|
| A1a | I/O Drivers Supply Voltage                | $V_{DDX}$         | -0.3 | +6.0 | V    |
| A2  | Digital Logic Supply Voltage <sup>1</sup> | $V_{DD2.5}$       | -0.3 | +3.0 | V    |
| A3  | PLL Supply Voltage <sup>1</sup>           | $V_{DDPLL}$       | -0.3 | +3.0 | V    |
| A4  | Analog Supply Voltage                     | $V_{DDA}$         | -0.3 | +6.0 | V    |
| A5  | Analog Reference                          | $V_{RH}, V_{RL}$  | -0.3 | +6.0 | V    |
| A6  | Voltage difference $V_{DDX}$ to $V_{DDA}$ | $\Delta V_{DDX}$  | -0.3 | +0.3 | V    |
| A7  | Voltage difference $V_{SSX}$ to $V_{SSA}$ | $\Delta V_{SSX}$  | -0.3 | +0.3 | V    |
| A8  | Voltage difference $V_{RH} - V_{RL}$      | $V_{RH} - V_{RL}$ | -0.3 | +6.0 | V    |

1. Refer to [Section 3.7, “Power Supply,”](#) for definition of  $V_{SS5}$  and  $V_{DD5}$ .

Table 4. Absolute Maximum Ratings (continued)

| Num | Rating                                                  | Symbol             | Min   | Max            | Unit |
|-----|---------------------------------------------------------|--------------------|-------|----------------|------|
| A9  | Voltage difference $V_{DDA} - V_{RH}$                   | $V_{DDA} - V_{RH}$ | -0.3  | +6.0           | V    |
| A10 | Digital I/O Input Voltage                               | $V_{IN}$           | -0.3  | +6.0           | V    |
| A11 | XFC, EXTAL, XTAL inputs                                 | $V_{ILV}$          | -0.3  | +3.0           | V    |
| A12 | TEST input                                              | $V_{TEST}$         | -0.3  | — <sup>2</sup> | V    |
|     | Instantaneous Maximum Current <sup>3</sup>              |                    |       |                |      |
| A13 | Single pin limit for XFC, EXTAL, XTAL <sup>4</sup>      | $I_{DL}$           | -25   | +25            | mA   |
| A14 | Single pin limit for all digital I/O pins <sup>5</sup>  | $I_D$              | -25   | +25            | mA   |
| A15 | Single pin limit for all analog input pins <sup>5</sup> | $I_{DA}$           | -25   | +25            | mA   |
| A16 | Single pin limit for TEST <sup>2</sup>                  | $I_{DT}$           | -0.25 | 0              | mA   |
| A17 | Storage Temperature Range                               | $T_{stg}$          | -65   | +155           | °C   |

## NOTES:

1. The device contains an internal voltage regulator to generate the logic and PLL supply from the I/O supply. The absolute maximum ratings apply when the device is powered from an external source.
2. This pin is clamped low to  $V_{SSX}$ , but not clamped high, and must be tied low in applications.
3. Input must be current limited to the value specified. To determine the value of the required current-limiting resistor, use the larger of the calculated values using  $V_{POSCLAMP} = V_{DDA} + 0.3V$  and  $V_{NEGCLAMP} = -0.3V$ .
4. These pins are internally clamped to  $V_{SSPLL}$  and  $V_{DDPLL}$ .
5. All I/O pins are internally clamped to  $V_{SSX}$  and  $V_{DDX}$ ,  $V_{SSR}$  and  $V_{DDR}$  or  $V_{SSA}$  and  $V_{DDA}$ .

### 3.3 ESD Protection and Latch-up Immunity

All ESD testing is in conformity with CDF-AEC-Q100 Stress test qualification for Automotive Grade Integrated Circuits. During the device qualification ESD stresses were performed for the Human Body Model (HBM), the Machine Model (MM) and the Charge Device Model.

A device is defined as a failure if after exposure to ESD pulses the device no longer meets the device specification. Complete DC parametric and functional testing is performed per the applicable device specification at room temperature followed by hot temperature, unless specified otherwise.

Table 5. ESD and Latch-up Test Conditions

| Model      | Description                                      | Symbol | Value       | Unit |
|------------|--------------------------------------------------|--------|-------------|------|
| Human Body | Series Resistance                                | R1     | 1500        | Ohm  |
|            | Storage Capacitance                              | C      | 100         | pF   |
|            | Number of Pulses per pin<br>positive<br>negative | —      | —<br>3<br>3 |      |
| Machine    | Series Resistance                                | R1     | 0           | Ohm  |
|            | Storage Capacitance                              | C      | 200         | pF   |
|            | Number of Pulse per pin<br>positive<br>negative  | —      | —<br>3<br>3 |      |
| Latch-up   | Minimum input voltage limit                      |        | -2.5        | V    |
|            | Maximum input voltage limit                      |        | 7.5         | V    |

Table 6. ESD and Latch-Up Protection Characteristics

| Num | C | Rating                                                                | Symbol    | Min          | Max | Unit |
|-----|---|-----------------------------------------------------------------------|-----------|--------------|-----|------|
| B1  | C | Human Body Model (HBM)                                                | $V_{HBM}$ | 2000         | —   | V    |
| B2  | C | Machine Model (MM)                                                    | $V_{MM}$  | 200          | —   | V    |
| B3  | C | Charge Device Model (CDM)                                             | $V_{CDM}$ | 500          | —   | V    |
| B4  | C | Latch-up Current at $T_A = 125^\circ\text{C}$<br>positive<br>negative | $I_{LAT}$ | +100<br>-100 | —   | mA   |
| B5  | C | Latch-up Current at $T_A = 27^\circ\text{C}$<br>positive<br>negative  | $I_{LAT}$ | +200<br>-200 | —   | mA   |

## 3.4 Operating Conditions

Unless otherwise noted, the following conditions apply to all parametric data. Refer to the temperature rating of the device (C, V, M) with respect to ambient temperature ( $T_A$ ) and junction temperature ( $T_J$ ). For power dissipation calculations refer to [Section 3.6, “Power Dissipation and Thermal Characteristics.”](#)

Table 7. MAC7100 Family Device Operating Conditions

| Num  | Rating                                                     | Symbol                 | Min  | Typ | Max  | Unit             |
|------|------------------------------------------------------------|------------------------|------|-----|------|------------------|
| C1   | I/O Drivers Supply Voltage                                 | $V_{DDX}$              | 3.15 | 5   | 5.5  | V                |
| C2   | Digital Logic Supply Voltage <sup>1</sup>                  | $V_{DD2.5}$            | 2.35 | 2.5 | 2.75 | V                |
| C3   | PLL Supply Voltage <sup>1</sup>                            | $V_{DDPLL}$            | 2.35 | 2.5 | 2.75 | V                |
| C4   | Analog Supply Voltage                                      | $V_{DDA}$              | 3.15 | 5   | 5.5  | V                |
| C5   | Voltage Difference $V_{DDX}$ to $V_{DDA}$                  | $\Delta V_{DDX}$       | -0.1 | 0   | 0.1  | V                |
| C6   | Voltage Difference $V_{SSX}$ to $V_{SSA}$                  | $\Delta V_{SSX}$       | -0.1 | 0   | 0.1  | V                |
| C7   | Oscillator Frequency                                       | $f_{OSC}$ <sup>2</sup> | 0.5  | —   | 16   | MHz              |
| C8   | System Clock Frequency                                     | $f_{SYS}$ <sup>2</sup> | 0.5  | —   | 50   | MHz              |
| C9a  | MAC71xxC Operating Junction Temperature Range <sup>3</sup> | $T_J$                  | -40  | —   | 110  | $^\circ\text{C}$ |
| C9b  | Operating Ambient Temperature Range <sup>3</sup>           | $T_A$                  | -40  | 25  | 85   | $^\circ\text{C}$ |
| C10a | MAC71xxV Operating Junction Temperature Range <sup>3</sup> | $T_J$                  | -40  | —   | 130  | $^\circ\text{C}$ |
| C10b | Operating Ambient Temperature Range <sup>3</sup>           | $T_A$                  | -40  | 25  | 105  | $^\circ\text{C}$ |
| C11a | MAC71xxM Operating Junction Temperature Range <sup>3</sup> | $T_J$                  | -40  | —   | 150  | $^\circ\text{C}$ |
| C11b | Operating Ambient Temperature Range <sup>3</sup>           | $T_A$                  | -40  | 25  | 125  | $^\circ\text{C}$ |

NOTES:

1. These ratings apply only when the VREG is disabled and the device is powered from an external source.
2. Throughout this document,  $t_{OSC}$  refers to  $1 \div f_{OSC}$ , and  $t_{SYS}$  refers to  $1 \div f_{SYS}$ .
3. Refer to [Section 3.6, “Power Dissipation and Thermal Characteristics,”](#) for more details about the relation between ambient temperature  $T_A$  and device junction temperature  $T_J$ .

### 3.4.1 Input/Output Pins

The I/O pins operate at a nominal level of 3.3 V to 5 V. This class of pins is comprised of the clocks, control and general purpose/peripheral pins. The internal structure of these pins is identical; however, some functionality may be disabled (for example, for analog inputs the output drivers, pull-up/down resistors are permanently disabled).

### 3.4.2 Oscillator Pins

The pins XFC, EXTAL, XTAL are dedicated to the oscillator and operate at a nominal level of 2.5V.

## 3.5 Input/Output Characteristics

This section describes the characteristics of all I/O pins in both 3.3 V and 5 V operating conditions. All parameters are not always applicable; for example, not all pins feature pull up/down resistances.

**Table 8. 5.0 V I/O Characteristics**

| Conditions shown in Table 7 unless otherwise noted |   |                                                                                                           |                        |                         |     |                         |         |
|----------------------------------------------------|---|-----------------------------------------------------------------------------------------------------------|------------------------|-------------------------|-----|-------------------------|---------|
| Num                                                | C | Rating                                                                                                    | Symbol                 | Min                     | Typ | Max                     | Unit    |
| D1a                                                | P | Input High Voltage                                                                                        | $V_{IH}$               | $0.65 \times V_{DD5}^1$ | —   | —                       | V       |
| D1b                                                | T | Input High Voltage                                                                                        | $V_{IH}$               | —                       | —   | $V_{DD5} + 0.3^1$       | V       |
| D2a                                                | P | Input Low Voltage                                                                                         | $V_{IL}$               | —                       | —   | $0.35 \times V_{DD5}^1$ | V       |
| D2b                                                | T | Input Low Voltage                                                                                         | $V_{IL}$               | $V_{SS5} - 0.3^1$       | —   | —                       | V       |
| D3                                                 | C | Input Hysteresis                                                                                          | $V_{HYS}$              | —                       | 250 | —                       | mV      |
| D4                                                 | P | Input Leakage Current (pins in high impedance input mode)<br>$V_{in} = V_{DD5}$ or $V_{SS5}^1$            | $I_{in}$               | $-1^2$                  | —   | $1^2$                   | $\mu A$ |
| D5                                                 | P | Output High Voltage (pins in output mode)<br>Partial Drive $I_{OH} = -2mA$<br>Full Drive $I_{OH} = -10mA$ | $V_{OH}$               | $V_{DD5} - 0.8$         | —   | —                       | V       |
| D6                                                 | P | Output Low Voltage (pins in output mode)<br>Partial Drive $I_{OL} = +2mA$<br>Full Drive $I_{OL} = +10mA$  | $V_{OL}$               | —                       | —   | 0.8                     | V       |
| D7                                                 | P | Internal Pull Up Device Current, tested at $V_{IL}$ Max.                                                  | $I_{PUL}$              | —                       | —   | -130                    | $\mu A$ |
| D8                                                 | P | Internal Pull Up Device Current, tested at $V_{IH}$ Min.                                                  | $I_{PUH}$              | -10                     | —   | —                       | $\mu A$ |
| D9                                                 | P | Internal Pull Down Device Current, tested at $V_{IH}$ Min.                                                | $I_{PDH}$              | —                       | —   | 130                     | $\mu A$ |
| D10                                                | P | Internal Pull Down Device Current, tested at $V_{IL}$ Max.                                                | $I_{PDL}$              | 10                      | —   | —                       | $\mu A$ |
| D11                                                | D | Input Capacitance                                                                                         | $C_{in}$               | —                       | 6   | —                       | pF      |
| D12                                                | T | Injection current <sup>3</sup><br>Single Pin limit<br>Total Device Limit. Sum of all injected currents    | $I_{ICS}$<br>$I_{ICP}$ | -2.5<br>-25             | —   | 2.5<br>25               | mA      |
| D13                                                | P | Port Interrupt Input Pulse filtered <sup>4</sup>                                                          | $t_{PULSE}$            | —                       | —   | 3                       | $\mu s$ |
| D14                                                | P | Port Interrupt Input Pulse passed <sup>4</sup>                                                            | $t_{PULSE}$            | 10                      | —   | —                       | $\mu s$ |

**NOTES:**

1. Refer to Section 3.7, "Power Supply," for definition of  $V_{SS5}$  and  $V_{DD5}$ .
2. Maximum leakage current occurs at maximum operating temperature. Current decreases by approximately one-half for each 8°C to 12°C in the temperature range from 50°C to 125°C.
3. Refer to Section 3.7.1, "Current Injection," for more details
4. Parameter only applies in STOP or Pseudo STOP mode.

Table 9. 3.3 V I/O Characteristics

| Conditions shown in Table 7, with $V_{DDX} = 3.3\text{ V} -5\%/+10\%$ and a temperature maximum of $+140^{\circ}\text{C}$ unless otherwise noted. |   |                                                                                                                             |                        |                         |     |                         |               |
|---------------------------------------------------------------------------------------------------------------------------------------------------|---|-----------------------------------------------------------------------------------------------------------------------------|------------------------|-------------------------|-----|-------------------------|---------------|
| Num                                                                                                                                               | C | Rating                                                                                                                      | Symbol                 | Min                     | Typ | Max                     | Unit          |
| E1a                                                                                                                                               | P | Input High Voltage                                                                                                          | $V_{IH}$               | $0.65 \times V_{DD5}^1$ | —   | —                       | V             |
| E1b                                                                                                                                               | T | Input High Voltage                                                                                                          | $V_{IH}$               | —                       | —   | $V_{DD5}^1 + 0.3^1$     | V             |
| E2a                                                                                                                                               | P | Input Low Voltage                                                                                                           | $V_{IL}$               | —                       | —   | $0.35 \times V_{DD5}^1$ | V             |
| E2b                                                                                                                                               | T | Input Low Voltage                                                                                                           | $V_{IL}$               | $V_{SS5} - 0.3^1$       | —   | —                       | V             |
| E3                                                                                                                                                | C | Input Hysteresis                                                                                                            | $V_{HYS}$              | —                       | 250 | —                       | mV            |
| E4                                                                                                                                                | P | Input Leakage Current (pins in high impedance input mode)<br>$V_{in} = V_{DD5}$ or $V_{SS5}^1$                              | $I_{in}$               | $-1^2$                  | —   | $1^2$                   | $\mu\text{A}$ |
| E5                                                                                                                                                | P | Output High Voltage (pins in output mode)<br>Partial Drive $I_{OH} = -0.75\text{mA}$<br>Full Drive $I_{OH} = -4.5\text{mA}$ | $V_{OH}$               | $V_{DD5} - 0.4$         | —   | —                       | V             |
| E6                                                                                                                                                | P | Output Low Voltage (pins in output mode)<br>Partial Drive $I_{OL} = +0.9\text{mA}$<br>Full Drive $I_{OL} = +5.5\text{mA}$   | $V_{OL}$               | —                       | —   | 0.4                     | V             |
| E7                                                                                                                                                | P | Internal Pull Up Device Current, tested at $V_{IL}$ Max.                                                                    | $I_{PUL}$              | —                       | —   | -60                     | $\mu\text{A}$ |
| E8                                                                                                                                                | P | Internal Pull Up Device Current, tested at $V_{IH}$ Min.                                                                    | $I_{PUH}$              | -6                      | —   | —                       | $\mu\text{A}$ |
| E9                                                                                                                                                | P | Internal Pull Down Device Current, tested at $V_{IH}$ Min.                                                                  | $I_{PDH}$              | —                       | —   | 60                      | $\mu\text{A}$ |
| E10                                                                                                                                               | P | Internal Pull Down Device Current, tested at $V_{IL}$ Max.                                                                  | $I_{PDL}$              | 6                       | —   | —                       | $\mu\text{A}$ |
| E11                                                                                                                                               | D | Input Capacitance                                                                                                           | $C_{in}$               | —                       | 6   | —                       | pF            |
| E12                                                                                                                                               | T | Injection current <sup>3</sup><br>Single Pin limit<br>Total Device Limit. Sum of all injected currents                      | $I_{ICS}$<br>$I_{ICP}$ | -2.5<br>-25             | —   | 2.5<br>25               | mA            |
| E13                                                                                                                                               | P | Port Interrupt Input Pulse filtered <sup>4</sup>                                                                            | $t_{PULSE}$            | —                       | —   | 3                       | $\mu\text{s}$ |
| E14                                                                                                                                               | P | Port Interrupt Input Pulse passed <sup>4</sup>                                                                              | $t_{PULSE}$            | 10                      | —   | —                       | $\mu\text{s}$ |

## NOTES:

1. Refer to Section 3.7, "Power Supply," for definition of  $V_{SS5}$  and  $V_{DD5}$ .
2. Maximum leakage current occurs at maximum operating temperature. Current decreases by approximately one-half for each  $8^{\circ}\text{C}$  to  $12^{\circ}\text{C}$  in the temperature range from  $50^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ .
3. Refer to Section 3.7.1, "Current Injection," for more details
4. Parameter only applies in STOP or Pseudo STOP mode.

## 3.6 Power Dissipation and Thermal Characteristics

Power dissipation and thermal characteristics are closely related. The user must assure that the maximum operating junction temperature is not exceeded.



Note that the JEDEC specification reserves the symbol  $R_{\theta JA}$  or  $\theta_{JA}$  (Theta-JA) strictly for junction-to-ambient thermal resistance on a 1s test board in natural convection environment.  $R_{\theta JMA}$  or  $\theta_{JMA}$  (Theta-JMA) will be used for both junction-to-ambient on a 2s2p test board in natural convection and for junction-to-ambient with forced convection on both 1s and 2s2p test boards. It is anticipated that the generic name,  $\theta_{JA}$ , will continue to be commonly used.

The average chip-junction temperature ( $T_J$ ) in °C is obtained from the formula:

$$T_J = T_A + P_D \cdot \theta_{JA} \quad \text{Eqn. 1}$$

where

$$\begin{aligned} T_J &= \text{Junction Temperature (°C)} \\ T_A &= \text{Ambient Temperature (°C)} \\ P_D &= \text{Total Chip Power Dissipation (W)} \\ \theta_{JA} &= \text{Package Thermal Resistance (°C/W)} \end{aligned}$$

The total power dissipation is calculated as:

$$P_D = P_{INT} + P_{IO} \quad \text{Eqn. 2}$$

where

$$\begin{aligned} P_{INT} &= \text{Chip Internal Power Dissipation (W)} \\ P_{IO} &= \text{Input / Output Power Dissipation (W)} \end{aligned}$$

Two cases must be considered for  $P_{INT}$ :

1. Internal voltage regulator enabled:

$$P_{INT} = (I_{DD}R \times V_{DD}R) + (I_{DD}A \times V_{DD}A) \quad \text{Eqn. 3}$$

2. Internal voltage regulator disabled ( $V_{DD}R = V_{SS}R = \text{system ground}$ ):

$$P_{INT} = (I_{DD}2.5 \times V_{DD}2.5) + (I_{DD}PLL \times V_{DD}PLL) + (I_{DD}A \times V_{DD}A) \quad \text{Eqn. 4}$$

$P_{IO}$  is the sum of all output currents on input/output pins associated with  $V_{DD}X$ :

$$P_{IO} = \sum_i R_{DSON} \cdot (I_{IO_i})^2 \quad \text{Eqn. 5}$$

where

$$R_{DSON} = \frac{V_{OL}}{I_{OL}} \quad (\text{for outputs driven low}) \quad \text{Eqn. 6}$$

or

$$R_{DSON} = \frac{V_{DD}X - V_{OH}}{I_{OL}} \quad (\text{for outputs driven high}) \quad \text{Eqn. 7}$$

**Table 10. Thermal Resistance 1/8 Simulation Model Packaging Parameters**

| Component          | Conductivity |
|--------------------|--------------|
| Mold Compound      | 0.9 W/m K    |
| Leadframe (Copper) | 263 W/m K    |
| Die Attach         | 1.7 W/m K    |

### 3.6.1 Thermal Resistance Simulation Details

**Table 11. Thermal Resistance for Case Outline 983-02, 100 Lead 14x14 mm LQFP, 0.5 mm Pitch**

| Rating                                   | Environment             | Symbol            | Value | Unit | Comments |
|------------------------------------------|-------------------------|-------------------|-------|------|----------|
| Junction to Ambient (Natural Convection) | Single layer board (1s) | R <sub>θJA</sub>  | 44    | °C/W | 1, 2     |
| Junction to Ambient (Natural Convection) | Four layer board (2s2p) | R <sub>θJMA</sub> | 34    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Single layer board (1s) | R <sub>θJMA</sub> | 37    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Four layer board (2s2p) | R <sub>θJMA</sub> | 29    | °C/W | 1, 3     |
| Junction to Board                        |                         | R <sub>θJB</sub>  | 18    | °C/W | 4        |
| Junction to Case                         |                         | R <sub>θJC</sub>  | 7     | °C/W | 5        |
| Junction to Package Top                  | Natural Convection      | Ψ <sub>JT</sub>   | 2     | °C/W | 6        |

**Table 12. Thermal Resistance for Case Outline 987-01, 112 Lead 20x20 mm LQFP, 0.65 mm Pitch**

| Rating                                   | Environment             | Symbol            | Value | Unit | Comments |
|------------------------------------------|-------------------------|-------------------|-------|------|----------|
| Junction to Ambient (Natural Convection) | Single layer board (1s) | R <sub>θJA</sub>  | 42    | °C/W | 1, 2     |
| Junction to Ambient (Natural Convection) | Four layer board (2s2p) | R <sub>θJMA</sub> | 34    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Single layer board (1s) | R <sub>θJMA</sub> | 35    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Four layer board (2s2p) | R <sub>θJMA</sub> | 30    | °C/W | 1, 3     |
| Junction to Board                        |                         | R <sub>θJB</sub>  | 22    | °C/W | 4        |
| Junction to Case                         |                         | R <sub>θJC</sub>  | 7     | °C/W | 5        |
| Junction to Package Top                  | Natural Convection      | Ψ <sub>JT</sub>   | 2     | °C/W | 6        |

**Table 13. Thermal Resistance for Case Outline 918-03, 144 Lead 20x20 mm LQFP, 0.5 mm Pitch**

| Rating                                   | Environment             | Symbol            | Value | Unit | Comments |
|------------------------------------------|-------------------------|-------------------|-------|------|----------|
| Junction to Ambient (Natural Convection) | Single layer board (1s) | R <sub>θJA</sub>  | 42    | °C/W | 1, 2     |
| Junction to Ambient (Natural Convection) | Four layer board (2s2p) | R <sub>θJMA</sub> | 34    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Single layer board (1s) | R <sub>θJMA</sub> | 35    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Four layer board (2s2p) | R <sub>θJMA</sub> | 30    | °C/W | 1, 3     |
| Junction to Board                        |                         | R <sub>θJB</sub>  | 22    | °C/W | 4        |
| Junction to Case                         |                         | R <sub>θJC</sub>  | 7     | °C/W | 5        |
| Junction to Package Top                  | Natural Convection      | Ψ <sub>JT</sub>   | 2     | °C/W | 6        |

**Table 14. Thermal Resistance for Case Outline 1159A-01, 208 Lead 17x17 mm MAP BGA, 1.0 mm Pitch**

| Rating                                   | Environment             | Symbol            | Value | Unit | Comments |
|------------------------------------------|-------------------------|-------------------|-------|------|----------|
| Junction to Ambient (Natural Convection) | Single layer board (1s) | R <sub>θJA</sub>  | 46    | °C/W | 1, 2     |
| Junction to Ambient (Natural Convection) | Four layer board (2s2p) | R <sub>θJMA</sub> | 29    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Single layer board (1s) | R <sub>θJMA</sub> | 38    | °C/W | 1, 3     |
| Junction to Ambient (@ 200 ft./min.)     | Four layer board (2s2p) | R <sub>θJMA</sub> | 26    | °C/W | 1, 3     |
| Junction to Board                        |                         | R <sub>θJB</sub>  | 19    | °C/W | 4        |
| Junction to Case                         |                         | R <sub>θJC</sub>  | 7     | °C/W | 5        |
| Junction to Package Top                  | Natural Convection      | Ψ <sub>JT</sub>   | 2     | °C/W | 6        |

**Comments:**

- Junction temperature is a function of die size, on-chip power dissipation, package thermal resistance, mounting site (board) temperature, ambient temperature, air flow, power dissipation of other components on the board, and board thermal resistance.
- Per SEMI G38-87 and JEDEC JESD51-2 with the single layer board (JESD51-3) horizontal.
- Per JEDEC JESD51-6 with the board (JESD51-7) horizontal.
- Thermal resistance between the die and the printed circuit board per JEDEC JESD51-8. Board temperature is measured on the top surface of the board at the center lead. For fused lead packages, the adjacent lead is used.
- Thermal resistance between the die and the case top surface as measured by the cold plate method (MIL SPEC-883 Method 1012.1).
- Thermal characterization parameter indicating the temperature difference between package top and junction temperature per JEDEC JESD51-2. When Greek letters are not available, the thermal characterization parameter is written as Psi-JT.

## 3.7 Power Supply

The MAC71xx Family utilizes several pins to supply power to the oscillator, PLL, digital core, I/O ports and ATD. In the context of this section,  $V_{DD5}$  is used for  $V_{DDA}$ ,  $V_{DDR}$  or  $V_{DDX}$ ;  $V_{SS5}$  is used for  $V_{SSA}$ ,  $V_{SSR}$  or  $V_{SSX}$  unless otherwise noted.  $I_{DD5}$  denotes the sum of the currents flowing into the  $V_{DDA}$ ,  $V_{DDX}$ , and  $V_{DDR}$ .  $V_{DD}$  is used for  $V_{DD2.5}$ , and  $V_{DDPLL}$ ,  $V_{SS}$  is used for  $V_{SS2.5}$  and  $V_{SSPLL}$ .  $I_{DD}$  is used for the sum of the currents flowing into  $V_{DD2.5}$  and  $V_{DDPLL}$ .

### 3.7.1 Current Injection

The power supply must maintain regulation within the  $V_{DD5}$  or  $V_{DD2.5}$  operating range during instantaneous and operating maximum current conditions. If positive injection current ( $V_{in} > V_{DD5}$ ) is greater than  $I_{DD5}$ , the injection current may flow out of  $V_{DD5}$  and could result in the external power supply going out of regulation. It is important to ensure that the external  $V_{DD5}$  load will shunt current greater than the maximum injection current. The greatest risk will be when the MCU is consuming very little power (for example, if no system clock is present, or if the clock rate is very low).

### 3.7.2 Power Supply Pins

The  $V_{DDR} - V_{SSR}$  pair supplies the internal voltage regulator. The  $V_{DDA} - V_{SSA}$  pair supplies the A/D converter and the reference circuit of the internal voltage regulator. The  $V_{DDX} - V_{SSX}$  pair supplies the I/O pins.  $V_{DDPLL} - V_{SSPLL}$  pair supplies the oscillator and PLL.

All  $V_{DDX}$  pins are internally connected by metal. All  $V_{SSX}$  pins are internally connected by metal. All  $V_{SS2.5}$  pins are internally connected by metal.  $V_{DDA}$ ,  $V_{DDX}$  and  $V_{DDR}$  as well as  $V_{SSA}$ ,  $V_{SSX}$  and  $V_{SSR}$  are connected by anti-parallel diodes for ESD protection.

### 3.7.3 Supply Current Characteristics

[Table 15](#) and [Table 16](#) list supply current characteristics for MAC71x1 and MAC71x6 devices at 40 MHz and 50 MHz operation, respectively. Characteristics for MAC71x2 devices are to be determined (TBD).

All current measurements are without output loads. Unless otherwise noted the currents are measured in single chip mode, internal voltage regulator enabled at the specified system frequency, using a 4 MHz oscillator in low power mode. Production testing is performed using a square wave signal at the EXTAL input. In expanded modes, the currents are highly dependent on the load and duty cycle on the address, data and control signals, thus no general numbers can be given. A good estimate is to take the single chip currents and add the currents due to the external loads.

Table 15. MAC71x1/6<sup>1</sup> Device Supply Current Characteristics – 40 MHz

| Conditions shown in Table 7, with $f_{SYS} = 40$ MHz. |   |                                            |                             |                  |                                    |                          |         |
|-------------------------------------------------------|---|--------------------------------------------|-----------------------------|------------------|------------------------------------|--------------------------|---------|
| Num                                                   | C | Rating                                     |                             | Symbol           | Typ                                | Max                      | Unit    |
| F1                                                    | P | Run Supply Current, Single Chip            |                             | $I_{DD}R_{reg}$  | 100                                | 130                      | mA      |
| F2                                                    | C | Doze Supply Current                        |                             | $I_{DD}D_{reg}$  | Run $\geq$ Doze $\geq$ Pseudo Stop |                          |         |
| F3                                                    | P | Pseudo Stop Supply Current (OSC on)        | $-40^{\circ}C$ <sup>2</sup> | $I_{DD}PS_{reg}$ | 400 / 500 <sup>3</sup>             | 600 / 700 <sup>3</sup>   | $\mu A$ |
|                                                       | P |                                            | $25^{\circ}C$ <sup>2</sup>  |                  | 400 / 500 <sup>3</sup>             | 600 / 700 <sup>3</sup>   | $\mu A$ |
|                                                       | C |                                            | $85^{\circ}C$ <sup>2</sup>  |                  | 800 / 1000 <sup>3</sup>            | 2000 / 2500 <sup>3</sup> | $\mu A$ |
|                                                       | C |                                            | $105^{\circ}C$ <sup>2</sup> |                  | 1200 / 1500 <sup>3</sup>           | 3500 / 4000 <sup>3</sup> | $\mu A$ |
|                                                       | P |                                            | $125^{\circ}C$ <sup>2</sup> |                  | 1500 / 2000 <sup>3</sup>           | 5500 / 6000 <sup>3</sup> | $\mu A$ |
| F4                                                    | P | Stop Supply Current ( $T_J = T_A$ assumed) | $-40^{\circ}C$ <sup>2</sup> | $I_{DD}S_{reg}$  | 30                                 | 150                      | $\mu A$ |
|                                                       | P |                                            | $25^{\circ}C$ <sup>2</sup>  |                  | 30                                 | 150                      | $\mu A$ |
|                                                       | C |                                            | $85^{\circ}C$ <sup>2</sup>  |                  | 330                                | 2500                     | $\mu A$ |
|                                                       | C |                                            | $105^{\circ}C$ <sup>2</sup> |                  | 470                                | 3500                     | $\mu A$ |
|                                                       | P |                                            | $125^{\circ}C$ <sup>2</sup> |                  | 660                                | 5000                     | $\mu A$ |

## NOTES:

- MAC71x2 characteristics are to be determined (TBD).
- $85^{\circ}C$ ,  $105^{\circ}C$ , and  $125^{\circ}C$  refer to the "C", "V", and "M" Temperature Options, respectively.
- RTI disabled / enabled.

Table 16. MAC71x1/6<sup>1</sup> Device Supply Current Characteristics – 50 MHz

| Conditions shown in Table 7, with $f_{SYS} = 50$ MHz. |   |                                            |                             |                  |                                    |                          |         |
|-------------------------------------------------------|---|--------------------------------------------|-----------------------------|------------------|------------------------------------|--------------------------|---------|
| Num                                                   | C | Rating                                     |                             | Symbol           | Typ                                | Max                      | Unit    |
| G1                                                    | P | Run Supply Current, Single Chip            |                             | $I_{DD}R_{reg}$  | 120                                | 150                      | mA      |
| G2                                                    | C | Doze Supply Current                        |                             | $I_{DD}D_{reg}$  | Run $\geq$ Doze $\geq$ Pseudo Stop |                          |         |
| G3                                                    | P | Pseudo Stop Supply Current (OSC on)        | $-40^{\circ}C$ <sup>2</sup> | $I_{DD}PS_{reg}$ | 400 / 500 <sup>3</sup>             | 600 / 700 <sup>3</sup>   | $\mu A$ |
|                                                       | P |                                            | $25^{\circ}C$ <sup>2</sup>  |                  | 400 / 500 <sup>3</sup>             | 600 / 700 <sup>3</sup>   | $\mu A$ |
|                                                       | C |                                            | $85^{\circ}C$ <sup>2</sup>  |                  | 800 / 1000 <sup>3</sup>            | 2000 / 2500 <sup>3</sup> | $\mu A$ |
|                                                       | C |                                            | $105^{\circ}C$ <sup>2</sup> |                  | 1200 / 1500 <sup>3</sup>           | 3500 / 4000 <sup>3</sup> | $\mu A$ |
|                                                       | P |                                            | $125^{\circ}C$ <sup>2</sup> |                  | 1500 / 2000 <sup>3</sup>           | 5500 / 6000 <sup>3</sup> | $\mu A$ |
| G4                                                    | P | Stop Supply Current ( $T_J = T_A$ assumed) | $-40^{\circ}C$ <sup>2</sup> | $I_{DD}S_{reg}$  | 30                                 | 150                      | $\mu A$ |
|                                                       | P |                                            | $25^{\circ}C$ <sup>2</sup>  |                  | 30                                 | 150                      | $\mu A$ |
|                                                       | C |                                            | $85^{\circ}C$ <sup>2</sup>  |                  | 330                                | 2500                     | $\mu A$ |
|                                                       | C |                                            | $105^{\circ}C$ <sup>2</sup> |                  | 470                                | 3500                     | $\mu A$ |
|                                                       | P |                                            | $125^{\circ}C$ <sup>2</sup> |                  | 660                                | 5000                     | $\mu A$ |

## NOTES:

- MAC71x2 characteristics are to be determined (TBD).
- $85^{\circ}C$ ,  $105^{\circ}C$ , and  $125^{\circ}C$  refer to the "C", "V", and "M" Temperature Options, respectively.
- RTI disabled / enabled.

### 3.7.4 Voltage Regulator Characteristics

Table 17. VREG Operating Conditions

| Num | C | Characteristic                     | Symbol      | Min            | Typical        | Max            | Unit |
|-----|---|------------------------------------|-------------|----------------|----------------|----------------|------|
| H1  | P | Input Voltages                     | $V_{VDDRA}$ | 3.15           | —              | 5.5            | V    |
| H2  | P | Output Voltage, Digital Logic      | $V_{DD2.5}$ |                |                |                |      |
|     |   | Full Performance Mode              |             | 2.45           | 2.5            | 2.75           | V    |
|     |   | Reduced Power Mode                 |             | 1.60           | 2.5            | 2.75           | V    |
|     |   | Shutdown Mode                      |             | — <sup>1</sup> | — <sup>1</sup> | — <sup>1</sup> | V    |
| H3  | P | Output Voltage, PLL                | $V_{DDPLL}$ |                |                |                |      |
|     |   | Full Performance Mode              |             | 2.35           | 2.5            | 2.75           | V    |
|     |   | Reduced Power Mode <sup>2</sup>    |             | 2.00           | 2.5            | 2.75           | V    |
|     |   | Reduced Power Mode <sup>3</sup>    |             | 1.60           | 2.5            | 2.75           | V    |
|     |   | Shutdown Mode                      |             | — <sup>1</sup> | — <sup>1</sup> | — <sup>1</sup> | V    |
| H4  | P | Low Voltage Interrupt <sup>4</sup> |             |                |                |                |      |
|     |   | Assert Level                       | $V_{LVIA}$  | 4.10           | 4.37           | 4.66           | V    |
|     |   | Negate Level                       | $V_{LVID}$  | 4.25           | 4.52           | 4.77           | V    |
| H5  | P | Low Voltage Reset <sup>5</sup>     |             |                |                |                |      |
|     |   | Assert Level                       | $V_{LVRA}$  | 2.25           | 2.35           | —              | V    |
| H6  | P | Power On Reset <sup>6</sup>        |             |                |                |                |      |
|     |   | Assert Level                       | $V_{PORA}$  | 0.97           | —              | —              | V    |
|     |   | Negate Level                       | $V_{PORD}$  | —              | —              | 2.05           | V    |

## NOTES:

1. High impedance output.
2. Current  $I_{DDPLL} = 1$  mA (Low Power Oscillator).
3. Current  $I_{DDPLL} = 3$  mA (Standard Oscillator).
4. Monitors  $V_{DDA}$ , active only in full performance mode. This interrupt indicates that I/O and ATD performance may be degraded due to low supply voltage.
5. Monitors  $V_{DD2.5}$ , active only in full performance mode. Only POR is active in reduced performance mode.
6. Monitors  $V_{DD2.5}$ , active in all modes.

### 3.7.5 Chip Power Up and Voltage Drops

The VREG sub-modules LVI (low voltage interrupt), POR (power on reset) and LVR (low voltage reset) handle chip power-up or drops of the supply voltage. Refer to [Figure 2](#).




Figure 2. VREG Chip Power-up and Voltage Monitoring

### 3.7.6 Output Loads

The on-chip voltage regulator is intended to supply the internal logic and oscillator circuits. No external DC load is allowed. Capacitive loads are specified in [Table 18](#). Capacitors with X7R dielectricum are required.

Table 18. VREG Recommended Load Capacitances

| Rating                                            | Symbol          | Min | Typ | Max   | Unit |
|---------------------------------------------------|-----------------|-----|-----|-------|------|
| Load Capacitance per $V_{DD2.5}$ pin <sup>1</sup> | $C_{LVDD}$      | 200 | 220 | 12000 | nF   |
| Load Capacitance on $V_{DDPLL}$ pin               | $C_{LVDDfcPLL}$ | 90  | 220 | 5000  | nF   |

NOTES:

- Refer to [Table 38](#) for the specific number of  $V_{DD2.5}$  pins on various packages. Each  $V_{DD2.5}$  pin should have the recommended loading as described in Section 3.7.3, "Circuit Board Layout," of the *MAC7100 Microcontroller Family Reference Manual* (MAC7100RM).

## 3.8 Clock and Reset Generator

This section describes the electrical characteristics for the oscillator, phase-locked loop, clock monitor and reset generator.

### 3.8.1 Oscillator Characteristics

The MAC7100 Family features an internal low power loop controlled Pierce oscillator and a full swing Pierce oscillator/external clock mode. The selection of loop controlled Pierce oscillator or full swing Pierce oscillator/external clock depends on the level of the  $\overline{\text{XCLKS}}$  signal at the rising edge of the  $\overline{\text{RESET}}$  signal. Before asserting the oscillator to the internal system clock distribution subsystem, the quality of the oscillation is checked for each start from either power on, STOP or oscillator fail.  $t_{\text{CQOUT}}$  specifies the maximum time before switching to the internal self clock mode after POR or STOP if a proper oscillation is not detected. The quality check also determines the minimum oscillator start-up time  $t_{\text{UPOSC}}$ . The device also features a clock monitor. A Clock Monitor Failure is asserted if the frequency of the incoming clock signal is below the Clock Monitor Assert Frequency  $f_{\text{CMFA}}$ .

**Table 19. Oscillator Characteristics**

| Num | C | Rating                                                      | Symbol                        | Min  | Typ            | Max             | Unit          |
|-----|---|-------------------------------------------------------------|-------------------------------|------|----------------|-----------------|---------------|
| J1a | C | Crystal oscillator range (loop controlled Pierce)           | $f_{\text{OSC}}$ <sup>1</sup> | 4.0  | —              | 16              | MHz           |
| J1b | C | Crystal oscillator range (full swing Pierce) <sup>2 3</sup> | $f_{\text{OSC}}$ <sup>1</sup> | 0.5  | —              | 40              | MHz           |
| J2  | P | Startup Current                                             | $I_{\text{OSC}}$              | 100  | —              | —               | $\mu\text{A}$ |
| J3  | C | Oscillator start-up time (loop controlled Pierce)           | $t_{\text{UPOSC}}$            | —    | 3 <sup>4</sup> | 50 <sup>5</sup> | ms            |
| J4  | D | Clock Quality check time-out                                | $t_{\text{CQOUT}}$            | 0.45 | —              | 2.5             | s             |
| J5  | P | Clock Monitor Failure Assert Frequency                      | $f_{\text{CMFA}}$             | 50   | 100            | 200             | KHz           |
| J6  | P | External square wave input frequency <sup>3</sup>           | $f_{\text{EXT}}$              | 0.5  | —              | 50              | MHz           |
| J7  | D | External square wave pulse width low                        | $t_{\text{EXTL}}$             | 9.5  | —              | —               | ns            |
| J8  | D | External square wave pulse width high                       | $t_{\text{EXTH}}$             | 9.5  | —              | —               | ns            |
| J9  | D | External square wave rise time                              | $t_{\text{EXTR}}$             | —    | —              | 1               | ns            |
| J10 | D | External square wave fall time                              | $t_{\text{EXTF}}$             | —    | —              | 1               | ns            |
| J11 | D | Input Capacitance (EXTAL, XTAL pins)                        | $C_{\text{IN}}$               | —    | 7              | —               | pF            |

**NOTES:**

1. If CLKSEL[PLLSEL] is clear then the system clock ( $f_{\text{SYS}}$ ) is equal to  $f_{\text{OSC}}$ , otherwise it is equal to  $f_{\text{VCO}}$  (table [Table 20, K3](#)). Throughout this document,  $t_{\text{SYS}}$  is used to specify a unit of time equal to  $1 \div f_{\text{SYS}}$ .
2. Depending on the crystal; a damping series resistor might be necessary
3.  $\overline{\text{XCLKS}}$  asserted (low) during reset
4.  $f_{\text{OSC}} = 4 \text{ MHz}$ ,  $C = 22 \text{ pF}$  (refer to the *MAC7100 Microcontroller Family Reference Manual* (MAC7100RM) for circuit board layout recommendations, including oscillator capacitor placement and values).
5. Maximum value is for extreme cases using high Q, low frequency crystals

### 3.8.2 PLL Filter Characteristics

The oscillator provides the reference clock for the PLL as shown in Figure 3. The voltage controlled oscillator (VCO) of the PLL is also the system clock source in self clock mode. In order to operate reliably, care must be taken to select proper values for external loop filter components.




Figure 3. Basic PLL Functional Diagram

The procedure described below can be used to calculate the resistance and capacitance values using typical values for  $K_1$ ,  $f_1$  and  $i_{ch}$  from Table 20. First, the VCO Gain at the desired VCO output frequency is approximated by:

$$K_V = K_1 \cdot e^{\frac{(f_1 - f_{VCO})}{K_1 \cdot 1V}} \quad \text{Eqn. 8}$$

The phase detector relationship is given by:

$$K_\Phi = -|i_{ch}| \cdot K_V \quad \text{Eqn. 9}$$

$i_{ch}$  is the current in tracking mode. The loop bandwidth  $f_C$  should be chosen to fulfill the Gardner's stability criteria by at least a factor of 10, a typical value for the stability factor is 50.  $\zeta = 0.9$  ensures a good transient response.

$$f_C < \frac{2 \cdot \zeta \cdot f_{REF}}{\pi \cdot (\zeta + \sqrt{1 + \zeta^2})} \cdot \frac{1}{10} \rightarrow f_C < \frac{f_{REF}}{4 \cdot 10}; (\zeta = 0.9) \quad \text{Eqn. 10}$$

And finally the frequency relationship is defined as:

$$n = \frac{f_{VCO}}{f_{REF}} = 2 \cdot (\text{SYNR} + 1) \quad \text{Eqn. 11}$$

With the above inputs the resistance can be calculated as:

$$R = \frac{2 \cdot \pi \cdot n \cdot f_C}{K_\Phi} \quad \text{Eqn. 12}$$

The capacitance  $C_S$  can now be calculated as:

$$C_S = \frac{2 \cdot \zeta^2}{\pi \cdot f_C \cdot R} \approx \frac{0.516}{f_C \cdot R}; (\zeta = 0.9) \quad \text{Eqn. 13}$$



The capacitance  $C_P$  should be chosen in the range of:

$$C_S \div 20 \leq C_P \leq C_S \div 10 \quad \text{Eqn. 14}$$

The stabilization delays shown in Table 20 are dependant on PLL operational settings and external component selection (for example, the crystal and XFC filter).

### 3.8.2.1 Jitter Information

With each transition of the clock  $f_{CMP}$ , the deviation from the reference clock  $f_{REF}$  is measured and input voltage to the VCO is adjusted accordingly. The adjustment is done continuously with no abrupt changes in the clock output frequency. Noise, voltage, temperature and other factors cause slight variations in the control loop resulting in a clock jitter. This jitter affects the real minimum and maximum clock periods as illustrated in Figure 4. It is important to note that the pre-scaler used by timers and serial modules will eliminate the effect of PLL jitter to a large extent.




Figure 4. Jitter Definitions

The relative deviation of  $t_{NOM}$  is at its maximum for one clock period, and decreases towards zero for larger number of clock periods ( $N$ ). Thus, jitter is defined as:

$$J(N) = \max\left(\left|1 - \frac{t_{MAX}(N)}{N \cdot t_{NOM}}\right|, \left|1 - \frac{t_{MIN}(N)}{N \cdot t_{NOM}}\right|\right) \quad \text{Eqn. 15}$$

For  $N < 100$ , the following equation is a good fit for the maximum jitter:

$$J(N) = \frac{j_1}{\sqrt{N}} + j_2 \quad \text{Eqn. 16}$$




Figure 5. Maximum Bus Clock Jitter Approximation

### 3.8.3 PLL Characteristics

Table 20. PLL Characteristics

| Num | C | Rating                                                     | Symbol                 | Min | Typ              | Max            | Unit           |
|-----|---|------------------------------------------------------------|------------------------|-----|------------------|----------------|----------------|
| K1  |   | PLL reference frequency, crystal oscillator range          | $f_{REF}$              | 0.5 | —                | 16             | MHz            |
| K2  | P | Self Clock Mode frequency                                  | $f_{SCM}$              | 2   | —                | 5.5            | MHz            |
| K3  | D | VCO locking range                                          | $f_{VCO}$ <sup>1</sup> | 8   | —                | 50             | MHz            |
| K4  | D | Lock Detector transition from Acquisition to Tracking mode | $ \Delta_{trk} $       | 3   | —                | 4              | % <sup>2</sup> |
| K5  | D | Lock Detection                                             | $ \Delta_{Lock} $      | 0   | —                | 1.5            | % <sup>2</sup> |
| K6  | D | Un-Lock Detection                                          | $ \Delta_{unl} $       | 0.5 | —                | 2.5            | % <sup>2</sup> |
| K7  | D | Lock Detector transition from Tracking to Acquisition mode | $ \Delta_{unt} $       | 6   | —                | 8              | % <sup>2</sup> |
| K8  | C | PLLON Total Stabilization delay (Auto Mode) <sup>3</sup>   | $t_{stab}$             | —   | 0.5 <sup>4</sup> | 3 <sup>5</sup> | ms             |
| K9  | D | PLLON Acquisition mode stabilization delay <sup>3</sup>    | $t_{acq}$              | —   | 0.3 <sup>4</sup> | 1 <sup>5</sup> | ms             |
| K10 | D | PLLON Tracking mode stabilization delay <sup>3</sup>       | $t_{al}$               | —   | 0.2 <sup>4</sup> | 2 <sup>5</sup> | ms             |
| K11 | D | Charge pump current acquisition mode                       | $ i_{ch} $             | —   | 38.5             | —              | $\mu A$        |
| K12 | D | Charge pump current tracking mode                          | $ i_{ch} $             | —   | 3.5              | —              | $\mu A$        |
| K13 | D | Jitter fit VCO loop gain parameter                         | $K_1$                  | —   | −195             | —              | MHz/V          |
| K14 | D | Jitter fit VCO loop frequency parameter                    | $f_1$                  | —   | 126              | —              | MHz            |
| K15 | C | Jitter fit parameter 1                                     | $j_1$                  | —   | —                | 1.3            | % <sup>4</sup> |
| K16 | C | Jitter fit parameter 2                                     | $j_2$                  | —   | —                | 0.12           | % <sup>4</sup> |

## NOTES:

1. If CLKSEL[PLLSEL] is set then the system clock ( $f_{SYS}$ ) is equal to  $f_{VCO}$ , otherwise it is equal to  $f_{OSC}$  (table Table 19, J1a or J1b). Throughout this document,  $t_{SYS}$  is used to specify a unit of time equal to  $1 \div f_{SYS}$ .
2. Percentage deviation from target frequency
3. PLL stabilization delay is highly dependent on operational requirement and external component values (for example, crystal and XFC filter component values). Notes 4 and 5 show component values for a typical configurations. Appropriate XFC filter values should be chosen based on operational requirement of system.
4.  $f_{OSC} = 4$  MHz,  $f_{VCO} = 40$  MHz (REFDV = 0x00, SYNRR = 0x04),  $C_S = 2.2$  nF,  $C_P = 220$  pF,  $R_S = 5.6$  K $\Omega$ .
5.  $f_{OSC} = 4$  MHz,  $f_{VCO} = 16$  MHz (REFDV = 0x00, SYNRR = 0x01),  $C_S = 4.7$  nF,  $C_P = 470$  pF,  $R_S = 2.7$  K $\Omega$ .

### 3.8.4 Crystal Monitor Time-out

The time-out Table 21 shows the delay for the crystal monitor to trigger when the clock stops, either at the high or at the low level. The corresponding clock period with an ideal 50% duty cycle is twice this time-out value.

Table 21. Crystal Monitor Time-Outs

| Min | Typ | Max  | Unit    |
|-----|-----|------|---------|
| 6   | 10  | 18.5 | $\mu s$ |

### 3.8.5 Clock Quality Checker

The timing for the clock quality check is derived from the oscillator and the VCO frequency range in Table 20. These numbers define the upper time limit for the individual check windows to complete.

Table 22. CRG Maximum Clock Quality Check Timings

| Clock Check Windows | Value       | Unit |
|---------------------|-------------|------|
| Check Window        | 9.1 to 20.0 | ms   |
| Timeout Window      | 0.46 to 1.0 | s    |

### 3.8.6 Startup

Table 23 summarizes several startup characteristics. Refer to Section 4.3.6.10, “CRG Operating Mode Details,” in the *MAC7100 Microcontroller Family Reference Manual* (MAC7100RM) for details.

Table 23. CRG Startup Characteristics

| Num | C | Rating                                                                | Symbol      | Min | Typ | Max | Unit      |
|-----|---|-----------------------------------------------------------------------|-------------|-----|-----|-----|-----------|
| L1  | D | Reset input pulse width                                               | $PW_{RSTL}$ | 2   | —   | —   | $t_{OSC}$ |
| L2  | D | Startup from Reset                                                    | $n_{RST}$   | 192 | —   | 196 | $t_{OSC}$ |
| L3  | D | $\overline{XIRQ}$ , $\overline{IRQ}$ pulse width, edge-sensitive mode | $PW_{IRQ}$  | 20  | —   | —   | ns        |

#### 3.8.6.1 Power On and Low Voltage Reset (POR and LVR)

The  $V_{PORR}$  and  $V_{PORA}$  levels are derived from  $V_{DD2.5}$ . The  $V_{LVRA}$  level is derived from  $V_{DD2.5}$ . They are also valid if the device is powered externally. After releasing a POR or LVR reset, the oscillator and clock quality checks start. After  $t_{CQOUT}$  (Table 19, J4) if no valid oscillation is detected, the MCU will start using the internal self-generated clock. The minimum startup time is given by  $t_{uposc}$  (Table 19, J3).

#### 3.8.6.2 SRAM Data Retention

SRAM content integrity is guaranteed if the CRGFLG[PORF] bit is not set following a reset operation.

#### 3.8.6.3 External Reset

When external reset is asserted for a time greater than  $PW_{RSTL}$ , the CRG generates an internal reset and the CPU fetches the reset vector without a clock quality check, if there was stable oscillation before reset.

#### 3.8.6.4 Stop Recovery

The MCU can return from stop to run mode in response to an external interrupt or an API. Two delays occur before the MCU resumes execution. First, the voltage regulator must exit reduced power mode and return to full performance mode (this assumes that the internal regulator is used rather than driving  $V_{DD2.5}$  and  $V_{DDPLL}$  with an external regulator). Second, a clock quality check is performed in the same manner as for a power-on reset before releasing the clocks to the system.

#### 3.8.6.5 Pseudo Stop Recovery

Recovery from pseudo stop mode is similar to stop mode in that the VREG must return to FPM, but since the oscillator is not stopped there is no delay for clock stabilization. The MCU is returned to run mode by internal or external interrupts.

#### 3.8.6.6 Doze Recovery

Recovery from doze mode avoids both the VREG and oscillator recovery periods. The MCU is returned to run mode by internal or external interrupts.

## 3.9 External Bus Timing

Table 24 lists processor bus input timings, which are shown in Figure 6, Figure 7 and Figure 8.

### NOTE


All processor bus timings are synchronous; that is, input setup/hold and output delay with respect to the rising edge of a reference clock. The reference clock is the CLKOUT output. All other timing relationships can be derived from these values.

**Table 24. External Bus Input Timing Specifications<sup>1</sup>**

| Num            | C | Rating                                             | Symbol      | Min | Max | Unit |
|----------------|---|----------------------------------------------------|-------------|-----|-----|------|
| M1             | P | CLKOUT period <sup>2</sup>                         | $t_{CYC}$   | 20  | —   | ns   |
| Control Inputs |   |                                                    |             |     |     |      |
| M2a            | P | Control input valid to CLKOUT high <sup>3</sup>    | $t_{CVCH}$  | 13  | —   | ns   |
| M3a            | P | CLKOUT high to control inputs invalid <sup>3</sup> | $t_{CHCII}$ | 0   | —   | ns   |
| Data Inputs    |   |                                                    |             |     |     |      |
| M4             | P | Data input (DATA[15:0]) valid to CLKOUT high       | $t_{DIVCH}$ | 9   | —   | ns   |
| M5             | P | CLKOUT high to data input (DATA[15:0]) invalid     | $t_{CHDII}$ | 0   | —   | ns   |

#### NOTES:

- Assumes CLKOUT is configured for full drive strength (via the PIM CONFIG2\_D[RDS] bit).
- CLKOUT is equal to the system clock,  $f_{SYS}$ . If CLKSEL[PLLSEL] is set then  $f_{SYS}$  is equal to  $f_{VCO}$  (table Table 20, K3); if it is clear then  $f_{SYS}$  is equal to  $f_{OSC}$  (table Table 19, J1a or J1b). Throughout this document,  $t_{CYC}$  is used to specify a unit of time equal to  $1 \div \text{CLKOUT}$  (which is equal to  $t_{f_{SYS}}$ ).
- The  $\overline{TA}$  pin is the only control input on MAC7100 family devices.



**Figure 6. General Input Timing Requirements**

### 3.9.1 Read and Write Bus Cycles


Table 25 lists processor bus output timings. Read/write bus timings listed in Table 25 are shown in Figure 7 and Figure 8.

**Table 25. External Bus Output Timing Specifications<sup>1</sup>**

| Num                                  | C | Rating                                                                                        | Symbol      | Min              | Max               | Unit |
|--------------------------------------|---|-----------------------------------------------------------------------------------------------|-------------|------------------|-------------------|------|
| <b>Control Outputs</b>               |   |                                                                                               |             |                  |                   |      |
| M6a                                  | P | CLKOUT high <sup>2</sup> to chip selects ( $\overline{CS}[2:0]$ ) valid                       | $t_{CHCV}$  | —                | $0.5t_{CYC} + 10$ | ns   |
| M6b                                  | P | CLKOUT high <sup>2</sup> to byte selects ( $\overline{BS}[1:0]$ ) valid                       | $t_{CHBV}$  | —                | $0.5t_{CYC} + 10$ | ns   |
| M6c                                  | P | CLKOUT high <sup>2</sup> to output select ( $\overline{OE}$ ) valid                           | $t_{CHOV}$  | —                | $0.5t_{CYC} + 10$ | ns   |
| M6d                                  | P | CLKOUT high <sup>2</sup> to address strobe ( $\overline{AS}$ ) valid                          | $t_{CHASV}$ | —                | $0.5t_{CYC} + 10$ | ns   |
| M7a                                  | P | CLKOUT high <sup>2</sup> to control output ( $\overline{BS}[1:0]$ , $\overline{OE}$ ) invalid | $t_{CHCOI}$ | $0.5t_{CYC} + 2$ | —                 | ns   |
| M7b                                  | P | CLKOUT high <sup>2</sup> to chip selects ( $\overline{CS}[2:0]$ ) invalid                     | $t_{CHCI}$  | $0.5t_{CYC} + 2$ | —                 | ns   |
| M7c                                  | P | CLKOUT high <sup>2</sup> to address strobe ( $\overline{AS}$ ) invalid                        | $t_{CHASI}$ | $0.5t_{CYC} + 2$ | —                 | ns   |
| <b>Address and Attribute Outputs</b> |   |                                                                                               |             |                  |                   |      |
| M8                                   | P | CLKOUT high to address (ADDR[21:0]) and control (R/W) valid                                   | $t_{CHAV}$  | —                | 10                | ns   |
| M9                                   | P | CLKOUT high to address (ADDR[21:0]) and control (R/W) invalid                                 | $t_{CHAI}$  | 2                | —                 | ns   |
| <b>Data Outputs</b>                  |   |                                                                                               |             |                  |                   |      |
| M10                                  | P | CLKOUT high to data output (DATA[15:0]) valid                                                 | $t_{CHDOV}$ | —                | 13                | ns   |
| M11                                  | P | CLKOUT high to data output (DATA[15:0]) invalid                                               | $t_{CHDOI}$ | 2                | —                 | ns   |
| M12                                  | D | CLKOUT high to data output (DATA[15:0]) high impedance                                        | $t_{CHDOZ}$ | —                | 9                 | ns   |


**NOTES:**

1. Assumes CLKOUT,  $\overline{CSn}$ ,  $\overline{BSn}$ ,  $\overline{OE}$ ,  $\overline{AS}$ , ADDR[21:0] and DATA[15:0] are configured for full drive strength (via the PIM).
2. The  $\overline{CSn}$ ,  $\overline{BSn}$ ,  $\overline{OE}$  and  $\overline{AS}$  signals are synchronous to the falling edge of CLKOUT. Therefore, changes on these signals are triggered by the falling edge of CLKOUT, even though they are specified in relation to the rising edge.



1. The  $\overline{TA}$  /  $\overline{AS}$  signals are multiplexed on a single pin, so only one function may be used during bus transactions.

**Figure 7. Read/Write Bus Cycles, Internal Termination**



1. The  $\overline{TA}$  /  $\overline{AS}$  signals are multiplexed on a single pin, so AS is not available when external cycle termination is used.

**Figure 8. Read Bus Cycle, External Termination**

### 3.10 Analog-to-Digital Converter

Table 26 and Table 27 show conditions under which the ATD operates. The following constraints exist to obtain full-scale, full range results:  $V_{SSA} \leq V_{RL} \leq V_{IN} \leq V_{RH} \leq V_{DDA}$ . This constraint exists because the sample buffer amplifier cannot drive beyond the ATD power supply levels. If the input level goes outside of this range it will effectively be clipped.

**Table 26. ATD Operating Characteristics in 5.0 V Range**

| Conditions shown in Table 7 unless otherwise noted |   |                                                                                           |                              |                               |        |                               |                   |
|----------------------------------------------------|---|-------------------------------------------------------------------------------------------|------------------------------|-------------------------------|--------|-------------------------------|-------------------|
| Num                                                | C | Rating                                                                                    | Symbol                       | Min                           | Typ    | Max                           | Unit              |
| N1                                                 | D | Reference Potential<br>Low<br>High                                                        | $V_{RL}$<br>$V_{RH}$         | $V_{SSA}$<br>$V_{DDA} \div 2$ | —<br>— | $V_{DDA} \div 2$<br>$V_{DDA}$ | V<br>V            |
| N2                                                 | C | Differential Reference Voltage <sup>1</sup>                                               | $V_{RH} - V_{RL}$            | 4.50                          | 5.00   | 5.50                          | V                 |
| N3                                                 | D | ATD Clock Frequency                                                                       | $f_{ATDCLK}$                 | 0.5                           | —      | 2.0                           | MHz               |
| N4                                                 | D | ATD 10-bit Conversion Period<br>$f_{ATDCLK}$ Cycles <sup>2</sup><br>@ 2.0MHz $f_{ATDCLK}$ | $N_{CONV10}$<br>$T_{CONV10}$ | 14<br>7                       | —<br>— | 28<br>14                      | Cycles<br>$\mu s$ |
| N5                                                 | D | ATD 8-bit Conversion Period<br>$f_{ATDCLK}$ Cycles <sup>2</sup><br>@ 2.0MHz $f_{ATDCLK}$  | $N_{CONV8}$<br>$T_{CONV8}$   | 12<br>6                       | —<br>— | 26<br>13                      | Cycles<br>$\mu s$ |
| N6                                                 | D | Stop Recovery Time ( $V_{DDA} = 5.0$ V)                                                   | $T_{REC}$                    | —                             | —      | 20                            | $\mu s$           |
| N7                                                 | P | Reference Supply current 1 ATD module on                                                  | $I_{REF}$                    | —                             | 0.200  | 0.255                         | mA                |
| N8                                                 | P | Reference Supply current 2 ATD modules on                                                 | $I_{REF}$                    | —                             | 0.400  | 0.510                         | mA                |

NOTES:

1. Full accuracy is not guaranteed when differential voltage is less than 4.50 V

2. Minimum time assumes a sample period of 2 ATD clocks; maximum time assumes a sample period of 16 ATD clocks.

**Table 27. ATD Operating Characteristics in 3.3 V Range**

| Conditions shown in Table 7, with $V_{DDX} = 3.3$ V $-5/+10\%$ and a temperature maximum of $+140^{\circ}\text{C}$ unless otherwise noted. |   |                                                                                           |                              |                               |        |                               |                   |
|--------------------------------------------------------------------------------------------------------------------------------------------|---|-------------------------------------------------------------------------------------------|------------------------------|-------------------------------|--------|-------------------------------|-------------------|
| Num                                                                                                                                        | C | Rating                                                                                    | Symbol                       | Min                           | Typ    | Max                           | Unit              |
| P1                                                                                                                                         | D | Reference Potential<br>Low<br>High                                                        | $V_{RL}$<br>$V_{RH}$         | $V_{SSA}$<br>$V_{DDA} \div 2$ | —<br>— | $V_{DDA} \div 2$<br>$V_{DDA}$ | V<br>V            |
| P2                                                                                                                                         | C | Differential Reference Voltage <sup>1</sup>                                               | $V_{RH} - V_{RL}$            | 3.15                          | 3.3    | 3.6                           | V                 |
| P3                                                                                                                                         | D | ATD Clock Frequency                                                                       | $f_{ATDCLK}$                 | 0.5                           | —      | 2.0                           | MHz               |
| P4                                                                                                                                         | D | ATD 10-bit Conversion Period<br>$f_{ATDCLK}$ Cycles <sup>2</sup><br>@ 2.0MHz $f_{ATDCLK}$ | $N_{CONV10}$<br>$T_{CONV10}$ | 14<br>7                       | —<br>— | 28<br>14                      | Cycles<br>$\mu s$ |
| P5                                                                                                                                         | D | ATD 8-bit Conversion Period<br>$f_{ATDCLK}$ Cycles <sup>2</sup><br>@ 2.0MHz $f_{ATDCLK}$  | $N_{CONV8}$<br>$T_{CONV8}$   | 12<br>6                       | —<br>— | 26<br>13                      | Cycles<br>$\mu s$ |
| P6                                                                                                                                         | D | Stop Recovery Time ( $V_{DDA} = 3.3$ V)                                                   | $T_{REC}$                    | —                             | —      | 20                            | $\mu s$           |
| P7                                                                                                                                         | P | Reference Supply current 1 ATD module on                                                  | $I_{REF}$                    | —                             | 0.130  | 0.170                         | mA                |
| P8                                                                                                                                         | P | Reference Supply current 2 ATD modules on                                                 | $I_{REF}$                    | —                             | 0.260  | 0.340                         | mA                |

NOTES:

1. Full accuracy is not guaranteed when differential voltage is less than 3.15 V

2. Minimum time assumes a sample period of 2 ATD clocks; maximum time assumes a sample period of 16 ATD clocks.



### 3.10.1 Factors Influencing Accuracy

Three factors—source resistance, source capacitance and current injection—have an influence on the accuracy of the ATD.

#### 3.10.1.1 Source Resistance

Due to the input pin leakage current as specified in [Table 8](#) in conjunction with the source resistance there will be a voltage drop from the signal source to the ATD input. The maximum specified source resistance  $R_S$ , results in an error of less than 1/2 LSB (2.5 mV) at the maximum leakage current. If the device or operating conditions are less than the worst case, or leakage-induced errors are acceptable, larger values of source resistance are allowed.

#### 3.10.1.2 Source Capacitance

When sampling, an additional internal capacitor is switched to the input. This can cause a voltage drop due to charge sharing with the external capacitance and the pin capacitance. For a maximum sampling error of the input voltage  $\leq 1$  LSB, then the external filter capacitor must be calculated as,  $C_f \geq 1024 \times (C_{INS} - C_{INN})$ .

#### 3.10.1.3 Current Injection

There are two cases to consider:

1. A current is injected into the channel being converted. The channel being stressed has conversion values of 0x3FF (0xFF in 8-bit mode) for analog inputs greater than  $V_{RH}$  and 0x000 for values less than  $V_{RL}$  unless the current is higher than specified as disruptive condition.
2. Current is injected into pins in the neighborhood of the channel being converted. A portion of this current is picked up by the channel (coupling ratio  $K$ ), This additional current impacts the accuracy of the conversion depending on the source resistance. The additional input voltage error on the converted channel can be calculated as  $V_{ERR} = K \times R_S \times I_{INJ}$ , with  $I_{INJ}$  being the sum of the currents injected into the two pins adjacent to the converted channel.

**Table 28. ATD Electrical Characteristics**

| Conditions are shown in <a href="#">Table 7</a> unless otherwise noted |   |                                           |                        |      |     |     |            |
|------------------------------------------------------------------------|---|-------------------------------------------|------------------------|------|-----|-----|------------|
| Num                                                                    | C | Rating                                    | Symbol                 | Min  | Typ | Max | Unit       |
| Q1                                                                     | C | Max input Source Resistance               | $R_S$                  | —    | —   | 1   | k $\Omega$ |
| Q2                                                                     | C | Total Input Capacitance                   | $C_{INN}$<br>$C_{INS}$ | —    | 10  | —   | pF         |
|                                                                        |   | Non Sampling<br>Sampling                  |                        | —    | 22  | —   | pF         |
| Q3                                                                     | C | Disruptive Analog Input Current           | $I_{NA}$               | –2.5 | —   | 2.5 | mA         |
| Q4                                                                     | C | Coupling Ratio positive current injection | $K_p$                  | —    | —   | TBD | A / A      |
| Q5                                                                     | C | Coupling Ratio negative current injection | $K_n$                  | —    | —   | TBD | A / A      |

### 3.10.2 ATD Accuracy

Table 29 and Table 30 specify the ATD conversion performance excluding any errors due to current injection, input capacitance and source resistance.

**Table 29. ATD Conversion Performance in 5.0 V Range**

| Conditions shown in Table 7 except as noted here:<br>f <sub>ATDCLK</sub> = 2.0 MHz, 4.5 V ≤ V <sub>DDA</sub> ≤ 5.5 V |   |                                    |        |      |                 |     |        |
|----------------------------------------------------------------------------------------------------------------------|---|------------------------------------|--------|------|-----------------|-----|--------|
| Num                                                                                                                  | C | Rating                             | Symbol | Min  | Typ             | Max | Unit   |
| R1                                                                                                                   | P | 10-bit Resolution                  | LSB    | —    | 5 <sup>1</sup>  | —   | mV     |
| R2                                                                                                                   | P | 10-bit Differential Nonlinearity   | DNL    | −1   | —               | 1   | Counts |
| R3                                                                                                                   | P | 10-bit Integral Nonlinearity       | INL    | −2.5 | ±1.5            | 2.5 | Counts |
| R4                                                                                                                   | P | 10-bit Absolute Error <sup>2</sup> | AE     | −3   | ±2.0            | 3   | Counts |
| R5                                                                                                                   | P | 8-bit Resolution                   | LSB    | —    | 20 <sup>1</sup> | —   | mV     |
| R6                                                                                                                   | P | 8-bit Differential Nonlinearity    | DNL    | −0.5 | —               | 0.5 | Counts |
| R7                                                                                                                   | P | 8-bit Integral Nonlinearity        | INL    | −1.0 | ±0.5            | 1.0 | Counts |
| R8                                                                                                                   | P | 8-bit Absolute Error <sup>2</sup>  | AE     | −1.5 | ±1.0            | 1.5 | Counts |

NOTES:

1. Assumes V<sub>REF</sub> = V<sub>RH</sub> − V<sub>RL</sub> = 5.12 V, other V<sub>REF</sub> conditions result in different LSB resolutions.
2. These values include the quantization error which is inherently ½ count for any A/D converter.

**Table 30. ATD Conversion Performance in 3.3 V Range**

| Conditions shown in Table 7 except as noted here:<br>f <sub>ATDCLK</sub> = 2.0 MHz, 3.15 V ≤ V <sub>DDA</sub> ≤ 3.6 V |   |                                    |        |      |                   |     |        |
|-----------------------------------------------------------------------------------------------------------------------|---|------------------------------------|--------|------|-------------------|-----|--------|
| Num                                                                                                                   | C | Rating                             | Symbol | Min  | Typ               | Max | Unit   |
| S1                                                                                                                    | P | 10-bit Resolution                  | LSB    | —    | 3.25 <sup>1</sup> | —   | mV     |
| S2                                                                                                                    | P | 10-bit Differential Nonlinearity   | DNL    | −1.5 | —                 | 1.5 | Counts |
| S3                                                                                                                    | P | 10-bit Integral Nonlinearity       | INL    | −3.5 | ±1.5              | 3.5 | Counts |
| S4                                                                                                                    | P | 10-bit Absolute Error <sup>2</sup> | AE     | −5   | ±2.0              | 5   | Counts |
| S5                                                                                                                    | P | 8-bit Resolution                   | LSB    | —    | 13 <sup>1</sup>   | —   | mV     |
| S6                                                                                                                    | P | 8-bit Differential Nonlinearity    | DNL    | −0.5 | —                 | 0.5 | Counts |
| S7                                                                                                                    | P | 8-bit Integral Nonlinearity        | INL    | −1.5 | ±1.0              | 1.5 | Counts |
| S8                                                                                                                    | P | 8-bit Absolute Error <sup>2</sup>  | AE     | −1.5 | ±1.0              | 1.5 | Counts |

NOTES:

1. Assumes V<sub>REF</sub> = V<sub>RH</sub> − V<sub>RL</sub> = 3.33 V, other V<sub>REF</sub> conditions result in different LSB resolutions.
2. These values include the quantization error which is inherently ½ count for any A/D converter.

For the following definitions, see Figure 9.

Differential Non-Linearity (DNL) is defined as the difference between two adjacent switching steps:

$$\text{DNL}(i) = \frac{V_i - V_{i-1}}{1 \text{ LSB}} - 1 \quad \text{Eqn. 17}$$

The Integral Non-Linearity (INL) is defined as the sum of all DNLs:

$$\text{INL}(n) = \sum_{i=1}^n \text{DNL}(i) = \frac{V_n - V_0}{1 \text{ LSB}} - n \quad \text{Eqn. 18}$$




Figure 9. ATD Accuracy Definitions

**NOTE**

Figure 9 shows only definitions, for specification values refer to [Table 29](#).

### 3.10.3 ATD Timing Specifications

Table 31. ATD External Trigger Timing Specifications

| Num | C | Parameter                                   | Symbol       | Min                          | Max | Unit                |
|-----|---|---------------------------------------------|--------------|------------------------------|-----|---------------------|
| T1  | D | ETRIG Period (Level-Sensitive Trigger Mode) | $T_{PERIOD}$ | $1 + N_{CONVn}$ <sup>1</sup> | —   | $f_{ATDCLK}$ Cycles |
| T2  | D | ETRIG Minimum Pulse Width                   | $t_{PW}$     | 1                            | —   | $f_{ATDCLK}$ Cycles |
|     |   | Edge-Sensitive Trigger Mode                 |              | 2                            | —   |                     |
| T3  | D | ETRIG Level Recovery <sup>2</sup>           | $t_{LR}$     | 1                            | —   | $f_{ATDCLK}$ Cycles |
| T4  | D | Conversion Start Delay                      | $t_{DLY}$    | —                            | 2   | $f_{ATDCLK}$ Cycles |

## NOTES:

- $N_{CONVn}$  denotes 8- or 10-bit conversion time (refer to specifications N4, N5, P4 and P5). In order to achieve the minimum period between conversions when using level-sensitive triggering, ETRIG must remain asserted this long.
- Time prior to the end of a conversion that ETRIG must be negated in order to prevent the start of another conversion.




Figure 10. ATD External Trigger Timing Diagram

## 3.11 Serial Peripheral Interface

### 3.11.1 Master Mode

Master mode timing values are shown in Table 32 and illustrated in Figure 11 and Figure 12.

**Table 32. SPI Master Mode Timing Characteristics**

| Conditions are shown in Table 7 unless otherwise noted, C <sub>LOAD</sub> = 200 pF on all outputs |   |                                                                       |                        |                             |     |                            |           |
|---------------------------------------------------------------------------------------------------|---|-----------------------------------------------------------------------|------------------------|-----------------------------|-----|----------------------------|-----------|
| Num                                                                                               | C | Rating                                                                | Symbol                 | Min                         | Typ | Max                        | Unit      |
| U1a                                                                                               | P | Operating Frequency (baud rate)                                       | $f_{OP}$ <sup>1</sup>  | $\frac{1}{7 \times 32,678}$ | —   | $\frac{1}{2}$ <sup>2</sup> | $f_{IPS}$ |
| U1b                                                                                               | P | SCK Period ( $t_{SCK} = 1 \div f_{OP}$ , $t_{IPS} = 1 \div f_{IPS}$ ) | $t_{SCK}$ <sup>1</sup> | $2$ <sup>2</sup>            | —   | $7 \times 32,768$          | $t_{IPS}$ |
| U2                                                                                                | D | Enable Lead Time                                                      | $t_{lead}$             | $\frac{1}{2}$               | —   | —                          | $t_{SCK}$ |
| U3                                                                                                | D | Enable Lag Time                                                       | $t_{lag}$              | $\frac{1}{2}$               | —   | —                          | $t_{SCK}$ |
| U4                                                                                                | D | Clock (SCK) High or Low Time                                          | $t_{wsck}$             | $t_{IPS} - 30$              | —   | $1024 t_{IPS}$             | ns        |
| U5                                                                                                | D | Data Setup Time (Inputs)                                              | $t_{su}$               | 25                          | —   | —                          | ns        |
| U6                                                                                                | D | Data Hold Time (Inputs)                                               | $t_{hi}$               | 0                           | —   | —                          | ns        |
| U9                                                                                                | D | Data Valid (after Enable Edge)                                        | $t_v$                  | —                           | —   | 25                         | ns        |
| U10                                                                                               | D | Data Hold Time (Outputs)                                              | $t_{ho}$               | 0                           | —   | —                          | ns        |
| U11                                                                                               | D | Rise Time Inputs and Outputs                                          | $t_r$                  | —                           | —   | 25                         | ns        |
| U12                                                                                               | D | Fall Time Inputs and Outputs                                          | $t_f$                  | —                           | —   | 25                         | ns        |

NOTES:

1. Refer to MAC7100 Microcontroller Family Reference Manual (MAC7100RM) Chapter 22 for all available baud rates.
2. On mask set L49P and L47W devices, U1a maximum =  $\frac{1}{4}$  and U1b minimum = 4.

### 3.11.2 Slave Mode


Slave mode timing values are shown in Table 33 and illustrated in Figure 13 and Figure 14.

**Table 33. SPI Slave Mode Timing Characteristics**

| Conditions are shown in Table 7 unless otherwise noted, C <sub>LOAD</sub> = 200 pF on all outputs |   |                                                                       |            |                             |     |                            |           |
|---------------------------------------------------------------------------------------------------|---|-----------------------------------------------------------------------|------------|-----------------------------|-----|----------------------------|-----------|
| Num                                                                                               | C | Rating                                                                | Symbol     | Min                         | Typ | Max                        | Unit      |
| V1a                                                                                               | P | Operating Frequency                                                   | $f_{OP}$   | $\frac{1}{7 \times 32,678}$ | —   | $\frac{1}{2}$ <sup>1</sup> | $f_{IPS}$ |
| V1b                                                                                               | P | SCK Period ( $t_{SCK} = 1 \div f_{OP}$ , $t_{IPS} = 1 \div f_{IPS}$ ) | $t_{SCK}$  | $2$ <sup>1</sup>            | —   | $7 \times 32,768$          | $t_{IPS}$ |
| V2                                                                                                | D | Enable Lead Time                                                      | $t_{lead}$ | 1                           | —   | —                          | $t_{IPS}$ |
| V3                                                                                                | D | Enable Lag Time                                                       | $t_{lag}$  | 1                           | —   | —                          | $t_{IPS}$ |
| V4                                                                                                | D | Clock (SCK) High or Low Time                                          | $t_{wsck}$ | $t_{IPS} - 30$              | —   | —                          | ns        |
| V5                                                                                                | D | Data Setup Time (Inputs)                                              | $t_{su}$   | 25                          | —   | —                          | ns        |
| V6                                                                                                | D | Data Hold Time (Inputs)                                               | $t_{hi}$   | 25                          | —   | —                          | ns        |
| V7                                                                                                | D | Slave Access Time                                                     | $t_a$      | —                           | —   | 1                          | $t_{IPS}$ |
| V8                                                                                                | D | Slave SIN Disable Time                                                | $t_{dis}$  | —                           | —   | 1                          | $t_{IPS}$ |
| V9                                                                                                | D | Data Valid (after SCK Edge)                                           | $t_v$      | —                           | —   | 25                         | ns        |
| V10                                                                                               | D | Data Hold Time (Outputs)                                              | $t_{ho}$   | 0                           | —   | —                          | ns        |
| V11                                                                                               | D | Rise Time Inputs and Outputs                                          | $t_r$      | —                           | —   | 25                         | ns        |
| V12                                                                                               | D | Fall Time Inputs and Outputs                                          | $t_f$      | —                           | —   | 25                         | ns        |


NOTES:

1. On mask set L49P and L47W devices, V1a maximum =  $\frac{1}{4}$  and V1b minimum = 4.



1. If configured as output.
2. LSBFE = 0. For LSBFE = 1, bit order is LSB, bit 1, ..., bit 6, MSB.

**Figure 11. SPI Master Timing (CPHA = 0)**



1. If configured as output.
2. LSBFE = 0. For LSBFE = 1, bit order is LSB, bit 1, ..., bit 6, MSB.

**Figure 12. SPI Master Timing (CPHA = 1)**




Figure 13. SPI Slave Timing (CPHA = 0)




Figure 14. SPI Slave Timing (CPHA = 1)

## 3.12 FlexCAN Interface

Table 34. FlexCAN Wake-up Pulse Characteristics

| Conditions are shown in Table 7 unless otherwise noted |   |                                         |           |     |     |     |               |
|--------------------------------------------------------|---|-----------------------------------------|-----------|-----|-----|-----|---------------|
| Num                                                    | C | Rating                                  | Symbol    | Min | Typ | Max | Unit          |
| W1                                                     | P | FlexCAN Wake-up dominant pulse filtered | $t_{WUP}$ | —   | —   | 2   | $\mu\text{s}$ |
| W2                                                     | P | FlexCAN Wake-up dominant pulse passed   | $t_{WUP}$ | 5   | —   | —   | $\mu\text{s}$ |

## 3.13 Common Flash Module

### NOTE

Unless otherwise noted the abbreviation NVM (Non-Volatile Memory) is used for both program Flash and data Flash.

The time base for all program and data Flash operations,  $f_{NVMOP}$  is derived from the IPS bus clock,  $f_{IPS}$ , using the CFMCLKD register to control the divider ratio. Throughout this section,  $t_{IPS}$  refers to  $1 \div f_{IPS}$ , and  $t_{NVMOP}$  refers to  $1 \div f_{NVMOP}$ . An  $f_{NVMOP}$  frequency range limit is imposed for performing program or erase operations. The CFM does not monitor the frequency and will not prevent program or erase operation at frequencies above or below the following limits:

$$150 \text{ KHz} < f_{NVMOP} \leq 200 \text{ KHz} \quad \text{Eqn. 19}$$

$f_{NVMOP} = 200 \text{ KHz}$  gives the fastest program and erase performance. Setting CFMCLKD to a value such that  $f_{NVMOP} < 150 \text{ KHz}$  should be avoided, as this can damage the Flash memory due to overstress. Setting CFMCLKD to a value such that  $f_{NVMOP} > 200 \text{ KHz}$  can result in incomplete programming or erasure of the Flash memory array cells.

### 3.13.1 Mass Erase Timing

The time required to erase the entire NVM array (both program and data) is calculated using the formula:

$$t_{\text{mass}} \approx 20000 \cdot t_{NVMOP} \quad \text{Eqn. 20}$$

The setup time can be ignored for this operation.

### 3.13.2 Blank Check Timing

The time it takes to perform a blank check on the program or data Flash is dependant on the location of the first non-blank word, starting from relative address zero. One  $f_{IPS}$  cycle is required per word to be verified, and the time required for the operation is calculated using the formula:

$$t_{\text{check}} = (\text{locations} + 15) \cdot t_{IPS} \quad \text{Eqn. 21}$$



### 3.13.3 Page Erase Timing

The time required to erase a 4 Kbyte program or 1 Kbyte data Flash logical page is calculated using the formulas:

$$t_{\text{erap}} = 4096 \cdot t_{\text{NVMOP}} + 15 \cdot t_{\text{IPS}} \quad \text{Eqn. 22}$$

$$t_{\text{erad}} = 1024 \cdot t_{\text{NVMOP}} + 15 \cdot t_{\text{IPS}} \quad \text{Eqn. 23}$$

### 3.13.4 Page Erase Verify Timing

The time required to verify that a program Flash page is erased depends on the location of the first non-blank word. The time required for the operation is calculated using the formula:

$$t_{\text{pevp}} = \left[ \left( \frac{4 \times 1024}{4} \right) + 15 \right] \times t_{\text{IPS}} \quad \text{Eqn. 24}$$

The time required to verify that a data Flash page is erased is calculated using the formula:

$$t_{\text{pevd}} = \left[ \left( \frac{1 \times 1024}{4} \right) + 15 \right] \times t_{\text{IPS}} \quad \text{Eqn. 25}$$

### 3.13.5 Programming Timing

Programming time is dependant on the  $f_{\text{IPS}}$  and  $f_{\text{NVMOP}}$  frequencies, and is calculated for a single word using the formula:

$$t_{\text{swpgm}} = 9 \cdot t_{\text{NVMOP}} + 25 \cdot t_{\text{IPS}} \quad \text{Eqn. 26}$$

Burst programming can be utilized with the program Flash, where up to 32 words in a row can be programmed consecutively by keeping the command pipeline filled. The time to program a consecutive word is calculated using the formula:

$$t_{\text{bwpgm}} = 4 \cdot t_{\text{NVMOP}} + 9 \cdot t_{\text{IPS}} \quad \text{Eqn. 27}$$

Therefore, the time to program a 32-word row is calculated using the formula:

$$t_{\text{brpgm}} = t_{\text{swpgm}} + 31 \cdot t_{\text{bwpgm}} \quad \text{Eqn. 28}$$

Note that burst programming is more than 2 times faster than single word programming.

### 3.13.6 Data Signature Timing<sup>1</sup>

The time required to perform a data signature command is dependant on the number of words or half-words compressed during the operation, and is calculated using the formula:

$$t_{\text{dsig}} = (\text{Words or Half-Words} + 15) \cdot t_{\text{IPS}} \quad \text{Eqn. 29}$$

1. This feature is not available on mask set L49P and L47W devices.

### 3.13.7 CFM Timing Specifications

Table 35 lists the time required to execute various operations described in the Section 3.13.1 through Section 3.13.6. For operating conditions other than those assumed below, Equation 19 through Equation 29 must be used to calculate the timing for specific commands under those conditions.

**Table 35. CFM Timing Characteristics**

| Conditions are shown in Table 7 unless otherwise noted |   |                                                           |                   |                            |     |                 |               |
|--------------------------------------------------------|---|-----------------------------------------------------------|-------------------|----------------------------|-----|-----------------|---------------|
| Num                                                    | C | Rating                                                    | Symbol            | Min                        | Typ | Max             | Unit          |
| X1                                                     | D | System Clock                                              | $f_{NVM/f_{sys}}$ | 0.5                        | —   | 50 <sup>1</sup> | MHz           |
| X2                                                     | D | Bus frequency for Programming or Erase Operations         | $f_{NVM/f_{ips}}$ | 1                          | —   | —               | MHz           |
| X3                                                     | D | Program/Erase Operating Frequency                         | $f_{NVMOP}$       | 150                        | —   | 200             | kHz           |
| X4                                                     | P | Programming Time, <sup>2</sup><br>Single Word             | $t_{swpgm}$       | $f_{sys} = 50 \text{ MHz}$ | —   | 71.0            | $\mu\text{s}$ |
|                                                        |   |                                                           |                   | $f_{sys} = 40 \text{ MHz}$ | —   | 71.0            |               |
| X5                                                     | D | Programming Time, <sup>2</sup><br>Consecutive Word Burst  | $t_{bwpgm}$       | $f_{sys} = 50 \text{ MHz}$ | —   | 30.5            | $\mu\text{s}$ |
|                                                        |   |                                                           |                   | $f_{sys} = 40 \text{ MHz}$ | —   | 30.5            |               |
| X6                                                     | D | Programming Time, <sup>2</sup><br>32-word Row Burst       | $t_{brpgm}$       | $f_{sys} = 50 \text{ MHz}$ | —   | 1,016.5         | $\mu\text{s}$ |
|                                                        |   |                                                           |                   | $f_{sys} = 40 \text{ MHz}$ | —   | 1,016.5         |               |
| X7a                                                    | P | Page Erase Time, <sup>2</sup><br>Program Flash            | $t_{erap}$        | $f_{sys} = 50 \text{ MHz}$ | —   | 26.6            | ms            |
|                                                        |   |                                                           |                   | $f_{sys} = 40 \text{ MHz}$ | —   | 26.6            |               |
| X7b                                                    | P | Page Erase Time, <sup>2</sup><br>Data Flash               | $t_{erad}$        | $f_{sys} = 50 \text{ MHz}$ | —   | 6.7             | ms            |
|                                                        |   |                                                           |                   | $f_{sys} = 40 \text{ MHz}$ | —   | 6.7             |               |
| X8                                                     | P | Mass Erase Time <sup>2</sup>                              | $t_{mass}$        | 100                        | —   | 130             | ms            |
| X9a                                                    | D | Blank Check Time, <sup>3</sup><br>Program Flash per Block | $t_{bcheckp}$     | MAC71x1, MAC71x6           | —   | 131,087         | $t_{ips}$     |
|                                                        |   |                                                           |                   | MAC71x2                    | —   | 65,551          |               |
| X9b                                                    | D | Blank Check Time, <sup>3</sup><br>Data Flash per Block    | $t_{bcheckd}$     | 16                         | —   | 8,207           | $t_{ips}$     |
| X9c                                                    | D | Page Erase Verify Time <sup>3</sup>                       | Program Flash     | $t_{pevp}$                 | —   | 1,039           | $t_{ips}$     |
|                                                        |   |                                                           | Data Flash        | $t_{pevd}$                 | —   | 271             |               |
| X10                                                    | D | Data Signature Time <sup>4</sup>                          | MAC71x6, Program  | $t_{dsig}$                 | —   | 262,159         | $t_{ips}$     |
|                                                        |   |                                                           | MAC71x1, Program  |                            | —   | 131,087         |               |
|                                                        |   |                                                           | MAC71x2, Program  |                            | —   | 65,551          |               |
|                                                        |   |                                                           | MAC71xx, Data     |                            | —   | 16,399          |               |

**NOTES:**

- Subject to restrictions in Table 19 and Table 20 for operating characteristics of the oscillator and PLL.
- Minimum erase and programming times are achieved with the indicated maximum  $f_{sys}$  (which is  $f_{ips} \times 2$ , and subject to the limits of Table 19 and Table 20) and corresponding maximum  $f_{NVMOP}$ . Maximum erase and programming times are dependent on the combination of  $f_{NVMOP}$  and  $f_{ips}$ ; values shown are calculated for  $f_{ips} = 2 \text{ MHz}$  and  $f_{NVMOP} = 154 \text{ kHz}$ .
- Minimum blank check or page erase verify time assumes the first word in the array is blank and the second is not. Maximum blank check or page erase verify time assumes the entire block or page is blank.
- Data signature timing is dependant on the number of words or half-words compressed for the program and data arrays, respectively. Minimum time is for two words or half-words; maximum time is for the entire array.

### 3.13.8 NVM Reliability

The reliability of the NVM blocks is guaranteed by stress test during qualification, constant process monitors and burn-in to screen early life failures. The failure rates for data retention and program/erase cycling are specified at the operating conditions noted. The program/erase cycle count on the sector is incremented every time a sector or mass erase event is executed.

**Table 36. NVM Reliability Characteristics**

| Conditions shown in <a href="#">Table 7</a> unless otherwise noted. |   |                                                            |        |        |
|---------------------------------------------------------------------|---|------------------------------------------------------------|--------|--------|
| Num                                                                 | C | Rating                                                     | Min    | Unit   |
| X11                                                                 | C | Program/Data Flash Program/Erase endurance (–40C to +125C) | 10,000 | Cycles |
| X12                                                                 | C | Program/Data Flash Data Retention Lifetime                 | 15     | Years  |

#### NOTE

All values shown in [Table 36](#) are target values and subject to characterization. For Flash cycling performance, each program operation must be preceded by an erase.

## 4 Device Pin Assignments

The MAC7100 Family is available in 208-pin ball grid array (MAP BGA), 144-pin low profile quad flat (LQFP), 112-pin LQFP, and 100-pin LQFP package options. The family of devices offer pin-compatible packaged devices to assist with system development and accommodate a direct application enhancement path. Refer to [Table 2](#) for a comparison of the peripheral sets and package options for each device.

Most pins perform two or more functions, which are described in more detail in the *MAC7100 Microcontroller Family Reference Manual* (MAC7100RM). [Table 37](#), [Table 38](#) and [Figure 15](#) through [Figure 22](#) show the pin assignments for various devices and packages.

**Table 37. Signal Pin Assignments**

| Primary /<br>GPIO<br>Function | Peripheral<br>Function <sup>1</sup> | External<br>Bus<br>Function <sup>1</sup> | Debug<br>Function <sup>1</sup> | Read on<br>Reset | Pin Number (by Device) |              |      |              |      |      |      |              |
|-------------------------------|-------------------------------------|------------------------------------------|--------------------------------|------------------|------------------------|--------------|------|--------------|------|------|------|--------------|
|                               |                                     |                                          |                                |                  | 7101<br>7106           | 7111<br>7116 | 7112 | 7121<br>7126 | 7122 | 7131 | 7136 | 7141<br>7142 |
| EXTAL                         | —                                   | —                                        | —                              | —                | 60                     | 60           | 60   | 48           | 48   | T10  | T10  | 45           |
| XTAL                          | —                                   | —                                        | —                              | —                | 61                     | 61           | 61   | 49           | 49   | T11  | T11  | 46           |
| XFC                           | —                                   | —                                        | —                              | —                | 58                     | 58           | 58   | 46           | 46   | T9   | T9   | 43           |
| RESET                         | —                                   | —                                        | —                              | —                | 48                     | 48           | 48   | 36           | 36   | T7   | T7   | 33           |
| TDI                           | —                                   | —                                        | —                              | —                | 128                    | 128          | 128  | 102          | 102  | A8   | A8   | 93           |
| TDO                           | —                                   | —                                        | —                              | —                | 129                    | 129          | 129  | 103          | 103  | B8   | B8   | 94           |
| TCK                           | —                                   | —                                        | —                              | —                | 130                    | 130          | 130  | 104          | 104  | A7   | A7   | 95           |
| TMS                           | —                                   | —                                        | —                              | —                | 131                    | 131          | 131  | 105          | 105  | B7   | B7   | 96           |
| —                             | —                                   | TA / AS <sup>2</sup>                     | —                              | —                | —                      | 79           | —    | —            | —    | M14  | M14  | —            |
| PA0                           | —                                   | DATA0 <sup>3</sup>                       | MCKO <sup>4</sup>              | —                | 138                    | 138          | 138  | 106          | 106  | B5   | B5   | —            |
| PA1                           | —                                   | DATA1 <sup>3</sup>                       | EVTO                           | —                | 137                    | 137          | 137  | —            | —    | C5   | C5   | —            |
| PA2                           | —                                   | DATA2 <sup>3</sup>                       | EVTI                           | —                | 136                    | 136          | 136  | —            | —    | A5   | A5   | —            |
| PA3                           | —                                   | DATA3 <sup>3</sup>                       | MDO0                           | —                | 135                    | 135          | 135  | —            | —    | C6   | C6   | —            |
| PA4                           | —                                   | DATA4 <sup>3</sup>                       | MDO1                           | —                | 134                    | 134          | 134  | —            | —    | B6   | B6   | —            |
| PA5                           | —                                   | DATA5 <sup>3</sup>                       | MSE0                           | —                | 133                    | 133          | 133  | —            | —    | A6   | A6   | —            |
| PA6                           | —                                   | DATA6 <sup>3</sup>                       | RDY                            | —                | 132                    | 132          | 132  | —            | —    | C7   | C7   | —            |
| PA7                           | —                                   | DATA7 <sup>3</sup>                       | —                              | —                | —                      | 98           | 98   | 74           | 74   | H15  | H15  | 65           |
| PA8                           | —                                   | DATA8 <sup>3</sup>                       | —                              | —                | —                      | 97           | 97   | 73           | 73   | H13  | H13  | 64           |
| PA9                           | —                                   | DATA9 <sup>3</sup>                       | —                              | —                | —                      | 96           | 96   | 72           | 72   | H14  | H14  | 63           |
| PA10                          | —                                   | DATA10 <sup>3</sup>                      | —                              | —                | —                      | 95           | 95   | 71           | 71   | H16  | H16  | —            |
| PA11                          | —                                   | DATA11 <sup>3</sup>                      | —                              | —                | —                      | 94           | 94   | 70           | 70   | J15  | J15  | —            |
| PA12                          | —                                   | DATA12 <sup>3</sup>                      | —                              | —                | —                      | 93           | 93   | 69           | 69   | J14  | J14  | —            |
| PA13                          | —                                   | DATA13 <sup>3</sup>                      | —                              | —                | 67                     | 67           | 67   | 53           | 53   | R12  | R12  | —            |
| PA14                          | —                                   | DATA14 <sup>3</sup>                      | —                              | PS <sup>3</sup>  | 66                     | 66           | 66   | 52           | 52   | T12  | T12  | —            |
| PA15                          | —                                   | DATA15 <sup>3</sup>                      | —                              | AA <sup>3</sup>  | 65                     | 65           | 65   | 51           | 51   | P11  | P11  | 48           |
| PB0                           | SDA                                 | —                                        | —                              | —                | 15                     | 15           | 15   | 11           | 11   | G1   | G1   | 8            |
| PB1                           | SCL                                 | —                                        | —                              | —                | 16                     | 16           | 16   | 12           | 12   | H3   | H3   | 9            |
| PB2                           | SIN_A                               | —                                        | —                              | —                | 17                     | 17           | 17   | 13           | 13   | H2   | H2   | 10           |
| PB3                           | SOUT_A                              | —                                        | —                              | —                | 18                     | 18           | 18   | 14           | 14   | H1   | H1   | 11           |
| PB4                           | SCK_A                               | —                                        | —                              | —                | 19                     | 19           | 19   | 15           | 15   | J3   | J3   | 12           |
| PB5                           | PCS0_A /<br>SS_A                    | —                                        | —                              | —                | 20                     | 20           | 20   | 16           | 16   | J1   | J1   | 13           |
| PB6                           | PCS1_A                              | —                                        | —                              | —                | 21                     | 21           | 21   | 17           | 17   | J2   | J2   | 14           |
| PB7                           | PCS2_A                              | —                                        | —                              | —                | 22                     | 22           | 22   | 18           | 18   | K1   | K1   | 15           |

Table 37. Signal Pin Assignments (continued)

| Primary /<br>GPIO<br>Function | Peripheral<br>Function <sup>1</sup> | External<br>Bus<br>Function <sup>1</sup> | Debug<br>Function <sup>1</sup> | Read on<br>Reset | Pin Number (by Device) |              |      |                 |      |      |      |              |
|-------------------------------|-------------------------------------|------------------------------------------|--------------------------------|------------------|------------------------|--------------|------|-----------------|------|------|------|--------------|
|                               |                                     |                                          |                                |                  | 7101<br>7106           | 7111<br>7116 | 7112 | 7121<br>7126    | 7122 | 7131 | 7136 | 7141<br>7142 |
| PB8                           | PCS5_A /<br>PCSS_A                  | —                                        | —                              | —                | 23                     | 23           | 23   | 19              | 19   | K2   | K2   | 16           |
| PB9                           | PCS0_B /<br>SS_B                    | —                                        | —                              | —                | 72                     | 72           | 72   | 56              | 56   | T14  | T14  | 51           |
| PB10                          | PCS5_B /<br>PCSS_B                  | —                                        | —                              | —                | 73                     | 73           | 73   | 57 <sup>5</sup> | 57   | R14  | R14  | 52           |
| PB11                          | PCS2_B                              | —                                        | —                              | —                | 74                     | 74           | 74   | — <sup>5</sup>  | —    | N14  | N14  | 53           |
| PB12                          | PCS1_B                              | —                                        | —                              | —                | 75                     | 75           | 75   | 58              | 58   | P15  | P15  | 54           |
| PB13                          | SCK_B                               | —                                        | —                              | —                | 76                     | 76           | 76   | 59              | 59   | P16  | P16  | 55           |
| PB14                          | SOUT_B                              | —                                        | —                              | —                | 77                     | 77           | 77   | 60              | 60   | N15  | N15  | 56           |
| PB15                          | SIN_B                               | —                                        | —                              | —                | 78                     | 78           | 78   | 61              | 61   | N16  | N16  | 57           |
| PC0                           | —                                   | ADDR0 <sup>3</sup>                       | —                              | —                | 9                      | 9            | 9    | —               | —    | F1   | F1   | —            |
| PC1                           | —                                   | ADDR1 <sup>3</sup>                       | —                              | —                | 10                     | 10           | 10   | —               | —    | F3   | F3   | —            |
| PC2                           | —                                   | ADDR2 <sup>3</sup>                       | —                              | —                | 11                     | 11           | 11   | —               | —    | G2   | G2   | —            |
| PC3                           | —                                   | ADDR3 <sup>3</sup>                       | —                              | —                | 12                     | 12           | 12   | —               | —    | G3   | G3   | —            |
| PC4                           | —                                   | ADDR4 <sup>3</sup>                       | —                              | —                | 28                     | 28           | 28   | —               | —    | L3   | L3   | —            |
| PC5                           | —                                   | ADDR5 <sup>3</sup>                       | —                              | —                | 29                     | 29           | 29   | —               | —    | M2   | M2   | —            |
| PC6                           | —                                   | ADDR6 <sup>3</sup>                       | —                              | —                | 30                     | 30           | 30   | —               | —    | M3   | M3   | —            |
| PC7                           | —                                   | ADDR7 <sup>3</sup>                       | —                              | —                | 31                     | 31           | 31   | —               | —    | N3   | N3   | —            |
| PC8                           | —                                   | ADDR8 <sup>3</sup>                       | —                              | —                | 44                     | 44           | 44   | —               | —    | P5   | P5   | —            |
| PC9                           | —                                   | ADDR9 <sup>3</sup>                       | —                              | —                | 45                     | 45           | 45   | —               | —    | R6   | R6   | —            |
| PC10                          | —                                   | ADDR10 <sup>3</sup>                      | —                              | —                | 46                     | 46           | 46   | —               | —    | P6   | P6   | —            |
| PC11                          | —                                   | ADDR11 <sup>3</sup>                      | —                              | —                | 47                     | 47           | 47   | —               | —    | T6   | T6   | —            |
| PC12                          | —                                   | ADDR12 <sup>3</sup>                      | —                              | —                | —                      | 88           | 88   | —               | —    | K14  | K14  | —            |
| PC13                          | —                                   | ADDR13 <sup>3</sup>                      | —                              | —                | —                      | 89           | 89   | —               | —    | K13  | K13  | —            |
| PC14                          | —                                   | ADDR14 <sup>3</sup>                      | —                              | —                | —                      | 90           | 90   | —               | —    | K15  | K15  | —            |
| PC15                          | —                                   | ADDR15 <sup>3</sup>                      | —                              | —                | —                      | 91           | 91   | 67              | 67   | J16  | J16  | —            |
| PD0                           | —                                   | BS0 <sup>3</sup>                         | —                              | MODB             | 70                     | 70           | 70   | 54              | 54   | T13  | T13  | 49           |
| PD1                           | —                                   | BS1 <sup>3</sup>                         | —                              | MODA             | 71                     | 71           | 71   | 55              | 55   | R13  | R13  | 50           |
| PD2 <sup>6</sup>              | —                                   | CLKOUT                                   | —                              | XCLKS            | 80                     | 80           | 80   | 62              | 62   | M16  | M16  | 58           |
| PD3                           | XIRQ                                | —                                        | —                              | —                | 81                     | 81           | 81   | 63              | 63   | M15  | M15  | 59           |
| PD4                           | IRQ                                 | —                                        | —                              | —                | 82                     | 82           | 82   | 64              | 64   | L16  | L16  | 60           |
| PD5                           | —                                   | ADDR16 <sup>3</sup>                      | —                              | —                | —                      | 92           | 92   | 68              | 68   | J13  | J13  | —            |
| PD6                           | —                                   | ADDR17 <sup>3</sup>                      | —                              | —                | —                      | 119          | 119  | 95              | 95   | C10  | C10  | 86           |
| PD7                           | —                                   | ADDR18 <sup>3</sup>                      | —                              | —                | —                      | 120          | 120  | 96              | 96   | D10  | D10  | 87           |
| PD8                           | —                                   | ADDR19 <sup>3</sup>                      | —                              | —                | —                      | 121          | 121  | 97              | 97   | D9   | D9   | 88           |
| PD9                           | —                                   | ADDR20 <sup>3</sup>                      | —                              | —                | —                      | 122          | 122  | 98              | 98   | B9   | B9   | 89           |
| PD10                          | —                                   | ADDR21 <sup>3</sup>                      | —                              | —                | —                      | 123          | 123  | 99              | 99   | D8   | D8   | 90           |
| PD11                          | —                                   | OE <sup>3</sup>                          | —                              | —                | 68                     | 68           | 68   | —               | —    | P12  | P12  | —            |
| PD12                          | —                                   | CS2 <sup>3</sup>                         | —                              | —                | 69                     | 69           | 69   | —               | —    | P13  | P13  | —            |
| PD13                          | —                                   | CS1 <sup>3</sup>                         | —                              | —                | 83                     | 83           | 83   | —               | —    | L13  | L13  | —            |
| PD14                          | —                                   | CS0 <sup>3</sup>                         | —                              | —                | 84                     | 84           | 84   | —               | —    | L14  | L14  | —            |
| PD15                          | —                                   | R/W <sup>3</sup>                         | —                              | —                | 85                     | 85           | 85   | —               | —    | L15  | L15  | —            |
| PE0                           | AN0_A                               | —                                        | MCKO'                          | —                | 89                     | 99           | 99   | 75              | 75   | G16  | G16  | 66           |
| PE1                           | AN1_A                               | —                                        | EVTO'                          | —                | 91                     | 100          | 100  | 76              | 76   | G15  | G15  | 67           |

Table 37. Signal Pin Assignments (continued)

| Primary /<br>GPIO<br>Function | Peripheral<br>Function <sup>1</sup> | External<br>Bus<br>Function <sup>1</sup> | Debug<br>Function <sup>1</sup> | Read on<br>Reset | Pin Number (by Device) |              |      |              |      |      |      |              |
|-------------------------------|-------------------------------------|------------------------------------------|--------------------------------|------------------|------------------------|--------------|------|--------------|------|------|------|--------------|
|                               |                                     |                                          |                                |                  | 7101<br>7106           | 7111<br>7116 | 7112 | 7121<br>7126 | 7122 | 7131 | 7136 | 7141<br>7142 |
| PE2                           | AN2_A                               | —                                        | EVTI'                          | —                | 93                     | 101          | 101  | 77           | 77   | F13  | F13  | 68           |
| PE3                           | AN3_A                               | —                                        | MDO0'                          | —                | 95                     | 102          | 102  | 78           | 78   | F14  | F14  | 69           |
| PE4                           | AN4_A                               | —                                        | MDO1'                          | —                | 97                     | 103          | 103  | 79           | 79   | E13  | E13  | 70           |
| PE5                           | AN5_A                               | —                                        | MSEO'                          | —                | 99                     | 104          | 104  | 80           | 80   | E14  | E14  | 71           |
| PE6                           | AN6_A                               | —                                        | RDY'                           | —                | 101                    | 105          | 105  | 81           | 81   | D15  | D15  | 72           |
| PE7                           | AN7_A                               | —                                        | —                              | —                | 103                    | 106          | 106  | 82           | 82   | C15  | C15  | 73           |
| PE8                           | AN8_A                               | —                                        | —                              | —                | 105                    | 107          | 107  | 83           | 83   | C14  | C14  | 74           |
| PE9                           | AN9_A                               | —                                        | —                              | —                | 107                    | 108          | 108  | 84           | 84   | D14  | D14  | 75           |
| PE10                          | AN10_A                              | —                                        | —                              | —                | 113                    | 113          | 113  | 89           | 89   | B13  | B13  | 80           |
| PE11                          | AN11_A                              | —                                        | —                              | —                | 115                    | 114          | 114  | 90           | 90   | C12  | C12  | 81           |
| PE12                          | AN12_A                              | —                                        | —                              | —                | 117                    | 115          | 115  | 91           | 91   | A12  | A12  | 82           |
| PE13                          | AN13_A                              | —                                        | —                              | —                | 119                    | 116          | 116  | 92           | 92   | B11  | B11  | 83           |
| PE14                          | AN14_A                              | —                                        | —                              | —                | 121                    | 117          | 117  | 93           | 93   | A10  | A10  | 84           |
| PE15                          | AN15_A                              | —                                        | —                              | —                | 123                    | 118          | 118  | 94           | 94   | A9   | A9   | 85           |
| PF0                           | eMIOS0                              | —                                        | Debug Status <sup>7</sup>      | NEXPS            | 43                     | 43           | 43   | 35           | 35   | T5   | T5   | 32           |
| PF1                           | eMIOS1                              | —                                        | Debug Status <sup>7</sup>      | NEXPR            | 42                     | 42           | 42   | 34           | 34   | R5   | R5   | 31           |
| PF2                           | eMIOS2                              | —                                        | Debug Status <sup>7</sup>      | —                | 41                     | 41           | 41   | 33           | 33   | T4   | T4   | 30           |
| PF3                           | eMIOS3                              | —                                        | Debug Status <sup>7</sup>      | —                | 40                     | 40           | 40   | 32           | 32   | R4   | R4   | 29           |
| PF4                           | eMIOS4                              | —                                        | Debug Status <sup>7</sup>      | —                | 39                     | 39           | 39   | 31           | 31   | T3   | T3   | 28           |
| PF5                           | eMIOS5                              | —                                        | Debug Status <sup>7</sup>      | —                | 38                     | 38           | 38   | 30           | 30   | P4   | P4   | 27           |
| PF6                           | eMIOS6                              | —                                        | Debug Status <sup>7</sup>      | —                | 37                     | 37           | 37   | 29           | 29   | R3   | R3   | 26           |
| PF7                           | eMIOS7                              | —                                        | Debug Status <sup>7</sup>      | —                | 36                     | 36           | 36   | 28           | 28   | R1   | R1   | 25           |
| PF8                           | eMIOS8                              | —                                        | Debug Status <sup>7</sup>      | —                | 35                     | 35           | 35   | 27           | 27   | P2   | P2   | 24           |
| PF9                           | eMIOS9                              | —                                        | Debug Status <sup>7</sup>      | —                | 34                     | 34           | 34   | 26           | 26   | P1   | P1   | 23           |
| PF10                          | eMIOS10                             | —                                        | Debug Status <sup>7</sup>      | —                | 33                     | 33           | 33   | 25           | 25   | N2   | N2   | 22           |
| PF11                          | eMIOS11                             | —                                        | Debug Status <sup>7</sup>      | —                | 32                     | 32           | 32   | 24           | 24   | N1   | N1   | 21           |
| PF12                          | eMIOS12                             | —                                        | Debug Status <sup>7</sup>      | —                | 27                     | 27           | 27   | 23           | 23   | M1   | M1   | 20           |
| PF13                          | eMIOS13                             | —                                        | Debug Status <sup>7</sup>      | —                | 26                     | 26           | 26   | 22           | 22   | L2   | L2   | 19           |
| PF14                          | eMIOS14                             | —                                        | Debug Status <sup>7</sup>      | —                | 25                     | 25           | 25   | 21           | 21   | L1   | L1   | 18           |
| PF15                          | eMIOS15                             | —                                        | Debug Status <sup>7</sup>      | —                | 24                     | 24           | 24   | 20           | 20   | K3   | K3   | 17           |
| PG0                           | RXD_B                               | —                                        | —                              | —                | 141                    | 141          | 141  | 109          | 109  | A3   | A3   | 97           |
| PG1                           | TXD_B                               | —                                        | —                              | —                | 142                    | 142          | 142  | 110          | 110  | C4   | C4   | 98           |
| PG2                           | RXD_A                               | —                                        | —                              | —                | 143                    | 143          | 143  | 111          | 111  | B3   | B3   | 99           |
| PG3                           | TXD_A                               | —                                        | —                              | —                | 144                    | 144          | 144  | 112          | 112  | C2   | C2   | 100          |
| PG4                           | CNTX_A                              | —                                        | —                              | —                | 1                      | 1            | 1    | 1            | 1    | D3   | D3   | 1            |
| PG5                           | CNRX_A                              | —                                        | —                              | —                | 2                      | 2            | 2    | 2            | 2    | C1   | C1   | 2            |
| PG6                           | CNTX_B                              | —                                        | —                              | —                | 7                      | 7            | 7    | 7            | 7    | E1   | E1   | 3            |
| PG7                           | CNRX_B                              | —                                        | —                              | —                | 8                      | 8            | 8    | 8            | 8    | F2   | F2   | 4            |
| PG8                           | CNTX_C <sup>8</sup>                 | —                                        | —                              | —                | 3                      | 3            | 3    | 3            | 3    | D2   | D2   | —            |
| PG9                           | CNRX_C <sup>8</sup>                 | —                                        | —                              | —                | 4                      | 4            | 4    | 4            | 4    | D1   | D1   | —            |
| PG10                          | CNTX_D <sup>8</sup>                 | —                                        | —                              | —                | 5                      | 5            | 5    | 5            | 5    | E3   | E3   | —            |
| PG11                          | CNRX_D <sup>8</sup>                 | —                                        | —                              | —                | 6                      | 6            | 6    | 6            | 6    | E2   | E2   | —            |
| PG12                          | RXD_D <sup>8</sup>                  | —                                        | —                              | —                | 51                     | 51           | 51   | 39           | 39   | R7   | R7   | 36           |
| PG13                          | TXD_D <sup>8</sup>                  | —                                        | —                              | —                | 52                     | 52           | 52   | 40           | 40   | R8   | R8   | 37           |

Table 37. Signal Pin Assignments (continued)

| Primary /<br>GPIO<br>Function | Peripheral<br>Function <sup>1</sup> | External<br>Bus<br>Function <sup>1</sup> | Debug<br>Function <sup>1</sup> | Read on<br>Reset | Pin Number (by Device) |              |      |              |      |      |      |              |
|-------------------------------|-------------------------------------|------------------------------------------|--------------------------------|------------------|------------------------|--------------|------|--------------|------|------|------|--------------|
|                               |                                     |                                          |                                |                  | 7101<br>7106           | 7111<br>7116 | 7112 | 7121<br>7126 | 7122 | 7131 | 7136 | 7141<br>7142 |
| PG14                          | RXD_C                               | —                                        | —                              | —                | 139                    | 139          | 139  | 107          | 107  | A4   | A4   | —            |
| PG15                          | TXD_C                               | —                                        | —                              | —                | 140                    | 140          | 140  | 108          | 108  | B4   | B4   | —            |
| PH0                           | AN0_B                               | —                                        | —                              | —                | 88                     | —            | —    | —            | —    | G13  | G13  | —            |
| PH1                           | AN1_B                               | —                                        | —                              | —                | 90                     | —            | —    | —            | —    | G14  | G14  | —            |
| PH2                           | AN2_B                               | —                                        | —                              | —                | 92                     | —            | —    | —            | —    | F16  | F16  | —            |
| PH3                           | AN3_B                               | —                                        | —                              | —                | 94                     | —            | —    | —            | —    | F15  | F15  | —            |
| PH4                           | AN4_B                               | —                                        | —                              | —                | 96                     | —            | —    | —            | —    | E16  | E16  | —            |
| PH5                           | AN5_B                               | —                                        | —                              | —                | 98                     | —            | —    | —            | —    | E15  | E15  | —            |
| PH6                           | AN6_B                               | —                                        | —                              | —                | 100                    | —            | —    | —            | —    | D16  | D16  | —            |
| PH7                           | AN7_B                               | —                                        | —                              | —                | 102                    | —            | —    | —            | —    | C16  | C16  | —            |
| PH8                           | AN8_B                               | —                                        | —                              | —                | 104                    | —            | —    | —            | —    | B16  | B16  | —            |
| PH9                           | AN9_B                               | —                                        | —                              | —                | 106                    | —            | —    | —            | —    | B14  | B14  | —            |
| PH10                          | AN10_B                              | —                                        | —                              | —                | 108                    | —            | —    | —            | —    | D13  | D13  | —            |
| PH11                          | AN11_B                              | —                                        | —                              | —                | 114                    | —            | —    | —            | —    | A13  | A13  | —            |
| PH12                          | AN12_B                              | —                                        | —                              | —                | 116                    | —            | —    | —            | —    | B12  | B12  | —            |
| PH13                          | AN13_B                              | —                                        | —                              | —                | 118                    | —            | —    | —            | —    | C11  | C11  | —            |
| PH14                          | AN14_B                              | —                                        | —                              | —                | 120                    | —            | —    | —            | —    | A11  | A11  | —            |
| PH15                          | AN15_B                              | —                                        | —                              | —                | 122                    | —            | —    | —            | —    | B10  | B10  | —            |
| PI0                           | PCS3_A                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | C3   | —            |
| PI1                           | PCS4_A                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | D5   | —            |
| PI2                           | PCS6_A                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | D4   | —            |
| PI3                           | PCS7_A                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | E4   | —            |
| PI4                           | PCS3_B                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | G4   | —            |
| PI5                           | PCS4_B                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | J4   | —            |
| PI6                           | PCS6_B                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | K4   | —            |
| PI7                           | PCS7_B                              | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | L4   | —            |
| PI8                           | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | N4   | —            |
| PI9                           | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | P3   | —            |
| PI10                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | R2   | —            |
| PI11                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | R15  | —            |
| PI12                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | N11  | —            |
| PI13                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | N12  | —            |
| PI14                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | N13  | —            |
| PI15                          | —                                   | —                                        | —                              | —                | —                      | —            | —    | —            | —    | —    | P14  | —            |

## NOTES:

1. The MAC7100 family maximum peripheral configurations are listed in these columns. Some family members do not implement the full complement of ATD, CAN, DSPI and eSCI peripherals. Refer to [Table 2 on page 3](#) for availability of peripheral functions on various devices.
2. AS function not available on mask set L49P devices.
3. MAC7111, MAC7116, MAC7131 and MAC7136 only.
4. The MCKO function cannot be used on MAC7121 devices (the alternate Nexus port must be used).
5. On MAC7121 mask set L49P devices, PB11 / PCS2\_B is bonded out on pin 57.
6. PD2 function not available on mask set L49P devices.
7. Optional debug status port not available on mask set L49P devices.
8. CAN C, CAN D and eSCI D not available on MAC7112, MAC7122 and MAC7142 devices.

Table 38. Power Supply, Voltage Regulator and Reference Pin Assignments


| Pin Name           | Pin Number (by Device)                                    |                    |                                                                                                                                                                                                                                               |             |
|--------------------|-----------------------------------------------------------|--------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
|                    | 7101 / 7106 /<br>7111 / 7112 / 7116                       | 7121 / 7122 / 7126 | 7131 / 7136                                                                                                                                                                                                                                   | 7141 / 7142 |
| V <sub>DDX</sub>   | 14, 50, 64, 87, 124                                       | 10, 38, 66         | C9, H4, K16, P7, P10                                                                                                                                                                                                                          | 6, 35, 62   |
| V <sub>SSX</sub>   | 13, 49, 63, 86, 125<br><br>7101 / 7106 / 7112 only:<br>79 | 9, 37, 65          | A1, A2, B1, B2, F4, G7,<br>G8, G9, G10, H7, H8, H9,<br>H10, J7, J8, J9, J10, K7,<br>K8, K9, K10, M4, M13,<br>R9, R10, R16, T1, T2,<br>T15, T16<br><br>7131 only:<br>C3, D4, D5, E4, G4, J4,<br>K4, L4, N4, N11, N12,<br>N13, P3, P14, R9, R10 | 5, 34, 61   |
| V <sub>DDR</sub>   | 56                                                        | 44                 | P9                                                                                                                                                                                                                                            | 41          |
| V <sub>SSR</sub>   | 55                                                        | 43                 | N5, N6                                                                                                                                                                                                                                        | 40          |
| V <sub>DD2.5</sub> | 53, 127                                                   | 41, 101            | C8, P8                                                                                                                                                                                                                                        | 38, 92      |
| V <sub>SS2.5</sub> | 54, 126                                                   | 42, 100            | D6, D7, N7, N8                                                                                                                                                                                                                                | 39, 91      |
| V <sub>DDPLL</sub> | 57                                                        | 45                 | T8                                                                                                                                                                                                                                            | 42          |
| V <sub>SSPLL</sub> | 59                                                        | 47                 | N9, N10                                                                                                                                                                                                                                       | 44          |
| V <sub>DDA</sub>   | 109                                                       | 85                 | A16, B15, C13                                                                                                                                                                                                                                 | 76          |
| V <sub>SSA</sub>   | 112                                                       | 88                 | D11, D12                                                                                                                                                                                                                                      | 79          |
| V <sub>RH</sub>    | 110                                                       | 86                 | A15                                                                                                                                                                                                                                           | 77          |
| V <sub>RL</sub>    | 111                                                       | 87                 | A14                                                                                                                                                                                                                                           | 78          |
| TEST <sup>1</sup>  | 62                                                        | 50                 | R11                                                                                                                                                                                                                                           | 47          |
| N/C                | —                                                         | —                  | —                                                                                                                                                                                                                                             | 7           |

## NOTES:

1. This pin is reserved for Freescale factory testing, and must be tied to system ground in all applications.



## 4.1 MAC7141 Pin Diagram



1. PD2 function not available on L49P mask set devices.

**Figure 15. Pin Assignments for MAC7141 in 100-pin LQFP**

## 4.2 MAC7142 Pin Diagram





Figure 16. Pin Assignments for MAC7142 in 100-pin LQFP

## 4.3 MAC7121 / MAC7126 Pin Diagram



1. PD2 function not available on L49P mask set devices.

2. On L49P mask set devices, PB11 / PCS2\_B is bonded out on pin 57.

**Figure 17. Pin Assignments for MAC7121 / MAC7126 in 112-pin LQFP**

## 4.4 MAC7122 Pin Diagram





Figure 18. Pin Assignments for MAC7122 in 112-pin LQFP


## 4.5 MAC7101 / MAC7106 Pin Diagram



1. PD2 function not available on L49P mask set devices.

**Figure 19. Pin Assignments for MAC7101 / MAC7106 in 144-pin LQFP**

## 4.6 MAC7111 / MAC7116 Pin Diagram



1. PD2 function not available on L49P mask set devices.

**Figure 20. Pin Assignments for MAC7111 / MAC7116 in 144-pin LQFP**

## 4.7 MAC7112 Pin Diagram




Figure 21. Pin Assignments for MAC7112 in 144-pin LQFP

## 4.8 MAC7131 Pin Diagram

|   | 1                 | 2                 | 3                 | 4                 | 5                 | 6                   | 7                         | 8                   | 9                   | 10                  | 11                | 12                | 13                | 14                                       | 15                | 16                 |
|---|-------------------|-------------------|-------------------|-------------------|-------------------|---------------------|---------------------------|---------------------|---------------------|---------------------|-------------------|-------------------|-------------------|------------------------------------------|-------------------|--------------------|
| A | V <sub>SS</sub> X | V <sub>SS</sub> X | PG0               | PG14              | PA2               | PA5                 | TCK                       | TDI                 | PE15                | PE14                | PH14              | PE12              | PH11              | V <sub>RL</sub>                          | V <sub>RH</sub>   | V <sub>DD</sub> A  |
| B | V <sub>SS</sub> X | V <sub>SS</sub> X | PG2               | PG15              | PA0               | PA4                 | TMS                       | TDO                 | PD9                 | PH15                | PE13              | PH12              | PE10              | PH9                                      | V <sub>DD</sub> A | PH8                |
| C | PG5               | PG3               | V <sub>SS</sub> X | PG1               | PA1               | PA3                 | PA6                       | V <sub>DD</sub> 2.5 | V <sub>DD</sub> X   | PD6                 | PH13              | PE11              | V <sub>DD</sub> A | PE8                                      | PE7               | PH7                |
| D | PG9               | PG8               | PG4               | V <sub>SS</sub> X | V <sub>SS</sub> X | V <sub>SS</sub> 2.5 | V <sub>SS</sub> 2.5       | PD10                | PD8                 | PD7                 | V <sub>SS</sub> A | V <sub>SS</sub> A | PH10              | PE9                                      | PE6               | PH6                |
| E | PG6               | PG11              | PG10              | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PE4               | PE5                                      | PH5               | PH4                |
| F | PC0               | PG7               | PC1               | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PE2               | PE3                                      | PH3               | PH2                |
| G | PB0               | PC2               | PC3               | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PH0               | PH1                                      | PE1               | PE0                |
| H | PB3               | PB2               | PB1               | V <sub>DD</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PA8               | PA9                                      | PA7               | PA10               |
| J | PB5               | PB6               | PB4               | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PD5               | PA12                                     | PA11              | PC15               |
| K | PB7               | PB8               | PF15              | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PC13              | PC12                                     | PC14              | V <sub>DD</sub> X  |
| L | PF14              | PF13              | PC4               | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | PD13              | PD14                                     | PD15              | PD4                |
| M | PF12              | PC5               | PC6               | V <sub>SS</sub> X |                   |                     |                           |                     |                     |                     |                   |                   | V <sub>SS</sub> X | $\overline{\text{TA/AS}}$ <sup>(1)</sup> | PD3               | PD2 <sup>(1)</sup> |
| N | PF11              | PF10              | PC7               | V <sub>SS</sub> X | V <sub>SS</sub> R | V <sub>SS</sub> R   | V <sub>SS</sub> 2.5       | V <sub>SS</sub> 2.5 | V <sub>SS</sub> PLL | V <sub>SS</sub> PLL | V <sub>SS</sub> X | V <sub>SS</sub> X | V <sub>SS</sub> X | PB11                                     | PB14              | PB15               |
| P | PF9               | PF8               | V <sub>SS</sub> X | PF5               | PC8               | PC10                | V <sub>DD</sub> X         | V <sub>DD</sub> 2.5 | V <sub>DD</sub> R   | V <sub>DD</sub> X   | PA15              | PD11              | PD12              | V <sub>SS</sub> X                        | PB12              | PB13               |
| R | PF7               | V <sub>SS</sub> X | PF6               | PF3               | PF1               | PC9                 | PG12                      | PG13                | V <sub>SS</sub> X   | V <sub>SS</sub> X   | TEST              | PA13              | PD1               | PB10                                     | V <sub>SS</sub> X | V <sub>SS</sub> X  |
| T | V <sub>SS</sub> X | V <sub>SS</sub> X | PF4               | PF2               | PF0               | PC11                | $\overline{\text{RESET}}$ | V <sub>DD</sub> PLL | XFC                 | EXTAL               | XTAL              | PA14              | PD0               | PB9                                      | V <sub>SS</sub> X | V <sub>SS</sub> X  |

1.  $\overline{\text{AS}}$  and PD2 functions not available on L49P mask set devices.

**Figure 22. Pin Assignments for MAC7131 in 208-pin MAP BGA**



## 4.9 MAC7136 Pin Diagram

|   | 1                 | 2                 | 3    | 4                 | 5                 | 6                   | 7                   | 8                   | 9                   | 10                  | 11                | 12                | 13                | 14                              | 15                | 16                |
|---|-------------------|-------------------|------|-------------------|-------------------|---------------------|---------------------|---------------------|---------------------|---------------------|-------------------|-------------------|-------------------|---------------------------------|-------------------|-------------------|
| A | V <sub>SS</sub> X | V <sub>SS</sub> X | PG0  | PG14              | PA2               | PA5                 | TCK                 | TDI                 | PE15                | PE14                | PH14              | PE12              | PH11              | V <sub>RL</sub>                 | V <sub>RH</sub>   | V <sub>DD</sub> A |
| B | V <sub>SS</sub> X | V <sub>SS</sub> X | PG2  | PG15              | PA0               | PA4                 | TMS                 | TDO                 | PD9                 | PH15                | PE13              | PH12              | PE10              | PH9                             | V <sub>DD</sub> A | PH8               |
| C | PG5               | PG3               | PI0  | PG1               | PA1               | PA3                 | PA6                 | V <sub>DD</sub> 2.5 | V <sub>DD</sub> X   | PD6                 | PH13              | PE11              | V <sub>DD</sub> A | PE8                             | PE7               | PH7               |
| D | PG9               | PG8               | PG4  | PI2               | PI1               | V <sub>SS</sub> 2.5 | V <sub>SS</sub> 2.5 | PD10                | PD8                 | PD7                 | V <sub>SS</sub> A | V <sub>SS</sub> A | PH10              | PE9                             | PE6               | PH6               |
| E | PG6               | PG11              | PG10 | PI3               |                   |                     |                     |                     |                     |                     |                   |                   | PE4               | PE5                             | PH5               | PH4               |
| F | PC0               | PG7               | PC1  | V <sub>SS</sub> X |                   |                     |                     |                     |                     |                     |                   |                   | PE2               | PE3                             | PH3               | PH2               |
| G | PB0               | PC2               | PC3  | PI4               |                   |                     |                     |                     |                     |                     |                   |                   | PH0               | PH1                             | PE1               | PE0               |
| H | PB3               | PB2               | PB1  | V <sub>DD</sub> X |                   |                     |                     |                     |                     |                     |                   |                   | PA8               | PA9                             | PA7               | PA10              |
| J | PB5               | PB6               | PB4  | PI5               |                   |                     |                     |                     |                     |                     |                   |                   | PD5               | PA12                            | PA11              | PC15              |
| K | PB7               | PB8               | PF15 | PI6               |                   |                     |                     |                     |                     |                     |                   |                   | PC13              | PC12                            | PC14              | V <sub>DD</sub> X |
| L | PF14              | PF13              | PC4  | PI7               |                   |                     |                     |                     |                     |                     |                   |                   | PD13              | PD14                            | PD15              | PD4               |
| M | PF12              | PC5               | PC6  | V <sub>SS</sub> X |                   |                     |                     |                     |                     |                     |                   |                   | V <sub>SS</sub> X | $\overline{TA} / \overline{AS}$ | PD3               | PD2               |
| N | PF11              | PF10              | PC7  | PI8               | V <sub>SS</sub> R | V <sub>SS</sub> R   | V <sub>SS</sub> 2.5 | V <sub>SS</sub> 2.5 | V <sub>SS</sub> PLL | V <sub>SS</sub> PLL | PI12              | PI13              | PI14              | PB11                            | PB14              | PB15              |
| P | PF9               | PF8               | PI9  | PF5               | PC8               | PC10                | V <sub>DD</sub> X   | V <sub>DD</sub> 2.5 | V <sub>DD</sub> R   | V <sub>DD</sub> X   | PA15              | PD11              | PD12              | PI15                            | PB12              | PB13              |
| R | PF7               | PI10              | PF6  | PF3               | PF1               | PC9                 | PG12                | PG13                | V <sub>SS</sub> X   | V <sub>SS</sub> X   | TEST              | PA13              | PD1               | PB10                            | PI11              | V <sub>SS</sub> X |
| T | V <sub>SS</sub> X | V <sub>SS</sub> X | PF4  | PF2               | PF0               | PC11                | $\overline{RESET}$  | V <sub>DD</sub> PLL | XFC                 | EXTAL               | XTAL              | PA14              | PD0               | PB9                             | V <sub>SS</sub> X | V <sub>SS</sub> X |

Figure 23. Pin Assignments for MAC7136 in 208-pin MAP BGA

## 5 Mechanical Information

As indicated in [Table 2](#), MAC7100 Family devices are available in several packages. Please refer to the [freescale.com](http://freescale.com) web site for the most up-to-date package availability and mechanical information. The table below lists available package identifiers and Freescale document numbers for reference.

**Table 39. Package Identifiers and Mechanical Specifications**

| Package Type     | Case Identifier | Mechanical Specification Document |
|------------------|-----------------|-----------------------------------|
| 100-lead LQFP    | 983-02          | <a href="#">98ASS23308W</a>       |
| 112-lead LQFP    | 987-02          | <a href="#">98ASS23330W</a>       |
| 144-lead LQFP    | 918-03          | <a href="#">98ASS23177W</a>       |
| 208-lead MAP BGA | 1159A-01        | <a href="#">98ARS23882W</a>       |

## Revision History

| Version No.<br>Release Date                                                  | Description of Changes                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               | Page<br>Numbers                                     |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
|------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------|----------|----------|-------------------------------------------|---------------------------------------------|---------------------------------------------|-------------------------------------------|---------------------------------------------|---------------------------------------------|------------------------------------------------------------------------------|------------------------------------------------------|-----------------------------------------------------|--------------------------------------------------------------------------|---------------------------------------------|----------------------------------------------|--------------------------------------------------------------------------|---------------------------------------------|---------------------|-------------------------------------------|---------------------------------------------|---------------------------------------------|----------------------------------------------------|--------------------------|--------------------------|--------------------------------------------|----------------------------------------------|----------------------------------------------|-------------------------------------|---------------------------------------------|---------------------------------------------|-------------------------------------------|--------------------------|--------------------------|---------------------------------------------------------|--------------------------|--------------------------|---------------------------------------------|---------------------------------------------|---------------------------------------------|----------------------------------------------------------|---------------------------------------------|---------------------------------------------|-----------------------------------------------------------|----------------------------------------------|----------------------------------------------|--------------------------------------------------------------|---------------------------------------------|---------------------------------------------|--------------------------------------------------------------|---------------------------------------------|---------------------------------------------|------------------------------------------------|---------------------------------------------|---------------------------------------------|-----------------------------------------------------------|---------------------------------------------|---------------------------------------------|-----------------------------------------------------------|---------------------------------------------|---------------------------------------------|------------------------------------------------------------|---------------------|---------------------------------------------|------------------------------------------------|---------------------|---------------------------------------------|-------------------------------------------|---------------------|---------------------------------------------|------------------------------------------------------------|---------------------------------------------|---------------------------------------------|--------------------------------------------------------|----------------------------------------------|----------------------------------------------|-------------------------------------------------------|----------------------------------------------|----------------------------------------------|-------------------------------------------------------|---------------------------------------------|---------------------------------------------|--------------------------------------------|---------------------------------------------|---------------------------------------------|-------------------------------------------------|----------------------------------------------|----------------------------------------------|---------------------------------------------------------------------------------------------------------|
| <b>v0.1</b><br><b>29-Oct-03</b>                                              | <b>First public customer release (preliminary).</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                                                     |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <b>v1.0</b><br><b>14-Sep-04</b>                                              | <p><b>General</b></p> <ul style="list-style-type: none"> <li>Converted to Freescale identity, with blue cross-reference highlights for enhanced PDF navigation, and miscellaneous updates for presentation consistency.</li> <li>The order of <a href="#">Section 3.5</a> and <a href="#">Section 3.6</a> were reversed for better content flow. This has caused specification numbering to change as detailed below.</li> </ul> <p><b>Note:</b> Content consolidation and reorganization has resulted in the following table and specification number changes (the first spec number of each table is shown):</p> <table> <tr> <th>Table Title</th><th>Rev. 1.0</th><th>Rev. 0.1</th></tr> <tr> <td><a href="#">5.0 V I/O Characteristics</a></td><td><a href="#">Table 8</a> <a href="#">D1a</a></td><td><a href="#">Table 15</a> <a href="#">F1</a></td></tr> <tr> <td><a href="#">3.3 V I/O Characteristics</a></td><td><a href="#">Table 9</a> <a href="#">E1a</a></td><td><a href="#">Table 16</a> <a href="#">G1</a></td></tr> <tr> <td><a href="#">Section 3.6, "Power Dissipation and Thermal Characteristics"</a></td><td><a href="#">Table 10</a> to <a href="#">Table 14</a></td><td><a href="#">Table 7</a> to <a href="#">Table 11</a></td></tr> <tr> <td><a href="#">MAC71x1/6 Device Supply Current Characteristics – 40 MHz</a></td><td><a href="#">Table 15</a> <a href="#">F1</a></td><td><a href="#">Table 12</a> <a href="#">D1a</a></td></tr> <tr> <td><a href="#">MAC71x1/6 Device Supply Current Characteristics – 50 MHz</a></td><td><a href="#">Table 16</a> <a href="#">G1</a></td><td><a href="#">N/A</a></td></tr> <tr> <td><a href="#">VREG Operating Conditions</a></td><td><a href="#">Table 17</a> <a href="#">H1</a></td><td><a href="#">Table 13</a> <a href="#">E1</a></td></tr> <tr> <td><a href="#">VREG Recommended Load Capacitances</a></td><td><a href="#">Table 18</a></td><td><a href="#">Table 14</a></td></tr> <tr> <td><a href="#">Oscillator Characteristics</a></td><td><a href="#">Table 19</a> <a href="#">J1a</a></td><td><a href="#">Table 17</a> <a href="#">H1a</a></td></tr> <tr> <td><a href="#">PLL Characteristics</a></td><td><a href="#">Table 20</a> <a href="#">K1</a></td><td><a href="#">Table 18</a> <a href="#">J1</a></td></tr> <tr> <td><a href="#">Crystal Monitor Time-Outs</a></td><td><a href="#">Table 21</a></td><td><a href="#">Table 19</a></td></tr> <tr> <td><a href="#">CRG Maximum Clock Quality Check Timings</a></td><td><a href="#">Table 22</a></td><td><a href="#">Table 20</a></td></tr> <tr> <td><a href="#">CRG Startup Characteristics</a></td><td><a href="#">Table 23</a> <a href="#">L1</a></td><td><a href="#">Table 21</a> <a href="#">K1</a></td></tr> <tr> <td><a href="#">External Bus Input Timing Specifications</a></td><td><a href="#">Table 24</a> <a href="#">M1</a></td><td><a href="#">Table 22</a> <a href="#">L1</a></td></tr> <tr> <td><a href="#">External Bus Output Timing Specifications</a></td><td><a href="#">Table 25</a> <a href="#">M6a</a></td><td><a href="#">Table 23</a> <a href="#">L6a</a></td></tr> <tr> <td><a href="#">ATD Operating Characteristics in 5.0 V Range</a></td><td><a href="#">Table 26</a> <a href="#">N1</a></td><td><a href="#">Table 24</a> <a href="#">M1</a></td></tr> <tr> <td><a href="#">ATD Operating Characteristics in 3.3 V Range</a></td><td><a href="#">Table 27</a> <a href="#">P1</a></td><td><a href="#">Table 25</a> <a href="#">N1</a></td></tr> <tr> <td><a href="#">ATD Electrical Characteristics</a></td><td><a href="#">Table 28</a> <a href="#">Q1</a></td><td><a href="#">Table 26</a> <a href="#">P1</a></td></tr> <tr> <td><a href="#">ATD Conversion Performance in 5.0 V Range</a></td><td><a href="#">Table 29</a> <a href="#">R1</a></td><td><a href="#">Table 27</a> <a href="#">Q1</a></td></tr> <tr> <td><a href="#">ATD Conversion Performance in 3.3 V Range</a></td><td><a href="#">Table 30</a> <a href="#">S1</a></td><td><a href="#">Table 28</a> <a href="#">R1</a></td></tr> <tr> <td><a href="#">ATD Electrical Characteristics (Operating)</a></td><td><a href="#">N/A</a></td><td><a href="#">Table 29</a> <a href="#">S1</a></td></tr> <tr> <td><a href="#">ATD Performance Specifications</a></td><td><a href="#">N/A</a></td><td><a href="#">Table 30</a> <a href="#">T1</a></td></tr> <tr> <td><a href="#">ATD Timing Specifications</a></td><td><a href="#">N/A</a></td><td><a href="#">Table 31</a> <a href="#">U1</a></td></tr> <tr> <td><a href="#">ATD External Trigger Timing Specifications</a></td><td><a href="#">Table 31</a> <a href="#">T1</a></td><td><a href="#">Table 32</a> <a href="#">V1</a></td></tr> <tr> <td><a href="#">SPI Master Mode Timing Characteristics</a></td><td><a href="#">Table 32</a> <a href="#">U1a</a></td><td><a href="#">Table 33</a> <a href="#">W1a</a></td></tr> <tr> <td><a href="#">SPI Slave Mode Timing Characteristics</a></td><td><a href="#">Table 33</a> <a href="#">V1a</a></td><td><a href="#">Table 34</a> <a href="#">X1a</a></td></tr> <tr> <td><a href="#">FlexCAN Wake-up Pulse Characteristics</a></td><td><a href="#">Table 34</a> <a href="#">W1</a></td><td><a href="#">Table 35</a> <a href="#">Y1</a></td></tr> <tr> <td><a href="#">CFM Timing Characteristics</a></td><td><a href="#">Table 35</a> <a href="#">X1</a></td><td><a href="#">Table 36</a> <a href="#">Z1</a></td></tr> <tr> <td><a href="#">NVM Reliability Characteristics</a></td><td><a href="#">Table 36</a> <a href="#">X9b</a></td><td><a href="#">Table 37</a> <a href="#">Z10</a></td></tr> </table> <p><b>Section 2, "Ordering Information"</b></p> <ul style="list-style-type: none"> <li>Added <a href="#">Table 1</a>, mask set information</li> <li>Updated <a href="#">Table 2</a> with expanded port pin counts, MAC71x2 and MAC71x6 family members</li> <li>Pin assignment changes for mask set L47W devices: <ul style="list-style-type: none"> <li>In <a href="#">Table 37</a>, PB10 / PCS5_B / PCSS_B changed to pin 57, footnote for L49P</li> </ul> </li> </ul> | Table Title                                         | Rev. 1.0 | Rev. 0.1 | <a href="#">5.0 V I/O Characteristics</a> | <a href="#">Table 8</a> <a href="#">D1a</a> | <a href="#">Table 15</a> <a href="#">F1</a> | <a href="#">3.3 V I/O Characteristics</a> | <a href="#">Table 9</a> <a href="#">E1a</a> | <a href="#">Table 16</a> <a href="#">G1</a> | <a href="#">Section 3.6, "Power Dissipation and Thermal Characteristics"</a> | <a href="#">Table 10</a> to <a href="#">Table 14</a> | <a href="#">Table 7</a> to <a href="#">Table 11</a> | <a href="#">MAC71x1/6 Device Supply Current Characteristics – 40 MHz</a> | <a href="#">Table 15</a> <a href="#">F1</a> | <a href="#">Table 12</a> <a href="#">D1a</a> | <a href="#">MAC71x1/6 Device Supply Current Characteristics – 50 MHz</a> | <a href="#">Table 16</a> <a href="#">G1</a> | <a href="#">N/A</a> | <a href="#">VREG Operating Conditions</a> | <a href="#">Table 17</a> <a href="#">H1</a> | <a href="#">Table 13</a> <a href="#">E1</a> | <a href="#">VREG Recommended Load Capacitances</a> | <a href="#">Table 18</a> | <a href="#">Table 14</a> | <a href="#">Oscillator Characteristics</a> | <a href="#">Table 19</a> <a href="#">J1a</a> | <a href="#">Table 17</a> <a href="#">H1a</a> | <a href="#">PLL Characteristics</a> | <a href="#">Table 20</a> <a href="#">K1</a> | <a href="#">Table 18</a> <a href="#">J1</a> | <a href="#">Crystal Monitor Time-Outs</a> | <a href="#">Table 21</a> | <a href="#">Table 19</a> | <a href="#">CRG Maximum Clock Quality Check Timings</a> | <a href="#">Table 22</a> | <a href="#">Table 20</a> | <a href="#">CRG Startup Characteristics</a> | <a href="#">Table 23</a> <a href="#">L1</a> | <a href="#">Table 21</a> <a href="#">K1</a> | <a href="#">External Bus Input Timing Specifications</a> | <a href="#">Table 24</a> <a href="#">M1</a> | <a href="#">Table 22</a> <a href="#">L1</a> | <a href="#">External Bus Output Timing Specifications</a> | <a href="#">Table 25</a> <a href="#">M6a</a> | <a href="#">Table 23</a> <a href="#">L6a</a> | <a href="#">ATD Operating Characteristics in 5.0 V Range</a> | <a href="#">Table 26</a> <a href="#">N1</a> | <a href="#">Table 24</a> <a href="#">M1</a> | <a href="#">ATD Operating Characteristics in 3.3 V Range</a> | <a href="#">Table 27</a> <a href="#">P1</a> | <a href="#">Table 25</a> <a href="#">N1</a> | <a href="#">ATD Electrical Characteristics</a> | <a href="#">Table 28</a> <a href="#">Q1</a> | <a href="#">Table 26</a> <a href="#">P1</a> | <a href="#">ATD Conversion Performance in 5.0 V Range</a> | <a href="#">Table 29</a> <a href="#">R1</a> | <a href="#">Table 27</a> <a href="#">Q1</a> | <a href="#">ATD Conversion Performance in 3.3 V Range</a> | <a href="#">Table 30</a> <a href="#">S1</a> | <a href="#">Table 28</a> <a href="#">R1</a> | <a href="#">ATD Electrical Characteristics (Operating)</a> | <a href="#">N/A</a> | <a href="#">Table 29</a> <a href="#">S1</a> | <a href="#">ATD Performance Specifications</a> | <a href="#">N/A</a> | <a href="#">Table 30</a> <a href="#">T1</a> | <a href="#">ATD Timing Specifications</a> | <a href="#">N/A</a> | <a href="#">Table 31</a> <a href="#">U1</a> | <a href="#">ATD External Trigger Timing Specifications</a> | <a href="#">Table 31</a> <a href="#">T1</a> | <a href="#">Table 32</a> <a href="#">V1</a> | <a href="#">SPI Master Mode Timing Characteristics</a> | <a href="#">Table 32</a> <a href="#">U1a</a> | <a href="#">Table 33</a> <a href="#">W1a</a> | <a href="#">SPI Slave Mode Timing Characteristics</a> | <a href="#">Table 33</a> <a href="#">V1a</a> | <a href="#">Table 34</a> <a href="#">X1a</a> | <a href="#">FlexCAN Wake-up Pulse Characteristics</a> | <a href="#">Table 34</a> <a href="#">W1</a> | <a href="#">Table 35</a> <a href="#">Y1</a> | <a href="#">CFM Timing Characteristics</a> | <a href="#">Table 35</a> <a href="#">X1</a> | <a href="#">Table 36</a> <a href="#">Z1</a> | <a href="#">NVM Reliability Characteristics</a> | <a href="#">Table 36</a> <a href="#">X9b</a> | <a href="#">Table 37</a> <a href="#">Z10</a> | <p><a href="#">7, 8</a></p> <p><a href="#">2</a></p> <p><a href="#">3</a></p> <p><a href="#">36</a></p> |
| Table Title                                                                  | Rev. 1.0                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | Rev. 0.1                                            |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">5.0 V I/O Characteristics</a>                                    | <a href="#">Table 8</a> <a href="#">D1a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 15</a> <a href="#">F1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">3.3 V I/O Characteristics</a>                                    | <a href="#">Table 9</a> <a href="#">E1a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 16</a> <a href="#">G1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">Section 3.6, "Power Dissipation and Thermal Characteristics"</a> | <a href="#">Table 10</a> to <a href="#">Table 14</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 | <a href="#">Table 7</a> to <a href="#">Table 11</a> |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">MAC71x1/6 Device Supply Current Characteristics – 40 MHz</a>     | <a href="#">Table 15</a> <a href="#">F1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 12</a> <a href="#">D1a</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">MAC71x1/6 Device Supply Current Characteristics – 50 MHz</a>     | <a href="#">Table 16</a> <a href="#">G1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">N/A</a>                                 |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">VREG Operating Conditions</a>                                    | <a href="#">Table 17</a> <a href="#">H1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 13</a> <a href="#">E1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">VREG Recommended Load Capacitances</a>                           | <a href="#">Table 18</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | <a href="#">Table 14</a>                            |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">Oscillator Characteristics</a>                                   | <a href="#">Table 19</a> <a href="#">J1a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <a href="#">Table 17</a> <a href="#">H1a</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">PLL Characteristics</a>                                          | <a href="#">Table 20</a> <a href="#">K1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 18</a> <a href="#">J1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">Crystal Monitor Time-Outs</a>                                    | <a href="#">Table 21</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | <a href="#">Table 19</a>                            |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">CRG Maximum Clock Quality Check Timings</a>                      | <a href="#">Table 22</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | <a href="#">Table 20</a>                            |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">CRG Startup Characteristics</a>                                  | <a href="#">Table 23</a> <a href="#">L1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 21</a> <a href="#">K1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">External Bus Input Timing Specifications</a>                     | <a href="#">Table 24</a> <a href="#">M1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 22</a> <a href="#">L1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">External Bus Output Timing Specifications</a>                    | <a href="#">Table 25</a> <a href="#">M6a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <a href="#">Table 23</a> <a href="#">L6a</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Operating Characteristics in 5.0 V Range</a>                 | <a href="#">Table 26</a> <a href="#">N1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 24</a> <a href="#">M1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Operating Characteristics in 3.3 V Range</a>                 | <a href="#">Table 27</a> <a href="#">P1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 25</a> <a href="#">N1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Electrical Characteristics</a>                               | <a href="#">Table 28</a> <a href="#">Q1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 26</a> <a href="#">P1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Conversion Performance in 5.0 V Range</a>                    | <a href="#">Table 29</a> <a href="#">R1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 27</a> <a href="#">Q1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Conversion Performance in 3.3 V Range</a>                    | <a href="#">Table 30</a> <a href="#">S1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 28</a> <a href="#">R1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Electrical Characteristics (Operating)</a>                   | <a href="#">N/A</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  | <a href="#">Table 29</a> <a href="#">S1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Performance Specifications</a>                               | <a href="#">N/A</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  | <a href="#">Table 30</a> <a href="#">T1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD Timing Specifications</a>                                    | <a href="#">N/A</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  | <a href="#">Table 31</a> <a href="#">U1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">ATD External Trigger Timing Specifications</a>                   | <a href="#">Table 31</a> <a href="#">T1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 32</a> <a href="#">V1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">SPI Master Mode Timing Characteristics</a>                       | <a href="#">Table 32</a> <a href="#">U1a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <a href="#">Table 33</a> <a href="#">W1a</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">SPI Slave Mode Timing Characteristics</a>                        | <a href="#">Table 33</a> <a href="#">V1a</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <a href="#">Table 34</a> <a href="#">X1a</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">FlexCAN Wake-up Pulse Characteristics</a>                        | <a href="#">Table 34</a> <a href="#">W1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 35</a> <a href="#">Y1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">CFM Timing Characteristics</a>                                   | <a href="#">Table 35</a> <a href="#">X1</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | <a href="#">Table 36</a> <a href="#">Z1</a>         |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |
| <a href="#">NVM Reliability Characteristics</a>                              | <a href="#">Table 36</a> <a href="#">X9b</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <a href="#">Table 37</a> <a href="#">Z10</a>        |          |          |                                           |                                             |                                             |                                           |                                             |                                             |                                                                              |                                                      |                                                     |                                                                          |                                             |                                              |                                                                          |                                             |                     |                                           |                                             |                                             |                                                    |                          |                          |                                            |                                              |                                              |                                     |                                             |                                             |                                           |                          |                          |                                                         |                          |                          |                                             |                                             |                                             |                                                          |                                             |                                             |                                                           |                                              |                                              |                                                              |                                             |                                             |                                                              |                                             |                                             |                                                |                                             |                                             |                                                           |                                             |                                             |                                                           |                                             |                                             |                                                            |                     |                                             |                                                |                     |                                             |                                           |                     |                                             |                                                            |                                             |                                             |                                                        |                                              |                                              |                                                       |                                              |                                              |                                                       |                                             |                                             |                                            |                                             |                                             |                                                 |                                              |                                              |                                                                                                         |

## Revision History (continued)

| Version No.<br>Release Date      | Description of Changes                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | Page<br>Numbers |
|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------|
| v1.0<br>14-Sep-04<br>(continued) | <b>Section 3, “Electrical Characteristics”</b> <ul style="list-style-type: none"><li>• <b>Section 3.2, “Absolute Maximum Ratings”</b><ul style="list-style-type: none"><li>— A1a renamed to V<sub>DDX</sub>4</li><li>— A4 “rating” changed to Analog (from ATD)4</li><li>— A9 minimum changed to −0.35</li><li>— A12 maximum value removed, footnote reference added5</li><li>— Table 8, Table 9 footnotes added regarding V<sub>DD5</sub>/V<sub>SS5</sub>7, 8</li></ul></li><li>• <b>Section 3.4, “Operating Conditions”</b><ul style="list-style-type: none"><li>— C1 renamed to V<sub>DDX</sub>6</li><li>— C4 added (C5 to C11b renumbered)6</li><li>— C8 maximum changed from 40 MHz to 50 MHz6</li></ul></li><li>• <b>Section 3.5, “Input/Output Characteristics”</b><ul style="list-style-type: none"><li>— Table 8 spec D4 updated (from TBD)7</li><li>— Table 9 spec E4 changed to 1 μA to match D48</li></ul></li><li>• <b>Section 3.6, “Power Dissipation and Thermal Characteristics”</b><ul style="list-style-type: none"><li>— Reworked Equation 1 through Equation 4 and supporting text9</li><li>— Section 3.6.1 and Table 10 name changed from “Power Dissipation...”10</li></ul></li><li>• <b>Section 3.7, “Power Supply”</b><ul style="list-style-type: none"><li>— Added MAC71x1 designation and footnotes to Table 15 / Table 1612</li><li>— Table 15 designated for 40 MHz, and<ul style="list-style-type: none"><li>– Numerous TBD entries replaced with values</li><li>– Run Supply Current collapsed from fifteen spec items to one</li><li>– Removed separate Core/Regulator/Pins specs for Run/Pseudo Stop/Stop modes</li><li>– F1 and F3 descriptions changed</li><li>– F1, F2, F3 and F4 values updated</li></ul></li><li>— Table 16 added for 50 MHz specifications12</li><li>— Table 17, deleted I<sub>REG</sub> spec (Regulator Current in Reduced Power, Shutdown Modes)13</li><li>— Table 18, V<sub>DD2.5</sub> load capacitance typical changed, with clarification footnote14</li></ul></li><li>• <b>Section 3.8, “Clock and Reset Generator”</b><ul style="list-style-type: none"><li>— Table 19 updates15<ul style="list-style-type: none"><li>– Changed specs J1b and J6 maximum from 40 MHz to 50 MHz</li><li>– Reversed polarity of XCLKS reference in footnote (3)</li><li>– J1b maximum changed to 40 MHz</li><li>– V<sub>DCBIAS</sub> removed</li><li>– Added footnote to define t<sub>fSYS</sub> as 1 ÷ f<sub>SYS</sub> for use elsewhere in the document</li></ul></li><li>— Updated Section 3.8.2, “PLL Filter Characteristics”16</li><li>— Table 20 updates18<ul style="list-style-type: none"><li>– Changed spec K3 maximum from 40 MHz to 50 MHz</li><li>– Added footnote to define t<sub>fSYS</sub> as 1 ÷ f<sub>SYS</sub> for use elsewhere in the document</li></ul></li><li>— Table 23 updates19<ul style="list-style-type: none"><li>– Removed V<sub>PORR</sub> and V<sub>PORA</sub>, as they duplicated H6</li><li>– Removed t<sub>WRS</sub></li></ul></li></ul></li><li>• <b>Section 3.9, “External Bus Timing”</b><ul style="list-style-type: none"><li>— Table 24 updates20<ul style="list-style-type: none"><li>– M1 minimum changed from 25 ns to 20 ns (Figure 6 also updated)</li><li>– Reworded footnote (1)</li><li>– Added footnote (2) to define t<sub>CYC</sub> as 1 ÷ CLKOUT</li></ul></li><li>— Table 25 updates21<ul style="list-style-type: none"><li>– Added footnote (1)</li><li>– Consolidated previous NOTES into footnote (2), (Figure 7, Figure 8 also updated)</li></ul></li></ul></li></ul> |                 |

## Revision History (continued)

| Version No.<br>Release Date      | Description of Changes                                                                                                                                                                                                                       | Page<br>Numbers |
|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------|
| v1.0<br>14-Sep-04<br>(continued) | <b>Section 3, “Electrical Characteristics” (continued)</b>                                                                                                                                                                                   |                 |
|                                  | • <b>Section 3.10, “Analog-to-Digital Converter”</b>                                                                                                                                                                                         | 24              |
|                                  | — Rev. 0.1 redundant and superfluous content deleted                                                                                                                                                                                         |                 |
|                                  | — Section 3.10.3, “ATD Electrical Specifications,” (included Table 29 and Table 30)                                                                                                                                                          |                 |
|                                  | — Table 31, “ATD Performance Specifications” (redundant with v0.1 Table 27 and Table 28, now <a href="#">Table 29</a> and <a href="#">Table 30</a> )                                                                                         |                 |
|                                  | — <a href="#">Table 26</a> updates                                                                                                                                                                                                           | 24              |
|                                  | — Deleted previous spec M6                                                                                                                                                                                                                   |                 |
|                                  | — Changed spec <a href="#">N7</a> and <a href="#">N8</a> values                                                                                                                                                                              |                 |
|                                  | — <a href="#">Table 27</a> updates                                                                                                                                                                                                           | 24              |
|                                  | — Deleted previous spec N6                                                                                                                                                                                                                   |                 |
|                                  | — Changed spec <a href="#">P7</a> and <a href="#">P8</a> values                                                                                                                                                                              |                 |
|                                  | — Changed spec <a href="#">P2</a> and footnote (1) to specify 3.15 V                                                                                                                                                                         |                 |
|                                  | — <a href="#">Table 28</a> updates                                                                                                                                                                                                           | 25              |
|                                  | — Changed spec <a href="#">Q2</a> parameter classification from T to C and 10 pF and 22 pF values moved from maximum to typical                                                                                                              |                 |
|                                  | — <a href="#">Table 29</a> updates                                                                                                                                                                                                           | 26              |
|                                  | — Operating conditions $V_{DDA}$ minimum changed to 4.5 V                                                                                                                                                                                    |                 |
|                                  | — $V_{REF}$ description moved from “conditions” header to new footnote (1)                                                                                                                                                                   |                 |
|                                  | — <a href="#">Table 30</a> updates                                                                                                                                                                                                           | 26              |
|                                  | — Operating conditions $V_{DDA}$ minimum changed to 3.15 V                                                                                                                                                                                   |                 |
|                                  | — $V_{REF}$ description moved from “conditions” header to new footnote (1)                                                                                                                                                                   |                 |
|                                  | — <a href="#">Table 31</a> updates                                                                                                                                                                                                           | 28              |
|                                  | — Spec <a href="#">T1</a> description clarified, max removed, min added with footnote                                                                                                                                                        |                 |
|                                  | — Spec <a href="#">T2</a> modified to show both edge- and level-sensitive modes                                                                                                                                                              |                 |
|                                  | — <a href="#">Figure 10</a> modified to remove “Max Frequency” label and clearly separate edge- and level-sensitive mode timing examples                                                                                                     | 28              |
|                                  | • <b>Section 3.11, “Serial Peripheral Interface”</b>                                                                                                                                                                                         |                 |
|                                  | — <a href="#">Table 32</a> updates                                                                                                                                                                                                           | 29              |
|                                  | — Changed specs <a href="#">U1a</a> , <a href="#">U1b</a> and <a href="#">U4</a> to use $f_{IPS}$ and $t_{IPS}$ for clarity and consistency with MAC7100RM                                                                                   |                 |
|                                  | — Changed <a href="#">U1a</a> max to ½ and <a href="#">U1b</a> min to 2 to account for the DBR bit                                                                                                                                           |                 |
|                                  | — <a href="#">Table 33</a> updates                                                                                                                                                                                                           | 29              |
|                                  | — Changed specs <a href="#">V1a</a> , <a href="#">V1b</a> , <a href="#">V2</a> , <a href="#">V3</a> , <a href="#">V4</a> , <a href="#">V7</a> , <a href="#">V8</a> to use $f_{IPS}$ and $t_{IPS}$ for clarity and consistency with MAC7100RM |                 |
|                                  | — Changed <a href="#">V1a</a> max to ½ and <a href="#">V1b</a> min to 2 to account for the DBR bit                                                                                                                                           |                 |
|                                  | • <b>Section 3.13, “Common Flash Module”</b>                                                                                                                                                                                                 |                 |
|                                  | — Significant rework to match MAC7100RM clock naming, references and timing calculations for clarity and consistency                                                                                                                         | 32 to 35        |
|                                  | — Changed <a href="#">X1</a> maximum from 40 MHz to 50 MHz ( <a href="#">Table 35</a> )                                                                                                                                                      | 34              |

## Revision History (continued)

| Version No.<br>Release Date      | Description of Changes                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | Page<br>Numbers                                                                              |
|----------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------|
| v1.0<br>14-Sep-04<br>(continued) | <b>Section 4, “Device Pin Assignments”</b> <ul style="list-style-type: none"> <li>Table 37 and Table 38 added</li> <li>Added PD2 label / footnote to Figure 15, Figure 17, Figure 19, Figure 20 and Figure 22</li> <li>Section 4.2, “MAC7142 Pin Diagram” / Figure 16 added</li> <li>Section 4.3, “MAC7121 / MAC7126 Pin Diagram” / Figure 17 updated <ul style="list-style-type: none"> <li>PB10 / PCS5_B / PCSS_B bonded out on pin 57, footnote for L49P</li> <li>Added MAC71x6 device information</li> </ul> </li> <li>Section 4.4, “MAC7122 Pin Diagram” / Figure 18 added</li> <li>Section 4.5, “MAC7101 / MAC7106 Pin Diagram” / Figure 19 updated <ul style="list-style-type: none"> <li>Added MAC71x6 device information</li> </ul> </li> <li>Section 4.6, “MAC7111 / MAC7116 Pin Diagram” / Figure 20 updated <ul style="list-style-type: none"> <li>Added AS to TA pin</li> <li>Added MAC71x6 device information</li> </ul> </li> <li>Section 4.7, “MAC7112 Pin Diagram” / Figure 21 added</li> <li>Section 4.8, “MAC7131 Pin Diagram” / Figure 22 corrected, updated <ul style="list-style-type: none"> <li>Changed pins C8 &amp; P8 from V<sub>SS</sub>2.5 to V<sub>DD</sub>2.5</li> <li>Changed pin T8 from V<sub>SS</sub>PLL to V<sub>DD</sub>PLL</li> <li>Added AS to TA pin</li> </ul> </li> <li>Section 4.9, “MAC7136 Pin Diagram” / Figure 23 added</li> </ul> | 36, 40<br>41, 43, 45, 46, 48<br>42<br>43<br><br>44<br>45<br><br>46<br><br>47<br>48<br><br>49 |
| v1.1<br>1-Dec-04                 | <b>Section 3, “Electrical Characteristics”</b> <ul style="list-style-type: none"> <li>Section 3.7, “Power Supply” <ul style="list-style-type: none"> <li>Table 15 spec F4 –40° C and 25° C max value changed</li> <li>Table 16 spec G4 –40° C and 25° C max value changed</li> </ul> </li> <li>Section 3.8, “Clock and Reset Generator” <ul style="list-style-type: none"> <li>Table 19 spec J3 typical TBD entry replaced with value</li> <li>Table 20 specs K15 and K16 maximum TBD entries replaced with values</li> </ul> </li> </ul>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | <br>12<br>12<br><br>15<br>18                                                                 |
| v1.1.1<br>3-Dec-04               | <b>Section 3, “Electrical Characteristics”</b> <ul style="list-style-type: none"> <li>Section 3.7, “Power Supply” <ul style="list-style-type: none"> <li>Table 15 spec F3 –40° C, 25° C and 125° C typ and max values and unit changed</li> <li>Table 16 spec G3 –40° C, 25° C and 125° C typ and max value and unit changed</li> </ul> </li> </ul>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               | <br>12<br>12                                                                                 |
| v1.2<br>10-Feb--06               | <b>Section 1, “Overview”</b> <ul style="list-style-type: none"> <li>Moved 71x6 device numbers from footnote to “covered” list</li> </ul> <b>Section 2, “Ordering Information”</b> <ul style="list-style-type: none"> <li>Added AF, AG and VM package identifiers to Figure 1</li> <li>Added 1L38Y to Table 1</li> </ul> <b>Section 3, “Electrical Characteristics”</b> <ul style="list-style-type: none"> <li>Replaced TBD values in Table 15 and Table 16 with final qualification data, changed table titles and footnotes to reflect 71x6 inclusion.</li> </ul> <b>Section 5, “Mechanical Information”</b> <ul style="list-style-type: none"> <li>Removed obsolete package diagrams, replaced with document IDs available on web site.</li> </ul>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | 1<br><br>2<br>2<br><br>12<br><br>50                                                          |



**This page intentionally left blank.**

## How to Reach Us:

### Home Page:

[www.freescale.com](http://www.freescale.com)

### E-mail:

[support@freescale.com](mailto:support@freescale.com)

### USA/Europe or Locations Not Listed:

Freescale Semiconductor  
Technical Information Center, CH370  
1300 N. Alma School Road  
Chandler, Arizona 85224  
+1-800-521-6274 or +1-480-768-2130  
[support@freescale.com](mailto:support@freescale.com)

### Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH  
Technical Information Center  
Schatzbogen 7  
81829 Muenchen, Germany  
+44 1296 380 456 (English)  
+46 8 52200080 (English)  
+49 89 92103 559 (German)  
+33 1 69 35 48 48 (French)  
[support@freescale.com](mailto:support@freescale.com)

### Japan:

Freescale Semiconductor Japan Ltd.  
Headquarters  
ARCO Tower 15F  
1-8-1, Shimo-Meguro, Meguro-ku,  
Tokyo 153-0064  
Japan  
0120 191014 or +81 3 5437 9125  
[support.japan@freescale.com](mailto:support.japan@freescale.com)

### Asia/Pacific:

Freescale Semiconductor Hong Kong Ltd.  
Technical Information Center  
2 Dai King Street  
Tai Po Industrial Estate  
Tai Po, N.T., Hong Kong  
+800 2666 8080  
[support.asia@freescale.com](mailto:support.asia@freescale.com)

### For Literature Requests Only:

Freescale Semiconductor Literature Distribution Center  
P.O. Box 5405  
Denver, Colorado 80217  
1-800-441-2447 or 303-675-2140  
Fax: 303-675-2150  
[LDCForFreescaleSemiconductor@hibbertgroup.com](mailto:LDCForFreescaleSemiconductor@hibbertgroup.com)

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

Freescale™ and the Freescale logo are trademarks of Freescale Semiconductor, Inc. The ARM POWERED logo is a registered trademark of ARM Limited. ARM7TDMI-S is a trademark of ARM Limited. All other product or service names are the property of their respective owners.

RoHS-compliant and/or Pb-free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb-free counterparts. For further information, see [www.freescale.com](http://www.freescale.com) or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to [www.freescale.com/epp](http://www.freescale.com/epp).

© Freescale Semiconductor, Inc. 2004-2006. All rights reserved.