

NC7SZ14

TinyLogic™ UHS Inverter with Schmitt Trigger Input

General Description

The NC7SZ14 is a single Inverter with Schmitt Trigger input from Fairchild's Ultra High Speed Series of TinyLogic™. The device is fabricated with advanced CMOS technology to achieve ultra high speed with high output drive while maintaining low static power dissipation over a very broad V_{CC} operating range. The device is specified to operate over the 1.65V to 5.5V V_{CC} range. The input and output are high impedance when V_{CC} is 0V. Inputs tolerate voltages up to 6V independent of V_{CC} operating voltage.


Features

- Space saving SOT23 or SC70 5-lead package
- Ultra High Speed; t_{PD} 3.7 ns Typ into 50 pF at 5V V_{CC}
- High Output Drive; ± 24 mA at 3V V_{CC}
- Broad V_{CC} Operating Range; 1.65V to 5.5V
- Matches the performance of LCX when operated at 3.3V V_{CC}
- Power down high impedance inputs/output
- Overvoltage Tolerant inputs facilitate 5V to 3V translation
- Patented noise/EMI reduction circuitry implemented


Ordering Code:

Order Number	Package Number	Product Code Top Mark	Package Description	Supplied As
NC7SZ14M5	MA05B	7Z14	5-Lead SOT23, JEDEC MO-178, 1.6mm	250 Units on Tape and Reel
NC7SZ14M5X	MA05B	7Z14	5-Lead SOT23, JEDEC MO-178, 1.6mm	3k Units on Tape and Reel
NC7SZ14P5	MAA05A	Z14	5-Lead SC70, EIAJ SC-88a, 1.25mm Wide	250 Units on Tape and Reel
NC7SZ14P5X	MAA05A	Z14	5-Lead SC70, EIAJ SC-88a, 1.25mm Wide	3k Units on Tape and Reel

Logic Symbol



Connection Diagram



Pin Descriptions

Pin Names	Description
A	Input
Y	Output
NC	No Connect

Function Table

$Y = \bar{A}$	
Input	Output
A	Y
L	H
H	L

H = HIGH Logic Level
L = LOW Logic Level

TinyLogic™ is a trademark of Fairchild Semiconductor Corporation.

Absolute Maximum Ratings(Note 1)

Supply Voltage (V_{CC})	−0.5V to +6V		Supply Voltage Operating (V_{CC})	1.65V to 5.5V
DC Input Voltage (V_{IN})	−0.5V to +6V		Supply Voltage Data Retention (V_{CC})	1.5V to 5.5V
DC Output Voltage (V_{OUT})	−0.5V to +6V		Input Voltage (V_{IN})	0V to 5.5V
DC Input Diode Current (I_{IK})	@ $V_{IN} < -0.5V$	−50 mA	Output Voltage (V_{OUT})	0V to V_{CC}
		+20 mA	Operating Temperature (T_A)	−40°C to +85°C
DC Output Diode Current (I_{OK})	@ $V_{OUT} < -0.5V$	−50 mA	Thermal Resistance (θ_{JA})	300°C/W
		+20 mA	SOT23-5	425°C/W
DC Output Current (I_{OUT})	±50 mA		SC70-5	
DC V_{CC}/GND Current (I_{CC}/I_{GND})	±50 mA			
Storage Temperature (T_{STG})	−65°C to +150°C			
Junction Temperature under Bias (T_J)	150°C			
Junction Lead Temperature (T1); (Soldering, 10 seconds)	260°C			
Power Dissipation (P_D) @ +85°C	200 mW			
SOT23-5	150 mW			
SC70-5				

Recommended Operating Conditions(Note 2)

Supply Voltage Operating (V_{CC})	1.65V to 5.5V
Supply Voltage Data Retention (V_{CC})	1.5V to 5.5V
Input Voltage (V_{IN})	0V to 5.5V
Output Voltage (V_{OUT})	0V to V_{CC}
Operating Temperature (T_A)	−40°C to +85°C
Thermal Resistance (θ_{JA})	
SOT23-5	300°C/W
SC70-5	425°C/W

Note 1: Absolute maximum ratings are DC values beyond which the device may be damaged or have its useful life impaired. The datasheet specification should be met, without exception, to ensure that the system design is reliable over its power supply, temperature, and output/input loading variables. Fairchild does not recommend operation outside datasheet specifications.

Note 2: Unused inputs must be held HIGH or LOW. They may not float.

DC Electrical Characteristics

Symbol	Parameter	V_{CC} (V)	$T_A = +25^\circ C$			Unit	Conditions
			Min	Typ	Max		
V_P	Positive Threshold Voltage	1.65	0.6	1.0	1.4	V	
		1.8	0.7	1.1	1.5		
		2.3	1.0	1.4	1.8		
		3.0	1.3	1.75	2.2		
		4.5	1.9	2.45	3.1		
		5.5	2.2	2.9	3.6		
V_N	Negative Threshold Voltage	1.65	0.2	0.5	0.8	V	
		1.8	0.25	0.55	0.9		
		2.3	0.40	0.75	1.15		
		3.0	0.6	1.0	1.5		
		4.5	1.0	1.43	2.0		
		5.5	1.2	1.70	2.3		
V_H	Hysteresis Voltage	1.65	0.1	0.48	0.9	V	
		1.8	0.15	0.54	1.0		
		2.3	0.25	0.65	1.1		
		3.0	0.4	0.77	1.2		
		4.5	0.6	1.01	1.5		
		5.5	0.7	1.18	1.7		
V_{OH}	HIGH Level Output Voltage	1.65	1.55	1.65	1.55	V	$V_{IN} = V_{IL}$
		1.8	1.7	1.8	1.7		
		2.3	2.2	2.3	2.2		
		3.0	2.9	3.0	2.9		
		4.5	4.4	4.5	4.4		
	1.65	1.29	1.52	1.29	1.29	V	$I_{OH} = -100 \mu A$
		2.3	1.9	2.15	1.9		
		3.0	2.4	2.80	2.4		
		3.0	2.3	2.68	2.3		
		4.5	3.8	4.20	3.8		

DC Electrical Characteristics (Continued)

Symbol	Parameter	V_{CC} (V)	$T_A = +25^\circ C$			Unit	Conditions			
			Min	Typ	Max					
V_{OL}	LOW Level Output Voltage	1.65	0.0	0.1	0.1	V	$V_{IN} = V_{IH}$	$I_{OL} = 100 \mu A$		
		1.8	0.0	0.1	0.1					
		2.3	0.0	0.1	0.1					
		3.0	0.0	0.1	0.1					
		4.5	0.0	0.1	0.1					
	1.65	0.08	0.24	0.24	V		$I_{OL} = 4 mA$			
		2.3	0.10	0.3						
		3.0	0.15	0.4						
		3.0	0.22	0.55						
		4.5	0.22	0.55						
I_{IN}	Input Leakage Current	0 to 5.5		± 1	± 10	μA	$V_{IN} = 5.5V, GND$			
I_{OFF}	Power Off Leakage Current	0.0		1	10	μA	V_{IN} or $V_{OUT} = 5.5V$			
I_{CC}	Quiescent Supply Current	1.65 to 5.5		2.0	20	μA	$V_{IN} = 5.5V, GND$			


AC Electrical Characteristics

Symbol	Parameter	V_{CC} (V)	$T_A = +25^\circ C$			Unit	Conditions	Fig. No.
			Min	Typ	Max			
t_{PLH}, t_{PHL}	Propagation Delay	1.65	2.0	9.1	15.0	ns	$C_L = 15 pF, R_L = 1 M\Omega$	Figures 1, 3
		1.8	2.0	7.6	12.5			
		2.5 ± 0.2	1.0	5.0	9.0			
		3.3 ± 0.3	1.0	3.7	6.3			
		5.0 ± 0.5	0.5	3.1	5.2			
t_{PLH}, t_{PHL}	Propagation Delay	3.3 ± 0.3	1.5	4.4	7.2	ns	$C_L = 50 pF, R_L = 500\Omega$	Figures 1, 3
		5.0 ± 0.5	0.8	3.7	5.9			
C_{IN}	Input Capacitance	0		4		pF		
C_{PD}	Power Dissipation	3.3		24		pF	(Note 3)	Figure 2
	Capacitance	5.0		30				

Note 3: C_{PD} is defined as the value of the internal equivalent capacitance which is derived from dynamic operating current consumption (I_{CCD}) at no output loading and operating at 50% duty cycle. (See Figure 2.) C_{PD} is related to I_{CCD} dynamic operating current by the expression:

$$I_{CCD} = (C_{PD}) / (V_{CC}) (f_{IN}) + (I_{CC} \text{ static})$$


AC Loading and Waveforms



C_L includes load and stray capacitance

Input PRR = 1.0 MHz; $t_w = 500$ ns

FIGURE 1. AC Test Circuit



Input = AC Waveform; $t_r = t_f = 1.8$ ns

PRR = 10 MHz; Duty Cycle = 50%

FIGURE 2. I_{CCD} Test Circuit





FIGURE 3. AC Waveforms

Tape and Reel Specification

TAPE FORMAT

Package Designator	Tape Section	Number Cavities	Cavity Status	Cover Tape Status
M5, P5	Leader (Start End)	125 (typ)	Empty	Sealed
	Carrier	250	Filled	Sealed
	Trailer (Hub End)	75 (typ)	Empty	Sealed
M5X, P5X	Leader (Start End)	125 (typ)	Empty	Sealed
	Carrier	3000	Filled	Sealed
	Trailer (Hub End)	75 (typ)	Empty	Sealed


TAPE DIMENSIONS inches (millimeters)



Package	Tape Size	DIM A	DIM B	DIM F	DIM K _o	DIM P1	DIM W
SC70-5	8 mm	0.093 (2.35)	0.096 (2.45)	0.138 ± 0.004 (3.5 ± 0.10)	0.053 ± 0.004 (1.35 ± 0.10)	0.157 (4)	0.315 ± 0.004 (8 ± 0.1)
SOT23-5	8 mm	0.130 (3.3)	0.130 (3.3)	0.138 ± 0.002 (3.5 ± 0.05)	0.055 ± 0.004 (1.4 ± 0.11)	0.157 (4)	0.315 ± 0.012 (8 ± 0.3)

NC75Z14


Tape and Reel Specification (Continued)
REEL DIMENSIONS inches (millimeters)





Tape Size	A (mm)	B (mm)	C (mm)	D (mm)	N (mm)	W1 (mm)	W2 (mm)	W3 (mm)
8 mm	7.0 (177.8)	0.059 (1.50)	0.512 (13.00)	0.795 (20.20)	2.165 (55.00)	$0.331 + 0.059/-0.000$ (8.40 + 1.50/-0.00)	0.567 (14.40)	$W1 + 0.078/-0.039$ $(W1 + 2.00/-1.00)$

NC7SZ14

Physical Dimensions inches (millimeters) unless otherwise noted



LAND PATTERN RECOMMENDATION




NOTES: UNLESS OTHERWISE SPECIFIED
A) THIS PACKAGE CONFORMS TO JEDEC
MO-178, ISSUE B, VARIATION AA,
DATED JANUARY 1999.
B) ALL DIMENSIONS ARE IN MILLIMETERS.

MA05BRevC

DETAIL A

5-Lead SOT23, JEDEC MO-178, 1.6mm
Package Number MA05B

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



NOTES:

A. CONFORMS TO EIAJ REGISTERED OUTLINE DRAWING SC88A.

B. DIMENSIONS DO NOT INCLUDE BURRS OR MOLD FLASH.

C. DIMENSIONS ARE IN MILLIMETERS.

MAA05ARevC

**5-Lead SC70, EIAJ SC-88a, 1.25mm Wide
Package Number MAA05A**

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com