# BTA204S series B and C

BTA204M series B and C

### **GENERAL DESCRIPTION**

# Passivated high commutation triacs in a plastic envelope suitable for surface mounting intended for use in circuits where high static and dynamic dV/dt and high dl/dt can occur. These devices will commutate the full rated rms current at the maximum rated junction temperature without the aid of a snubber.


### **QUICK REFERENCE DATA**

SYMBOL	PARAMETER	MAX.	MAX.	MAX.	UNIT
V <sub>DRM</sub> I <sub>T(RMS)</sub> I <sub>TSM</sub>	BTA204S (or BTA204M)- BTA204S (or BTA204M)- Repetitive peak off-state voltages RMS on-state current Non-repetitive peak on-state current	500B 500C 500 4 25	600B 600C 600 4 25	800B 800C 800 4 25	V A A


### **PINNING - SOT428**

PIN NUMBER	Standard S	Alternative M
1	MT1	gate
2	MT2	MT2
3	gate	MT1
tab	MT2	MT2

## **PIN CONFIGURATION**



### **SYMBOL**



### LIMITING VALUES

Limiting values in accordance with the Absolute Maximum System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.			UNIT
$V_{DRM}$	Repetitive peak off-state voltages			<b>-500</b> 500 <sup>1</sup>	<b>-600</b> 600 <sup>1</sup>	<b>-800</b> 800	V
I <sub>T(RMS)</sub>	RMS on-state current	full sine wave;	-		4		Α
I <sub>TSM</sub>	Non-repetitive peak on-state current	$T_{mb} \le 107$ °C full sine wave; $T_{j} = 25$ °C prior to surge $t = 20$ ms	1		25		A
l <sup>2</sup> t	I <sup>2</sup> t for fusing	t = 16.7 ms t = 10 ms	-		27 3.1		A A <sup>2</sup> s
dl <sub>⊤</sub> /dt	Repetitive rate of rise of on-state current after triggering	$I_{TM} = 6 \text{ A}; I_G = 0.2 \text{ A}; $ $dI_G/dt = 0.2 \text{ A}/\mu\text{s}$		100		Α/με	
I <sub>GM</sub> V <sub>GM</sub> P <sub>GM</sub> P <sub>G(AV)</sub>	Peak gate current Peak gate voltage Peak gate power Average gate power	over any 20 ms			2 5 5 0.5		A V W W
$T_{stg}$	Storage temperature Operating junction temperature	period	-40 -	150 125		°C °C	

December 1998 1 Rev 1.000

<sup>1</sup> Although not recommended, off-state voltages up to 800V may be applied without damage, but the triac may switch to the on-state. The rate of rise of current should not exceed 6 A/µs.

BTA204S series B and C BTA204M series B and C

## THERMAL RESISTANCES

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
$R_{th\ j\text{-mb}}$ $R_{th\ j\text{-a}}$	Thermal resistance junction to mounting base Thermal resistance junction to ambient	full cycle half cycle pcb (FR4) mounted; footprint as in Fig.2	1 1 1	- - 75	3.0 3.7 -	K/W K/W K/W

# STATIC CHARACTERISTICS

 $T_i = 25$  °C unless otherwise stated

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.		UNIT
		BTA204 (or BTA204M)-			B	C	
I <sub>GT</sub>	Gate trigger current <sup>2</sup>	$V_D = 12 \text{ V}; I_T = 0.1 \text{ A}$					
		T2+ G+	-	-	50	35	mA
		T2+ G-	-	-	50	35	mA
		T2- G-	-	-	50	35	mA
I <sub>L</sub>	Latching current	$V_D = 12 \text{ V}; I_{GT} = 0.1 \text{ A}$					
		T2+ G+	-	-	30	20	mA
		T2+ G-	-	-	45	30	mA
		T2- G-	-	-	30	20	mA
I <sub>H</sub>	Holding current	$V_D = 12 \text{ V}; I_{GT} = 0.1 \text{ A}$	-	-	30	20	mA
$V_{T}$	On-state voltage	$I_T = 5 A$	-	1.4	1.	.7	V
V <sub>GT</sub>	Gate trigger voltage	$\dot{V}_{D} = 12 \text{ V}; I_{T} = 0.1 \text{ A}$	-	0.7	1.	.5	V
		$V_D = 400 \text{ V}; I_T = 0.1 \text{ A};$	0.25	0.4		-	V
1,	Off-state leakage current	$T_j = 125  ^{\circ}\text{C}$ $V_D = V_{DRM(max)}; T_j = 125  ^{\circ}\text{C}$	_	0.1	0.	5	mA
I <sub>D</sub>	On-State leakage current	$v_D - v_{DRM(max)}, I_j = 125 C$		0.1	U	.5	шА

# **DYNAMIC CHARACTERISTICS**

 $T_i = 25$  °C unless otherwise stated

1						
SYMBOL	PARAMETER	CONDITIONS		MIN.		UNIT
		BTA204S (or BTA204M)-	В	C		
dV <sub>D</sub> /dt	Critical rate of rise of off-state voltage	V <sub>DM</sub> = 67% V <sub>DRM(max)</sub> ; T <sub>j</sub> = 125 °C; exponential waveform; gate open circuit	1000	1000	-	V/μs
dl <sub>com</sub> /dt	Critical rate of change of commutating current	$V_{DM} = 400 \text{ V; } T_i = 125 \text{ °C; } I_{T(RMS)} = 4 \text{ A;}$ $dV_{com}/dt = 20 \text{ V/}\mu\text{s; gate open circuit}$	6	3	-	A/ms
t <sub>gt</sub>	Gate controlled turn-on time	$I_{TM} = 12 \text{ A}; V_D = V_{DRM(max)}; I_G = 0.1 \text{ A}; \\ dI_G/dt = 5 \text{ A}/\mu\text{s}$	-	-	2	μs

December 1998 2 Rev 1.000

<sup>2</sup> Device does not trigger in the T2-, G+ quadrant.

# BTA204S series B and C BTA204M series B and C




Fig.1. Maximum on-state dissipation,  $P_{tot}$ , versus rms on-state current,  $I_{T(RMS)}$ , where  $\alpha =$  conduction angle.




Fig.4. Maximum permissible rms current  $I_{T(RMS)}$ , versus mounting base temperature  $T_{mb}$ .




Fig.2. Maximum permissible non-repetitive peak on-state current  $I_{TSM}$ , versus pulse width  $t_p$ , for sinusoidal currents,  $t_p \le 20$ ms.




Fig.5. Maximum permissible repetitive rms on-state current  $I_{T(RMS)}$ , versus surge duration, for sinusoidal currents, f = 50 Hz;  $T_{mb} \le 107$  °C.




Fig.3. Maximum permissible non-repetitive peak on-state current  $I_{TSM}$ , versus number of cycles, for sinusoidal currents, f = 50 Hz.








Fig.6. Normalised gate trigger voltage  $V_{GT}(T_j)/V_{GT}(25^{\circ}C)$ , versus junction temperature  $T_j$ .

# BTA204S series B and C BTA204M series B and C














Fig.9. Normalised holding current  $I_H(T_i)/I_H(25^{\circ}C)$ , versus junction temperature  $T_i$ .

BTA204S series B and C BTA204M series B and C

## **MECHANICAL DATA**



## **MOUNTING INSTRUCTIONS**



### **Notes**

1. Plastic meets UL94 V0 at 1/8".

BTA204S series B and C BTA204M series B and C

#### **DEFINITIONS**

Data sheet status					
Objective specification	This data sheet contains target or goal specifications for product development.				
Preliminary specification This data sheet contains preliminary data; supplementary data may be published la					
Product specification This data sheet contains final product specifications.					

#### Limiting values

Limiting values are given in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of this specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

#### **Application information**

Where application information is given, it is advisory and does not form part of the specification.

## © Philips Electronics N.V. 1998

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.

The information presented in this document does not form part of any quotation or contract, it is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent or other industrial or intellectual property rights.

#### LIFE SUPPORT APPLICATIONS

These products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.