

Bipolar Power Transistors**Darlington Power Transistors (Continued)**

Type No.	I _C A	V _{CEO} V	h _{FE}		P _T W	JEDEC Package	
			I _C A	V _{CE} V			
2N6385 FAMILY (n-p-n)			Complementary to 2N6650 Family				
2N6383	10	40	1000 min.	5	3	100	TO-204AA/ TO-3
BDX83	10	45	1000 min.	5	3	125	
2N6055	8	60	750 min.	4	3	100	
2N6384	10	60	1000 min.	5	3	100	
2N6576	15	60	2000 min.	4	3	120	
BDX83A	10	60	1000 min.	5	3	125	
RCA1000	5	60	1000 min.	3	3	90	
2N6056	8	80	750 min.	4	3	100	
2N6385	10	80	1000 min.	5	3	100	
BDX83B	10	80	1000 min.	5	3	125	
RCA1001	5	80	1000 min.	3	3	90	
2N6577	15	90	2000 min.	4	3	120	
BDX83C	10	100	1000 min.	5	3	125	
2N6578	15	120	2000 min.	4	3	120	
2N6388 FAMILY (n-p-n)			Complementary to 2N6666 Family				
2N6386	8	40	1000 min.	3	3	65	TO-220AB
BDX53	8	45	750 min.	3	3	60	
BD643	8	45	750 min.	3	3	62.5	
BD895, A	8	45	750 min.	3	3	70	
BDX33	10	45	750 min.	4	3	70	
BDX53A	8	60	750 min.	3	3	60	
BD645	8	60	750 min.	3	3	62.5	
BD897, A	8	60	750 min.	3	3	70	
2N6043	8	60	1000 min.	4	4	75	
2N6387	10	60	1000 min.	5	3	65	
BDX33A	10	60	750 min.	4	3	70	
TIP100	8	60	1000 min.	3	4	80	
TIP120	8	60	1000 min.	3	3	65	
2N6044	8	80	1000 min.	4	4	75	
2N6388	10	80	1000 min.	5	3	65	
BDX33B	10	80	750 min.	3	3	70	
TP101	8	80	1000 min.	3	4	80	
TP121	8	80	1000 min.	3	3	65	
BDX53B	8	80	750 min.	3	3	60	
BD647	8	80	750 min.	3	3	62.5	
BD899, A	8	80	750 min.	3	3	70	
2N6045	8	100	1000 min.	4	4	75	
BDX33C	10	100	750 min.	3	3	70	
TIP102	8	100	1000 min.	3	4	80	
TIP122	8	100	1000 min.	3	3	65	
BDX53C	8	100	750 min.	3	3	60	
BD901	8	100	750 min.	3	3	70	
BDX33D	10	120	750 min.	3	3	70	
2N6530 FAMILY (n-p-n)							
2N6530	8	80	1000-10,000	5	3	65	TO-220AB
2N6531	8	100	500-10,000	3	3	65	
2N6532	8	100	1000-10,000	5	3	65	
2N6533	8	120	1000-10,000	3	3	65	