

# SILICON TRANSISTOR 2SC3518-Z

# NPN SILICON EPITAXIAL TRANSISTOR MP-3

## **DESCRIPTION**

2SC3518-Z is designed for Audio Frequency Amplifier and Switching, especially in Hybrid Integrated Circuits.

#### **FEATURES**

- High DC Current Gain hre = 100 to 400
- Low VCE(sat): VCE(sat) = 0.09 V TYP.
- Complement to 2SA1385-Z

## **QUALITY GRADE**


Standard

Please refer to "Quality grade on NEC Semiconductor Devices" (Document number IEI-1209) published by NEC Corporation to know the specification of quality grade on the devices and its recommended applications.

# ABSOLUTE MAXIMUM RATINGS (Ta = 25 °C)

Collector to Base Voltage	Vсво	60	٧
Collector to Emitter Voltage	VCEO	60	٧
Emitter to Base Voltage	VEBO	7	٧
Collector Current (DC)	lc ·	5	Α
Collector Current (Pulse)*	Ic	7	Α
Total Power Dissipation (Ta = 25 °C)**	Рт	2.0	W
Junction Temperature	$T_{j}$	150	°C
Storage Temperature	Tstg	-55 to +150	°C

- PW ≤ 10 ms, Duty Cycle ≤ 50 %
- \*\* When mounted on ceramic substrate of 7.5 cm $^2 imes 0.7$  mm





# ELECTRICAL CHARACTERISTICS (Ta = 25 °C)


CHARACTERISTIC	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS
Collector Cutoff Current	Ісво			10	μА	VcB = 50 V, IE = 0
Emitter Cutoff Current	IEBO			10	μА	VEB = 7.0 V, Ic = 0
DC Current Gain	hFE1*	100		400		VCE = 1.0 V, IC = 2.0 A
DC Current Gain	hFE2*	50				VcE = 1.0 V, lc = 5.0 A
Collector Saturation Voltage	VCE(sat)*			0.3	V	Ic = 2.0 A, IB = 0.2 A
Base Saturation Voltage	VBE(sat)*			1.2	v	Ic = 2.0 A, IB = 0.2 A
Gain Bandwidth Product	fr*		120		MHz	VcE = 10 V, IE = 500 mA
Turn-on Time	ton		0.07	1.0	μs	Ic = 2.0 A, Vcc = 10 V
Storage Time	tstg	-	0.8	2.5	μs	RL = 5.0 Ω
Fall Time	tr		0.12	1.0	μs	

<sup>\*</sup> Pulsed: PW ≤ 350 μs, Duty Cycle ≤ 2 %


#### hre Classification

MARKING	М	L	К
hFE1	100 to 200	160 to 320	200 to 400


# TYPICAL CHARACTERISTICS (Ta = 25 °C)









SAFE OPERATING AREA





VcE - Collector to Emitter Voltage - V





Vce - Collector to Emitter Voltage - V














#### Reference

Application note name	No.
Quality control of NEC semiconductors devices.	TEI-1202
Quality control guide of semiconductors devices.	MEI-1202
Assembly manual of semiconductors devices.	IEI-1207
Design of Push-Pull Type Switching Regulators (Basic)	TEB-1002
Design of Push-Pull Type Switching Regulators (Applications)	TEB-1003
Optimum Base Drive Conditions of Switching Power Transistors	TEB-1014

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Corporation.NEC Corporation assumes no responsibility for any errors which may appear in this document.

NEC Corporation does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from use of a device described herein or any other liability arising from use of such device. No license, either express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Corporation or others.

The devices listed in this document are not suitable for use in aerospace equipment, submarine cables, nuclear reactor control systems and life support systems. If customers intend to use NEC devices for above applications or they intend to use "Standard" quality grade NEC devices for applications not intended by NEC, please contact our sales people in advance.

Application examples recommended by NEC Corporation.

Standard: Computer, Office equipment, Communication equipment, Test and Measurement equipment, Machine tools, Industrial robots, Audio and Visual equipment, Other consumer products, etc.

Special: Automotive and Transportation equipment, Traffic control systems, Antidisaster systems, Anticrime systems, etc.

M4 92.6