


AC Voltage Sensor


E-312A-I 2PDT, 10 Amps, 440 VAC

Features:

- 2PDT Main Contacts
- Hermetically Sealed
- Three Phase Voltage Sensor
- 440 VAC, 400 Hz, 3Ø Operation
- 10 Amps
- High Reliability
- Meets many requirements of MIL-R-6106



CONTACTOR CONFIGURATION



Dimensions for this product are expressed in inches.	
Multiply values by 25.4 for millimeters.	

PRODUCT SPECIFICATIONS		
Input Voltage	440, 400 Hz	
Trip Voltage	480 ±2% VAC (3 Ø Average) at 25°C	
Reset Voltage	0 Volts Input	
Time Delay 5V Above Trip	0.5 to 1.5 Second	
Time Delay at 500 VAC	.6 ±.15 Second	
Contacts	2PDT, Hermetically Sealed 10 Amps Resistive at 28 VDC 10 Amps Resistive at 115 VAC 0.1 Amp Inductive at 115 VDC with Transient of 0.75 Amp for 60 M Second	
Temperature	0°C to 65°C	
Weight	15 Oz.	

Notes:

For factory-direct application assistance, contact the HARTMAN product team at (419) 521-9500, Fax (419) 526-2749.

© 2004 by Tyco Electronics Corporation. All Rights Reserved. HARTMAN and TYCO are trademarks.

Catalog (web doc only)	Di
Revised 5-04	m
	sr

www.tycoelectronics.com

Dimensions are in inches and millimeters unless otherwise specified. Values in brackets are metric equivalents. Dimensions are shown for reference purposes only. Specifications subject to change. USA: 1-800-522-6752 Canada: 1-905-470-4425 Mexico: 01-800-733-8926 C. America: 52-55-5-729-0425 South America: 55-11-3611-1514 Hong Kong: 852-2735-1628 Japan: 81-44-844-8013 UK: 44-141-810-8967